

## **OsmoBSC VTY Reference**

Copyright © 2012-2019

This work is copyright by sysmocom - s.f.m.c. GmbH. All rights reserved.

**COLLABORATORS**

	<i>TITLE :</i> OsmoBSC VTY Reference		
<i>ACTION</i>	<i>NAME</i>	<i>DATE</i>	<i>SIGNATURE</i>
WRITTEN BY		September 25, 2021	

**REVISION HISTORY**

NUMBER	DATE	DESCRIPTION	NAME
v1	13th August 2012	Initial	hf
v2	5th March 2014	Update to match osmo-bsc version 0.13.0-305	hf
v3	6th June 2019	Update to match osmo-bsc version 1.4.0.84-3f1f	dw

# Contents

<b>1</b>	<b>VTY reference</b>	<b>1</b>
1.1	Common Commands	1
1.1.1	end	2
1.1.2	exit	2
1.1.3	help	2
1.1.4	list [with-flags]	2
1.1.5	show running-config	3
1.1.6	show vty-attributes	3
1.1.7	show vty-attributes (application library global)	3
1.1.8	write	4
1.1.9	write file [PATH]	4
1.1.10	write memory	4
1.1.11	write terminal	4
1.2	view	5
1.2.1	enable [expert-mode]	5
1.2.2	logging color (0 1)	5
1.2.3	logging disable	5
1.2.4	logging enable	6
1.2.5	logging filter all (0 1)	6
1.2.6	logging filter imsi IMSI	6
1.2.7	logging level (r l m m l r l r s l n m p a g m e a s m s c h o h d e c r e f c t r l f l t e r p c u l l c l s c ...	7
1.2.8	logging level force-all (debug info notice error fatal)	10
1.2.9	logging level set-all (debug info notice error fatal)	10
1.2.10	logging print category (0 1)	11
1.2.11	logging print category-hex (0 1)	11
1.2.12	logging print extended-timestamp (0 1)	12
1.2.13	logging print file (0 1 basename) [last]	12
1.2.14	logging print level (0 1)	13
1.2.15	logging print thread-id (0 1)	13
1.2.16	logging set-log-mask MASK	14

1.2.17	logging timestamp (0 1)	14
1.2.18	logp (rlllmmllrrllrslnmlpaglmeaslm sclholhodeclreflectrlfilterlpcullclslchanltslas...	14
1.2.19	no logging level force-all	17
1.2.20	show alarms	18
1.2.21	show asciidoc counters	18
1.2.22	show bts <0-255> fail-rep [reset]	18
1.2.23	show bts <0-255> neighbor arfcn <0-1023> bsic (<0-63> any)	19
1.2.24	show bts <0-255> om2k-mo	19
1.2.25	show bts <0-255> smscb [(basic extended)]	20
1.2.26	show bts [<0-255>]	20
1.2.27	show cbc	20
1.2.28	show conns	21
1.2.29	show cpu-sched threads	21
1.2.30	show cs7 (sualm3ualipa) [<0-65534>]	21
1.2.31	show cs7 config	22
1.2.32	show cs7 instance <0-15> as (activelalllm3ualsua)	22
1.2.33	show cs7 instance <0-15> asp	23
1.2.34	show cs7 instance <0-15> sccp addressbook	23
1.2.35	show cs7 instance <0-15> sccp connections	24
1.2.36	show cs7 instance <0-15> sccp ssn <0-65535>	24
1.2.37	show cs7 instance <0-15> sccp timers	25
1.2.38	show cs7 instance <0-15> sccp users	25
1.2.39	show cs7 instance <0-15> users	26
1.2.40	show e1_driver	26
1.2.41	show e1_line [line_nr] [stats]	26
1.2.42	show e1_timeslot [line_nr] [ts_nr]	27
1.2.43	show fsm NAME	27
1.2.44	show fsm all	27
1.2.45	show fsm-instances NAME	28
1.2.46	show fsm-instances all	28
1.2.47	show history	28
1.2.48	show lchan [<0-255>] [<0-255>] [<0-7>] [<0-7>]	29
1.2.49	show lchan summary [<0-255>] [<0-255>] [<0-7>] [<0-7>]	29
1.2.50	show lchan summary-all [<0-255>] [<0-255>] [<0-7>] [<0-7>]	30
1.2.51	show logging vty	30
1.2.52	show mscs	31
1.2.53	show network	31
1.2.54	show nri [<0-1000>]	31
1.2.55	show online-help	32

1.2.56	show paging [<0-255>]	32
1.2.57	show paging-group <0-255> IMSI	32
1.2.58	show position	33
1.2.59	show rate-counters	33
1.2.60	show rejected-bts	33
1.2.61	show statistics	33
1.2.62	show stats	34
1.2.63	show stats level (globalpeer subscriber)	34
1.2.64	show subscriber all	34
1.2.65	show talloc-context (application all) (full brief DEPTH)	35
1.2.66	show talloc-context (application all) (full brief DEPTH) filter REGEXP	35
1.2.67	show talloc-context (application all) (full brief DEPTH) tree ADDRESS	36
1.2.68	show timer [(net mgw)] [TNNNN]	36
1.2.69	show timeslot [<0-255>] [<0-255>] [<0-7>]	37
1.2.70	show trx (connected disconnected)	37
1.2.71	show trx [<0-255>] [<0-255>]	38
1.2.72	show version	38
1.2.73	terminal length <0-512>	38
1.2.74	terminal no length	39
1.2.75	who	39
1.3	enable	39
1.3.1	assignment any	39
1.3.2	bts <0-255> om2000 class (trxc t g ts t fl sl con ld pl mctr cl ft xlrx) <0-255> <0-255>...	40
1.3.3	bts <0-255> om2000 class <0-255> <0-255> <0-255> <0-255>	41
1.3.4	bts <0-255> oml class (site-manager bts radio-carrier baseband-transceiver chann...	41
1.3.5	bts <0-255> oml class <0-255> instance <0-255> <0-255> <0-255>	43
1.3.6	bts <0-255> resend-power-control-defaults	44
1.3.7	bts <0-255> resend-system-information	44
1.3.8	bts <0-255> trx <0-255> timeslot <0-7> pdch (activate deactivate)	44
1.3.9	bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> (activate deactivate) (hrl...	45
1.3.10	bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> assignment	46
1.3.11	bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> handover <0-255>	47
1.3.12	bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> mdex A.B.C.D <0-65535>	47
1.3.13	configure terminal	48
1.3.14	copy running-config startup-config	48
1.3.15	ctrl-interface generate-trap TRAP VALUE	49
1.3.16	disable	49
1.3.17	drop bts connection <0-65535> (oml rs l)	49
1.3.18	generate-location-state-trap <0-255>	50

1.3.19	handover any . . . . .	50
1.3.20	handover any to arfcn <0-1023> bsic (<0-63>lany) . . . . .	50
1.3.21	logging color (0 1) . . . . .	51
1.3.22	logging disable . . . . .	51
1.3.23	logging enable . . . . .	52
1.3.24	logging filter all (0 1) . . . . .	52
1.3.25	logging filter imsi IMSI . . . . .	52
1.3.26	logging level (rlllmmllrrllrsllnmlpaglmeaslm sclholhodeclreflctrlfilterlpcullclslc... . . . .	53
1.3.27	logging level force-all (debuglinfo lnotice lerror lfatal) . . . . .	56
1.3.28	logging level set-all (debuglinfo lnotice lerror lfatal) . . . . .	56
1.3.29	logging print category (0 1) . . . . .	57
1.3.30	logging print category-hex (0 1) . . . . .	57
1.3.31	logging print extended-timestamp (0 1) . . . . .	58
1.3.32	logging print file (0 1 basename) [last] . . . . .	58
1.3.33	logging print level (0 1) . . . . .	59
1.3.34	logging print thread-id (0 1) . . . . .	59
1.3.35	logging set-log-mask MASK . . . . .	60
1.3.36	logging timestamp (0 1) . . . . .	60
1.3.37	logp (rlllmmllrrllrsllnmlpaglmeaslm sclholhodeclreflctrlfilterlpcullclslchanltslas... . . . .	60
1.3.38	no logging level force-all . . . . .	63
1.3.39	restart-bts <0-65535> . . . . .	64
1.3.40	show alarms . . . . .	64
1.3.41	show asciidoc counters . . . . .	64
1.3.42	show bts <0-255> fail-rep [reset] . . . . .	65
1.3.43	show bts <0-255> neighbor arfcn <0-1023> bsic (<0-63>lany) . . . . .	65
1.3.44	show bts <0-255> om2k-mo . . . . .	66
1.3.45	show bts <0-255> smscb [(basic extended)] . . . . .	66
1.3.46	show bts [<0-255>] . . . . .	67
1.3.47	show cbc . . . . .	67
1.3.48	show conns . . . . .	67
1.3.49	show cpu-sched threads . . . . .	68
1.3.50	show cs7 (sualm3ualipa) [<0-65534>] . . . . .	68
1.3.51	show cs7 config . . . . .	68
1.3.52	show cs7 instance <0-15> as (active all m3ualsua) . . . . .	69
1.3.53	show cs7 instance <0-15> asp . . . . .	69
1.3.54	show cs7 instance <0-15> sccp addressbook . . . . .	70
1.3.55	show cs7 instance <0-15> sccp connections . . . . .	70
1.3.56	show cs7 instance <0-15> sccp ssn <0-65535> . . . . .	71
1.3.57	show cs7 instance <0-15> sccp timers . . . . .	71

1.3.58	show cs7 instance <0-15> sccp users . . . . .	72
1.3.59	show cs7 instance <0-15> users . . . . .	72
1.3.60	show e1_driver . . . . .	73
1.3.61	show e1_line [line_nr] [stats] . . . . .	73
1.3.62	show e1_timeslot [line_nr] [ts_nr] . . . . .	74
1.3.63	show fsm NAME . . . . .	74
1.3.64	show fsm all . . . . .	74
1.3.65	show fsm-instances NAME . . . . .	75
1.3.66	show fsm-instances all . . . . .	75
1.3.67	show history . . . . .	75
1.3.68	show lchan [<0-255>] [<0-255>] [<0-7>] [<0-7>] . . . . .	76
1.3.69	show lchan summary [<0-255>] [<0-255>] [<0-7>] [<0-7>] . . . . .	76
1.3.70	show lchan summary-all [<0-255>] [<0-255>] [<0-7>] [<0-7>] . . . . .	77
1.3.71	show logging vty . . . . .	77
1.3.72	show mscs . . . . .	78
1.3.73	show network . . . . .	78
1.3.74	show nri [<0-1000>] . . . . .	78
1.3.75	show online-help . . . . .	79
1.3.76	show paging [<0-255>] . . . . .	79
1.3.77	show paging-group <0-255> IMSI . . . . .	79
1.3.78	show position . . . . .	80
1.3.79	show rate-counters . . . . .	80
1.3.80	show rejected-bts . . . . .	80
1.3.81	show startup-config . . . . .	80
1.3.82	show statistics . . . . .	81
1.3.83	show stats . . . . .	81
1.3.84	show stats level (globalpeer subscriber) . . . . .	81
1.3.85	show subscriber all . . . . .	82
1.3.86	show talloc-context (application all) (full brief DEPTH) . . . . .	82
1.3.87	show talloc-context (application all) (full brief DEPTH) filter REGEXP . . . . .	83
1.3.88	show talloc-context (application all) (full brief DEPTH) tree ADDRESS . . . . .	83
1.3.89	show timer [(net mgw)] [TNNNN] . . . . .	84
1.3.90	show timeslot [<0-255>] [<0-255>] [<0-7>] . . . . .	84
1.3.91	show trx (connected disconnected) . . . . .	85
1.3.92	show trx [<0-255>] [<0-255>] . . . . .	85
1.3.93	show version . . . . .	86
1.3.94	stats report . . . . .	86
1.3.95	stats reset . . . . .	86
1.3.96	terminal length <0-512> . . . . .	87



1.3.97	terminal monitor	87
1.3.98	terminal no length	87
1.3.99	terminal no monitor	88
1.3.100	who	88
1.4	config	88
1.4.1	banner motd default	88
1.4.2	banner motd file [FILE]	89
1.4.3	bsc	89
1.4.4	cbc	89
1.4.5	cpu-sched	90
1.4.6	cs7 instance <0-15>	90
1.4.7	ctrl	90
1.4.8	e1_input	91
1.4.9	enable password (8l) WORD	91
1.4.10	enable password LINE	91
1.4.11	hostname WORD	92
1.4.12	line vty	92
1.4.13	log alarms <2-32700>	92
1.4.14	log file .FILENAME	93
1.4.15	log gsmtap [HOSTNAME]	93
1.4.16	log stderr	93
1.4.17	log syslog (authpriv cron daemon ftp lpr mail news user uucp)	94
1.4.18	log syslog local <0-7>	94
1.4.19	log systemd-journal [raw]	95
1.4.20	msc [<0-1000>]	95
1.4.21	network	96
1.4.22	no banner motd	96
1.4.23	no enable password	96
1.4.24	no hostname [HOSTNAME]	97
1.4.25	no log alarms	97
1.4.26	no log file .FILENAME	97
1.4.27	no log stderr	98
1.4.28	no log syslog	98
1.4.29	no log systemd-journal	98
1.4.30	no service advanced-vty	99
1.4.31	no service terminal-length [<0-512>]	99
1.4.32	no stats reporter log	99
1.4.33	no stats reporter statsd	100
1.4.34	password (8l) WORD	100

1.4.35	password LINE . . . . .	100
1.4.36	service advanced-vty . . . . .	101
1.4.37	service terminal-length <0-512> . . . . .	101
1.4.38	show history . . . . .	101
1.4.39	stats interval <0-65535> . . . . .	102
1.4.40	stats reporter log . . . . .	102
1.4.41	stats reporter statsd . . . . .	102
1.5	config-log . . . . .	103
1.5.1	logging color (0 1) . . . . .	103
1.5.2	logging filter all (0 1) . . . . .	103
1.5.3	logging filter imsi IMSI . . . . .	104
1.5.4	logging level (rlllmmllrrllrsllnmlpaglmeaslm sclholhoclreflctrlfilterlpcullclsc... . . . .	104
1.5.5	logging level force-all (debuglinfo noticeerrorlfatal) . . . . .	107
1.5.6	logging level set-all (debuglinfo noticeerrorlfatal) . . . . .	107
1.5.7	logging print category (0 1) . . . . .	108
1.5.8	logging print category-hex (0 1) . . . . .	108
1.5.9	logging print extended-timestamp (0 1) . . . . .	109
1.5.10	logging print file (0 1 basename) [last] . . . . .	109
1.5.11	logging print level (0 1) . . . . .	110
1.5.12	logging print thread-id (0 1) . . . . .	110
1.5.13	logging timestamp (0 1) . . . . .	111
1.5.14	no logging level force-all . . . . .	111
1.6	config-stats . . . . .	112
1.6.1	disable . . . . .	112
1.6.2	enable . . . . .	112
1.6.3	flush-period <0-65535> . . . . .	112
1.6.4	level (global peer subscriber) . . . . .	112
1.6.5	local-ip ADDR . . . . .	113
1.6.6	mtu <100-65535> . . . . .	113
1.6.7	no local-ip . . . . .	113
1.6.8	no mtu . . . . .	114
1.6.9	no prefix . . . . .	114
1.6.10	prefix PREFIX . . . . .	114
1.6.11	remote-ip ADDR . . . . .	114
1.6.12	remote-port <1-65535> . . . . .	115
1.7	config-line . . . . .	115
1.7.1	bind A.B.C.D [<0-65535>] . . . . .	115
1.7.2	login . . . . .	115
1.7.3	no login . . . . .	116

1.8	config-e1_input . . . . .	116
1.8.1	e1_line <0-255> driver (misdn misdn_lapd dahdile1 dlipalunixsocket) . . . . .	116
1.8.2	e1_line <0-255> ipa-keepalive <1-300> <1-300> . . . . .	117
1.8.3	e1_line <0-255> keepalive . . . . .	117
1.8.4	e1_line <0-255> keepalive <1-300> <1-20> <1-300> . . . . .	118
1.8.5	e1_line <0-255> name .LINE . . . . .	118
1.8.6	e1_line <0-255> port <0-255> . . . . .	119
1.8.7	e1_line <0-255> socket .SOCKET . . . . .	119
1.8.8	ipa bind A.B.C.D . . . . .	120
1.8.9	no e1_line <0-255> ipa-keepalive . . . . .	120
1.8.10	no e1_line <0-255> keepalive . . . . .	121
1.8.11	no pcap . . . . .	121
1.8.12	pcap .FILE . . . . .	122
1.9	config-ctrl . . . . .	122
1.9.1	bind A.B.C.D . . . . .	122
1.10	config-cs7 . . . . .	122
1.10.1	as NAME (sualm3ualipa) . . . . .	122
1.10.2	asp NAME <0-65535> <0-65535> (sualm3ualipa) . . . . .	123
1.10.3	description .TEXT . . . . .	124
1.10.4	network-indicator (international   national   reserved   spare) . . . . .	124
1.10.5	no as NAME . . . . .	124
1.10.6	no asp NAME . . . . .	125
1.10.7	no sccp-address NAME . . . . .	125
1.10.8	point-code POINT_CODE . . . . .	126
1.10.9	point-code delimiter (default dash) . . . . .	126
1.10.10	point-code format <1-24> [<1-23>] [<1-22>] . . . . .	127
1.10.11	point-code format default . . . . .	127
1.10.12	sccp-address NAME . . . . .	128
1.10.13	sccp-timer (conn_est ias iar rellrepeat_rellint guard reset reassembly) <1-99999...> . . . . .	128
1.10.14	xua rkm routing-key-allocation (static-only dynamic-permitted) . . . . .	129
1.11	config-cs7-as . . . . .	130
1.11.1	asp NAME . . . . .	130
1.11.2	description .TEXT . . . . .	130
1.11.3	no asp NAME . . . . .	130
1.11.4	no traffic-mode . . . . .	131
1.11.5	point-code override dpc PC . . . . .	131
1.11.6	point-code override patch-sccp (disabled both) . . . . .	131
1.11.7	qos-class <0-255> . . . . .	132
1.11.8	recovery-timeout <1-2000> . . . . .	132

1.11.9	routing-key RCONTEXT DPC	133
1.11.10	routing-key RCONTEXT DPC si (aal2lbicclb-isuplh248lisuplsat-isuplsccpltup)	133
1.11.11	routing-key RCONTEXT DPC si (aal2lbicclb-isuplh248lisuplsat-isuplsccpltup) ssn S...	134
1.11.12	routing-key RCONTEXT DPC ssn SSN	135
1.11.13	traffic-mode (broadcast   loadshare   roundrobin   override)	136
1.12	config-cs7-asp	136
1.12.1	block	136
1.12.2	description .TEXT	136
1.12.3	local-ip (A.B.C.D X::X::X:X)	137
1.12.4	qos-class <0-255>	137
1.12.5	remote-ip (A.B.C.D X::X::X:X)	137
1.12.6	role (sglasplisp)	138
1.12.7	sctp-role (client server)	138
1.12.8	shutdown	139
1.13	config-cs7-sccpaddr	139
1.13.1	global-title	139
1.13.2	no global-title	140
1.13.3	no point-code	140
1.13.4	no subsystem-number	140
1.13.5	point-code POINT_CODE	141
1.13.6	routing-indicator (GT PC IP)	141
1.13.7	subsystem-number <0-4294967295>	142
1.14	config-cs7-sccpaddr-gt	142
1.14.1	digits DIGITS	142
1.14.2	global-title-indicator <0-15>	142
1.14.3	nature-of-address-indicator <0-127>	143
1.14.4	numbering-plan-indicator <0-15>	143
1.14.5	translation-type <0-255>	144
1.15	config-cpu-sched	144
1.15.1	cpu-affinity (self all <0-4294967295> THREADNAME) CPUHEXMASK [delay]	144
1.15.2	policy rr <1-32>	145
1.16	config-net	145
1.16.1	allow-unusable-timeslots	145
1.16.2	bts <0-255>	145
1.16.3	encryption a5 <0-3> [<0-3>] [<0-3>] [<0-3>]	146
1.16.4	handover (0 1 default)	146
1.16.5	handover algorithm (1 2 default)	147
1.16.6	handover1 maximum distance (<0-9999> default)	147
1.16.7	handover1 power budget hysteresis (<0-999> default)	148

1.16.8 handover1 power budget interval (<1-99> default)	148
1.16.9 handover1 window rxlev averaging (<1-10> default)	149
1.16.10 handover1 window rxlev neighbor averaging (<1-10> default)	149
1.16.11 handover1 window rxqual averaging (<1-10> default)	150
1.16.12 handover2 afs-bias rxlev (<0-20> default)	151
1.16.13 handover2 afs-bias rxqual (<0-7> default)	151
1.16.14 handover2 assignment (0 1 default)	152
1.16.15 handover2 congestion-check (disabled <1-999> now)	152
1.16.16 handover2 max-handovers (<1-9999> default)	153
1.16.17 handover2 maximum distance (<0-9999> default)	153
1.16.18 handover2 min rxlev (<-110--50> default)	154
1.16.19 handover2 min rxqual (<0-7> default)	154
1.16.20 handover2 min-free-slots tch/f (<0-9999> default)	155
1.16.21 handover2 min-free-slots tch/h (<0-9999> default)	155
1.16.22 handover2 penalty-time failed-assignment (<0-99999> default)	156
1.16.23 handover2 penalty-time failed-ho (<0-99999> default)	156
1.16.24 handover2 penalty-time max-distance (<0-99999> default)	157
1.16.25 handover2 power budget hysteresis (<0-999> default)	157
1.16.26 handover2 power budget interval (<1-99> default)	158
1.16.27 handover2 retries (<0-9> default)	158
1.16.28 handover2 tdma-measurement (full subset default)	159
1.16.29 handover2 window rxlev averaging (<1-10> default)	159
1.16.30 handover2 window rxlev neighbor averaging (<1-10> default)	160
1.16.31 handover2 window rxqual averaging (<1-10> default)	160
1.16.32 meas-feed destination ADDR <0-65535>	161
1.16.33 meas-feed scenario NAME	161
1.16.34 mobile network code <0-999>	162
1.16.35 neci (0 1)	162
1.16.36 neighbor-resolution bind (A.B.C.D X:X::X:X) [<0-65535>]	163
1.16.37 network country code <1-999>	163
1.16.38 no periodic location update	164
1.16.39 no timezone	164
1.16.40 nri bitlen <1-15>	164
1.16.41 nri null add <0-32767> [<0-32767>]	165
1.16.42 nri null del <0-32767> [<0-32767>]	165
1.16.43 paging any use tch (0 1)	166
1.16.44 periodic location update <6-1530>	167
1.16.45 timer [(net mgw)] [TNNNN] [<0-2147483647> default]	167
1.16.46 timezone <-19-19> (0 15 30 45)	168

1.16.47	timezone <-19-19> (0 15 30 45) <0-2> . . . . .	168
1.17	config-net-bts . . . . .	169
1.17.1	(bs-power-controllms-power-control) . . . . .	169
1.17.2	abis-lower-transport (single-timeslotsuper-channel) . . . . .	169
1.17.3	access-control-class-ramping . . . . .	170
1.17.4	access-control-class-ramping-chan-load <0-100> <0-100> . . . . .	170
1.17.5	access-control-class-ramping-step-interval (<5-600> dynamic) . . . . .	170
1.17.6	access-control-class-ramping-step-size (<1-10>) . . . . .	171
1.17.7	access-control-class-rotate <0-10> . . . . .	171
1.17.8	access-control-class-rotate-quantum <1-65535> . . . . .	172
1.17.9	amr tch-f hysteresis (mslbt) <0-15> . . . . .	172
1.17.10	amr tch-f hysteresis (mslbt) <0-15> <0-15> . . . . .	173
1.17.11	amr tch-f hysteresis (mslbt) <0-15> <0-15> <0-15> . . . . .	173
1.17.12	amr tch-f modes (0 1 2 3 4 5 6 7) . . . . .	174
1.17.13	amr tch-f modes (0 1 2 3 4 5 6 7) (0 1 2 3 4 5 6 7) . . . . .	175
1.17.14	amr tch-f modes (0 1 2 3 4 5 6 7) (0 1 2 3 4 5 6 7) (0 1 2 3 4 5 6 7) . . . . .	176
1.17.15	amr tch-f modes (0 1 2 3 4 5 6 7) (0 1 2 3 4 5 6 7) (0 1 2 3 4 5 6 7) (0 1 2 3 4... . . . .	178
1.17.16	amr tch-f start-mode (auto 1 2 3 4) . . . . .	180
1.17.17	amr tch-f threshold (mslbt) <0-63> . . . . .	181
1.17.18	amr tch-f threshold (mslbt) <0-63> <0-63> . . . . .	181
1.17.19	amr tch-f threshold (mslbt) <0-63> <0-63> <0-63> . . . . .	182
1.17.20	amr tch-h hysteresis (mslbt) <0-15> . . . . .	183
1.17.21	amr tch-h hysteresis (mslbt) <0-15> <0-15> . . . . .	183
1.17.22	amr tch-h hysteresis (mslbt) <0-15> <0-15> <0-15> . . . . .	184
1.17.23	amr tch-h modes (0 1 2 3 4 5) . . . . .	185
1.17.24	amr tch-h modes (0 1 2 3 4 5) (0 1 2 3 4 5) . . . . .	185
1.17.25	amr tch-h modes (0 1 2 3 4 5) (0 1 2 3 4 5) (0 1 2 3 4 5) . . . . .	186
1.17.26	amr tch-h modes (0 1 2 3 4 5) (0 1 2 3 4 5) (0 1 2 3 4 5) (0 1 2 3 4 5) . . . . .	188
1.17.27	amr tch-h start-mode (auto 1 2 3 4) . . . . .	189
1.17.28	amr tch-h threshold (mslbt) <0-63> . . . . .	190
1.17.29	amr tch-h threshold (mslbt) <0-63> <0-63> . . . . .	191
1.17.30	amr tch-h threshold (mslbt) <0-63> <0-63> <0-63> . . . . .	191
1.17.31	band BAND . . . . .	192
1.17.32	base_station_id_code <0-63> . . . . .	192
1.17.33	ccch load-indication-threshold <0-100> . . . . .	193
1.17.34	cell bar qualify (0 1) . . . . .	193
1.17.35	cell barred (0 1) . . . . .	194
1.17.36	cell reselection hysteresis <0-14> . . . . .	194
1.17.37	cell reselection offset <0-126> . . . . .	195

1.17.38 cell_identity <0-65535> . . . . .	195
1.17.39 channel allocator (ascending descending) . . . . .	196
1.17.40 channel-description attach (0 1) . . . . .	196
1.17.41 channel-description bs-ag-blks-res <0-7> . . . . .	197
1.17.42 channel-description bs-pa-mfrms <2-9> . . . . .	197
1.17.43 codec-support fr . . . . .	198
1.17.44 codec-support fr (hrlefrlramr) . . . . .	198
1.17.45 codec-support fr (hrlefrlramr) (hrlefrlramr) . . . . .	199
1.17.46 codec-support fr (hrlefrlramr) (hrlefrlramr) (hrlefrlramr) . . . . .	199
1.17.47 codec-support fr (hrlefrlramr) (hrlefrlramr) (hrlefrlramr) (hrlefrlramr) . . . . .	200
1.17.48 con-connection-group <1-31> . . . . .	201
1.17.49 del-connection-group <1-31> . . . . .	202
1.17.50 depends-on-bts <0-255> . . . . .	202
1.17.51 description .TEXT . . . . .	202
1.17.52 dtx downlink . . . . .	203
1.17.53 dtx uplink [force] . . . . .	203
1.17.54 early-classmark-sending (allowed forbidden) . . . . .	203
1.17.55 early-classmark-sending-3g (allowed forbidden) . . . . .	204
1.17.56 force-combined-si . . . . .	204
1.17.57 gprs ccn-active (0 1 default) . . . . .	205
1.17.58 gprs cell bvci <2-65535> . . . . .	205
1.17.59 gprs cell timer (blocking-timer blocking-retries unblocking-retries reset-timer ... . . . .	206
1.17.60 gprs control-ack-type-rach . . . . .	207
1.17.61 gprs egprs-packet-channel-request . . . . .	207
1.17.62 gprs mode (none gprs egprs) . . . . .	207
1.17.63 gprs network-control-order (nc0 nc1 nc2) . . . . .	208
1.17.64 gprs ns timer (tns-block tns-block-retries tns-reset tns-reset-retries tns-testl... . . . .	209
1.17.65 gprs nsei <0-65535> . . . . .	210
1.17.66 gprs nsvc <0-1> local udp port <0-65535> . . . . .	210
1.17.67 gprs nsvc <0-1> nsvci <0-65535> . . . . .	211
1.17.68 gprs nsvc <0-1> remote ip (A.B.C.D X::X::X:X) . . . . .	211
1.17.69 gprs nsvc <0-1> remote udp port <0-65535> . . . . .	212
1.17.70 gprs power-control alpha <0-10> . . . . .	212
1.17.71 gprs routing area <0-255> . . . . .	213
1.17.72 handover (0 1 default) . . . . .	213
1.17.73 handover algorithm (1 2 default) . . . . .	214
1.17.74 handover1 maximum distance (<0-9999> default) . . . . .	215
1.17.75 handover1 power budget hysteresis (<0-999> default) . . . . .	215
1.17.76 handover1 power budget interval (<1-99> default) . . . . .	216

1.17.77 handover1 window rxlev averaging (<1-10> default)	216
1.17.78 handover1 window rxlev neighbor averaging (<1-10> default)	217
1.17.79 handover1 window rxqual averaging (<1-10> default)	217
1.17.80 handover2 afs-bias rxlev (<0-20> default)	218
1.17.81 handover2 afs-bias rxqual (<0-7> default)	219
1.17.82 handover2 assignment (0 1 default)	219
1.17.83 handover2 max-handovers (<1-9999> default)	220
1.17.84 handover2 maximum distance (<0-9999> default)	220
1.17.85 handover2 min rxlev (<-110--50> default)	221
1.17.86 handover2 min rxqual (<0-7> default)	221
1.17.87 handover2 min-free-slots tch/f (<0-9999> default)	222
1.17.88 handover2 min-free-slots tch/h (<0-9999> default)	222
1.17.89 handover2 penalty-time failed-assignment (<0-99999> default)	223
1.17.90 handover2 penalty-time failed-ho (<0-99999> default)	223
1.17.91 handover2 penalty-time max-distance (<0-99999> default)	224
1.17.92 handover2 power budget hysteresis (<0-999> default)	224
1.17.93 handover2 power budget interval (<1-99> default)	225
1.17.94 handover2 retries (<0-9> default)	225
1.17.95 handover2 tdma-measurement (full subset default)	226
1.17.96 handover2 window rxlev averaging (<1-10> default)	226
1.17.97 handover2 window rxlev neighbor averaging (<1-10> default)	227
1.17.98 handover2 window rxqual averaging (<1-10> default)	227
1.17.99 ipa rsl-ip A.B.C.D	228
1.17.100 pa unit-id <0-65534> <0-255>	228
1.17.101 s-connection-list (add del) <0-2047> <0-2047> <0-255>	229
1.17.102 location_area_code <0-65535>	229
1.17.103 ms max power <0-40>	230
1.17.104 neighbor bts <0-255>	230
1.17.105 neighbor cgi <0-999> <0-999> <0-65535> <0-65535>	230
1.17.106 neighbor cgi <0-999> <0-999> <0-65535> <0-65535> arfcn <0-1023> bsic (<0-63> any...	231
1.17.107 neighbor cgi-ps <0-999> <0-999> <0-65535> <0-255> <0-65535>	232
1.17.108 neighbor cgi-ps <0-999> <0-999> <0-65535> <0-255> <0-65535> arfcn <0-1023> bsic ...	232
1.17.109 neighbor lac <0-65535>	233
1.17.110 neighbor lac <0-65535> arfcn <0-1023> bsic (<0-63> any)	233
1.17.111 neighbor lac-ci <0-65535> <0-65535>	234
1.17.112 neighbor lac-ci <0-65535> <0-65535> arfcn <0-1023> bsic (<0-63> any)	234
1.17.113 neighbor-list (add del) arfcn <0-1023>	235
1.17.114 neighbor-list mode (automatic manual manual-si5)	236
1.17.115 no (bs-power-control ms-power-control)	236



1.17.116	no access-control-class-ramping	237
1.17.117	no depends-on-bts <0-255>	237
1.17.118	no description	237
1.17.119	no dtx downlink	238
1.17.120	no dtx uplink	238
1.17.121	no force-combined-si	239
1.17.122	no gprs control-ack-type-rach	239
1.17.123	no gprs egprs-packet-channel-request	240
1.17.124	no neighbor arfcn <0-1023> bsic (<0-63> any)	240
1.17.125	no neighbor bts <0-255>	241
1.17.126	no neighbors	241
1.17.127	no repeat (ul-sacch dl-sacch)	241
1.17.128	no repeat dl-facch	242
1.17.129	no rf-lock-exclude	242
1.17.130	no system-information unused-send-empty	243
1.17.131	no timer-dynamic TNNNN	243
1.17.132	nokia_site bts-reset-timer <15-100>	244
1.17.133	nokia_site no-local-rel-conf (0 1)	244
1.17.134	nokia_site skip-reset (0 1)	245
1.17.135	om2000 version-limit (oml rs) gen <0-99> rev <0-99>	245
1.17.136	oml e1 line E1_LINE timeslot <1-31> sub-slot (0 1 2 3 full)	246
1.17.137	oml e1 tei <0-63>	247
1.17.138	oml ipa stream-id <0-255> line E1_LINE	247
1.17.139	paging free <-1-1024>	248
1.17.140	pcu-socket PATH	248
1.17.141	penalty time <20-620>	248
1.17.142	penalty time reserved	249
1.17.143	rach access-control-class (0 1 2 3 4 5 6 7 8 9 11 12 13 14 15) (barred allowed)	249
1.17.144	rach emergency call allowed (0 1)	251
1.17.145	rach max transmission (1 2 4 7)	251
1.17.146	rach nm busy threshold <0-255>	252
1.17.147	rach nm load average <0-65535>	252
1.17.148	rach tx integer <0-15>	253
1.17.149	radio-link-timeout <4-64>	253
1.17.150	radio-link-timeout infinite	254
1.17.151	repeat (ul-sacch dl-sacch)	254
1.17.152	repeat dl-facch (command all)	255
1.17.153	repeat rxqual (0 1 2 3 4 5 6 7)	255
1.17.154	rf-lock-exclude	256

1.17.155	rxlev access min <0-63> . . . . .	256
1.17.156	i2quater neighbor-list add earfcn <0-65535> thresh-hi <0-31> thresh-lo <0-32> p... . . . .	257
1.17.157	i2quater neighbor-list add uarfcn <0-16383> <0-511> <0-1> . . . . .	258
1.17.158	i2quater neighbor-list del earfcn <0-65535> . . . . .	258
1.17.159	i2quater neighbor-list del uarfcn <0-16383> <0-511> . . . . .	259
1.17.160	i5 neighbor-list (add del) arfcn <0-1023> . . . . .	259
1.17.161	system-information (1 2 3 4 5 6 7 8 9 10 13 16 17 18 19 20 2bis 2ter 2quater 5bi... . . . .	260
1.17.162	system-information (1 2 3 4 5 6 7 8 9 10 13 16 17 18 19 20 2bis 2ter 2quater 5bi... . . . .	262
1.17.163	system-information unused-send-empty . . . . .	263
1.17.164	temporary offset <0-60> . . . . .	264
1.17.165	temporary offset infinite . . . . .	264
1.17.166	timer-dynamic TNNNN . . . . .	265
1.17.167	tx <0-255> . . . . .	265
1.17.168	type (unknown bs11 nanobts lrbs2000 nokia_sitel sysmobts) . . . . .	265
1.18	config-net-bts-trx . . . . .	266
1.18.1	arfcn <0-1023> . . . . .	266
1.18.2	description .TEXT . . . . .	266
1.18.3	max_power_red <0-100> . . . . .	267
1.18.4	no description . . . . .	267
1.18.5	nominal power <-20-100> . . . . .	267
1.18.6	rf_locked (0 1) . . . . .	268
1.18.7	rsl e1 line E1_LINE timeslot <1-31> sub-slot (0 1 2 3 full) . . . . .	268
1.18.8	rsl e1 tei <0-63> . . . . .	269
1.18.9	timeslot <0-7> . . . . .	269
1.19	config-net-bts-trx-ts . . . . .	270
1.19.1	e1 line E1_LINE timeslot <1-31> sub-slot (0 1 2 3 full) . . . . .	270
1.19.2	hopping arfcn add <0-1023> . . . . .	271
1.19.3	hopping arfcn del <0-1023> . . . . .	271
1.19.4	hopping arfcn del-all . . . . .	272
1.19.5	hopping enabled (0 1) . . . . .	272
1.19.6	hopping maio <0-63> . . . . .	273
1.19.7	hopping sequence-number <0-63> . . . . .	273
1.19.8	phys_chan_config (none ccc lccc h+sdcc 4 tch ftch h sdcc 8 pdch tch f_pdch unkno... . . . .	274
1.19.9	training_sequence_code <0-7> . . . . .	275
1.20	oml . . . . .	275
1.20.1	change-adm-state (locked unlocked shutdown null) . . . . .	275
1.20.2	opstart . . . . .	275
1.21	config-msc . . . . .	276
1.21.1	allow-attach . . . . .	276

1.21.2	allow-emergency (allowdeny)	276
1.21.3	amr-config 10_2k (allowed forbidden)	277
1.21.4	amr-config 12_2k (allowed forbidden)	277
1.21.5	amr-config 4_75k (allowed forbidden)	278
1.21.6	amr-config 5_15k (allowed forbidden)	278
1.21.7	amr-config 5_90k (allowed forbidden)	279
1.21.8	amr-config 6_70k (allowed forbidden)	279
1.21.9	amr-config 7_40k (allowed forbidden)	280
1.21.10	amr-config 7_95k (allowed forbidden)	280
1.21.11	amr-payload (octet-aligned bandwidth-efficient)	281
1.21.12	asp-protocol (m3ualsualipa)	281
1.21.13	bsc-addr NAME	281
1.21.14	codec-list .LIST	282
1.21.15	core-mobile-country-code <1-999>	282
1.21.16	core-mobile-network-code <1-999>	282
1.21.17	lcls-codec-mismatch (allowed forbidden)	283
1.21.18	lcls-mode (disabled mgw-loop bts-loop)	283
1.21.19	mgw endpoint-domain NAME	284
1.21.20	mgw local-ip (A.B.C.D X:X::X:X)	284
1.21.21	mgw local-port <0-65535>	284
1.21.22	mgw remote-ip (A.B.C.D X:X::X:X)	285
1.21.23	mgw remote-port <0-65535>	285
1.21.24	mgw x-osmo-ign call-id	285
1.21.25	msc-addr NAME	286
1.21.26	no allow-attach	286
1.21.27	no mgw x-osmo-ign	287
1.21.28	nri add <0-32767> [<0-32767>]	287
1.21.29	nri del <0-32767> [<0-32767>]	288
1.21.30	osmux (on off only)	288
1.21.31	show nri	289
1.22	om2k	289
1.22.1	arbitrary <0-65535> [HEXSTRING]	289
1.22.2	capabilities-request	289
1.22.3	configuration-request	290
1.22.4	connect-command	290
1.22.5	disable-request	290
1.22.6	disconnect-command	290
1.22.7	enable-request	291
1.22.8	operational-info <0-1>	291

1.22.9	reset-command	291
1.22.10	start-request	291
1.22.11	status-request	292
1.22.12	test-request	292
1.23	om2k-con-group	292
1.23.1	con-path (addlde) <0-2047> <0-255> concentrated <1-16>	292
1.23.2	con-path (addlde) <0-2047> <0-255> deconcentrated <0-63>	293
1.24	config-bsc	293
1.24.1	bsc-auto-rf-off <1-65000>	293
1.24.2	bsc-rf-socket PATH	294
1.24.3	mid-call-timeout NR	294
1.24.4	no bsc-auto-rf-off	294
1.25	config-cbc	295
1.25.1	client	295
1.25.2	mode (server client disabled)	295
1.25.3	server	295
1.26	config-cbc-server	296
1.26.1	local-ip (A.B.C.D X::X:X)	296
1.26.2	local-port <1-65535>	296
1.27	config-cbc-client	296
1.27.1	local-ip (A.B.C.D X::X:X)	296
1.27.2	local-port <1-65535>	297
1.27.3	no local-ip	297
1.27.4	no local-port	297
1.27.5	remote-ip (A.B.C.D X::X:X)	298
1.27.6	remote-port <1-65535>	298
1.28	config-power-ctrl	298
1.28.1	(rxlev-avg rxqual-avg) algo (unweighted weighted mod-median)	298
1.28.2	(rxlev-avg rxqual-avg) algo osmo-ewma beta <1-99>	299
1.28.3	(rxlev-avg rxqual-avg) params hreqave <1-31> hreqt <1-31>	300
1.28.4	bs-power (static dyn-max) <0-30>	300
1.28.5	ctrl-interval <0-31>	301
1.28.6	mode (static dyn-bts) [reset]	301
1.28.7	no (rxlev-avg rxqual-avg)	302
1.28.8	rxlev-thresh lower <0-63> upper <0-63>	302
1.28.9	rxlev-thresh-comp lower <0-31> <0-31> upper <0-31> <0-31>	303
1.28.10	rxqual-thresh lower <0-7> upper <0-7>	303
1.28.11	rxqual-thresh-comp lower <0-31> <0-31> upper <0-31> <0-31>	304
1.28.12	step-size inc <2-6> red <2-4>	305

# List of Tables

1.1	VTY Parameter Patterns . . . . .	1
1.2	VTY port numbers . . . . .	1

# Chapter 1

## VTY reference

The Virtual Tele Type (VTY) has the concept of nodes and commands. This chapter lists all nodes and the commands that are available within the node. Each command can consist out of several words followed by a variable number of parameters. There are common patterns for the parameters, these include IPv4 addresses, number ranges, a word, a line of text and choice. The following will explain the commonly used patterns.

Pattern	Example	Explanation
A.B.C.D	127.0.0.1	A IPv4 address
TEXT	example01	A single string without any spaces, tabs
.TEXT	Some information	A line of text
(OptionA OptionB OptionC)	OptionA	A choice between a list of available options
<0-10>	5	A number from a range

Table 1.1: VTY Parameter Patterns

The application is configured through the VTY. For configuring a system one needs to enter the **enable** node and then enter the **configure terminal** command. Then the configuration can be made according to the available commands. After the system has been configured one can use the **write** command to write the new configuration to the configuration file. The new file will be used after the application has been restarted.

The following table lists the TCP port numbers of the VTY for the various Osmocom GSM related programs as used on sysmocom products:

Port Number	Software
4240	osmo-pcu
4241	osmo-bts
4242	osmo-nitb, osmo-bsc
4243	osmo-bsc_mgcp
4244	osmo-bsc_nat
4245	osmo-sgsn
4246	osmo-gbproxy

Table 1.2: VTY port numbers

### 1.1 Common Commands

These commands are available on all VTY nodes. They are listed here only once, to unclutter the VTY reference.

### 1.1.1 end

#### Command

```
end
```

#### Parameters

end

End current mode and change to enable mode.

### 1.1.2 exit

#### Command

```
exit
```

#### Parameters

exit

Exit current mode and down to previous mode

### 1.1.3 help

#### Command

```
help
```

#### Parameters

help

Description of the interactive help system

### 1.1.4 list [with-flags]

#### Command

```
list [with-flags]
```

#### Parameters

list

Print command list

[with-flags]

Also print the VTY attribute flags

---

### 1.1.5 show running-config

#### Command

```
show running-config
```

#### Parameters

##### show

Show running system information

##### running-config

running configuration

### 1.1.6 show vty-attributes

#### Command

```
show vty-attributes
```

#### Parameters

##### show

Show running system information

##### vty-attributes

List of VTY attributes

### 1.1.7 show vty-attributes (application|library|global)

#### Command

```
show vty-attributes (application|library|global)
```

#### Parameters

##### show

Show running system information

##### vty-attributes

List of VTY attributes

##### application

Application specific attributes only

##### library

Library specific attributes only

##### global

Global attributes only

---



### 1.1.8 write

Command

```
write
```

Parameters

write

Write running configuration to memory, network, or terminal

### 1.1.9 write file [PATH]

Command

```
write file [PATH]
```

Parameters

write

Write running configuration to memory, network, or terminal

file

Write to configuration file

[PATH]

Set file path to store the config, or replace if already exists

### 1.1.10 write memory

Command

```
write memory
```

Parameters

write

Write running configuration to memory, network, or terminal

memory

Write configuration to the file (same as write file)

### 1.1.11 write terminal

Command

```
write terminal
```

Parameters

write

Write running configuration to memory, network, or terminal

terminal

Write to terminal

## 1.2 view

The view node is the default node when connecting to the VTY interface. This node does not require any additional permission and allows to introspect the application.

### 1.2.1 enable [expert-mode]

Command

```
enable [expert-mode]
```

Parameters

enable

Turn on privileged mode command

[expert-mode]

Enable the expert mode (show hidden commands)

### 1.2.2 logging color (0|1)

Command

```
logging color (0|1)
```

Parameters

logging

Configure logging

color

Configure color-printing for log messages

0

Don't use color for printing messages

1

Use color for printing messages

### 1.2.3 logging disable

Command

```
logging disable
```

Parameters

logging

Configure logging

disable

Disables logging to this vty

---

### 1.2.4 logging enable

This command is required to make logging commands available on the telnet VTY.

#### Command

```
logging enable
```

#### Parameters

##### logging

Configure logging

##### enable

Enables logging to this vty

### 1.2.5 logging filter all (0|1)

Disable/enable general log output on a given target. Typically, 'logging filter all 1' allows to see the usual log output on a given target. Setting to '0' can be useful when logging to the telnet VTY console: mute all log output to allow typing VTY commands on the telnet prompt without interference from log output; 'logging filter all 1' then re-enables logging in the same log output configuration as before. Some applications provide more specific filters, e.g. to log a given IMSI only. To employ such filters, set 'logging filter all 0' to disable general logging, and then enable a more specific filter instead.

#### Command

```
logging filter all (0|1)
```

#### Parameters

##### logging

Configure logging

##### filter

Filter log messages

##### all

Do you want to log all messages?

##### 0

Only print messages matched by other filters

##### 1

Bypass filter and print all messages

### 1.2.6 logging filter imsi IMSI

#### Command

```
logging filter imsi IMSI
```

#### Parameters

---

**logging**

Configure logging

**filter**

Filter log messages

**imsi**

Filter log messages by IMSI

**IMSI**

IMSI to be used as filter

**1.2.7 logging level (rll|mm|rr|rs|nm|pag|meas|msc|ho|hodec|ref|ctrl|filter|pcu|lcls|c...****Command**

```
logging level (rll|mm|rr|rs|nm|pag|meas|msc|ho|hodec|ref|ctrl|filter|pcu|lcls|chan|ts| ↵
as|cbs|lcs|reset|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgsup|loap ↵
|lss7|lsccp|lsua|lm3ua|lmgcp|ljibuf|lrspro|lms|lbssgp) (debug|info|notice|error| ↵
fatal)
```

**Parameters****logging**

Configure logging

**level**

Set the log level for a specified category

**rll**

A-bis Radio Link Layer (RLL)

**mm**

Layer3 Mobility Management (MM)

**rr**

Layer3 Radio Resource (RR)

**rs**

A-bis Radio Signalling Link (RSL)

**nm**

A-bis Network Management / O&amp;M (NM/OML)

**pag**

Paging Subsystem

**meas**

Radio Measurement Processing

**msc**

Mobile Switching Center

**ho**

Hand-Over Process

---

hodec  
    Hand-Over Decision

ref  
    Reference Counting

ctrl  
    Control interface

filter  
    BSC/NAT IMSI based filtering

pcu  
    PCU Interface

lcls  
    Local Call, Local Switch

chan  
    lchan FSM

ts  
    timeslot FSM

as  
    assignment FSM

cbs  
    Cell Broadcast System

lcs  
    Location Services

reset  
    RESET/ACK on A and Lb interfaces

lglobal  
    Library-internal global log family

llapd  
    LAPD in libosmogsm

linp  
    A-bis Input Subsystem

lmux  
    A-bis B-Subchannel TRAU Frame Multiplex

lmi  
    A-bis Input Driver for Signalling

lmib  
    A-bis Input Driver for B-Channels (voice)

lsms  
    Layer3 Short Message Service (SMS)

---

---

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

lsccp  
libosmo-sigtran SCCP Implementation

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

lmgcp  
libosmo-mgcp Media Gateway Control Protocol

ljibuf  
libosmo-netif Jitter Buffer

lrspro  
Remote SIM protocol

lns  
GPRS NS layer

lbssgp  
GPRS BSSGP layer

debug  
Log debug messages and higher levels

info  
Log informational messages and higher levels

notice  
Log noticeable messages and higher levels

error  
Log error messages and higher levels

fatal  
Log only fatal messages

---

### 1.2.8 logging level force-all (debug|info|notice|error|fatal)

#### Command

```
logging level force-all (debug|info|notice|error|fatal)
```

#### Parameters

##### logging

Configure logging

##### level

Set the log level for a specified category

##### force-all

Globally force all logging categories to a specific level. This is released by the 'no logging level force-all' command. Note: any 'logging level <category> <level>' commands will have no visible effect after this, until the forced level is released.

##### debug

Log debug messages and higher levels

##### info

Log informational messages and higher levels

##### notice

Log noticeable messages and higher levels

##### error

Log error messages and higher levels

##### fatal

Log only fatal messages

### 1.2.9 logging level set-all (debug|info|notice|error|fatal)

#### Command

```
logging level set-all (debug|info|notice|error|fatal)
```

#### Parameters

##### logging

Configure logging

##### level

Set the log level for a specified category

##### set-all

Once-off set all categories to the given log level. There is no single command to take back these changes -- each category is set to the given level, period.

##### debug

Log debug messages and higher levels

---

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.2.10 logging print category (0|1)

Command

```
logging print category (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem name

### 1.2.11 logging print category-hex (0|1)

Command

```
logging print category-hex (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category-hex

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem nr in hex ('<000b>')



### 1.2.12 logging print extended-timestamp (0|1)

#### Command

```
logging print extended-timestamp (0|1)
```

#### Parameters

##### logging

Configure logging

##### print

Log output settings

##### extended-timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp with YYYYMMDDhhmmssnnn

### 1.2.13 logging print file (0|1|basename) [last]

#### Command

```
logging print file (0|1|basename) [last]
```

#### Parameters

##### logging

Configure logging

##### print

Log output settings

##### file

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the source file and line

##### basename

Prefix each log message with the source file's basename (strip leading paths) and line

##### [last]

Log source file info at the end of a log line. If omitted, log source file info just before the log text.

### 1.2.14 logging print level (0|1)

#### Command

```
logging print level (0|1)
```

#### Parameters

##### logging

Configure logging

##### print

Log output settings

##### level

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the log level name

### 1.2.15 logging print thread-id (0|1)

#### Command

```
logging print thread-id (0|1)
```

#### Parameters

##### logging

Configure logging

##### print

Log output settings

##### thread-id

Configure log message logging Thread ID

0

Don't prefix each log message

1

Prefix each log message with current Thread ID

### 1.2.16 logging set-log-mask MASK

#### Command

```
logging set-log-mask MASK
```

#### Parameters

##### logging

Configure logging

##### set-log-mask

Set the logmask of this logging target

##### MASK

List of logging categories to log, e.g. 'abc:mno:xyz'. Available log categories depend on the specific application, refer to the 'logging level' command. Optionally add individual log levels like 'abc,1:mno,3:xyz,5', where the level numbers are LOGL\_DEBUG=1 LOGL\_INFO=3 LOGL\_NOTICE=5 LOGL\_ERROR=7 LOGL\_FATAL=8

### 1.2.17 logging timestamp (0|1)

#### Command

```
logging timestamp (0|1)
```

#### Parameters

##### logging

Configure logging

##### timestamp

Configure log message timestamping

##### 0

Don't prefix each log message

##### 1

Prefix each log message with current timestamp

### 1.2.18 logp (rll|mm|rr|rs|nm|pag|meas|msc|ho|hodec|ref|ctrl|filter|pcu|lcls|chan|ts|as...

#### Command

```
logp (rll|mm|rr|rs|nm|pag|meas|msc|ho|hodec|ref|ctrl|filter|pcu|lcls|chan|ts|as|cbs| ↵
lcs|reset|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtpl|lstats|lgsup|loap|lss7| ↵
lsccp|lsua|lm3ua|lmgcp|ljibuf|lrspro|lms|lbssgp) (debug|info|notice|error|fatal) . ↵
LOGMESSAGE
```

#### Parameters

logp

Print a message on all log outputs; useful for placing markers in test logs

rl

A-bis Radio Link Layer (RLL)

mm

Layer3 Mobility Management (MM)

rr

Layer3 Radio Resource (RR)

rsl

A-bis Radio Signalling Link (RSL)

nm

A-bis Network Management / O&M (NM/OML)

pag

Paging Subsystem

meas

Radio Measurement Processing

msc

Mobile Switching Center

ho

Hand-Over Process

hodec

Hand-Over Decision

ref

Reference Counting

ctrl

Control interface

filter

BSC/NAT IMSI based filtering

pcu

PCU Interface

lcls

Local Call, Local Switch

chan

lchan FSM

ts

timeslot FSM

as

assignment FSM

---

---

cbs  
Cell Broadcast System

lcs  
Location Services

reset  
RESET/ACK on A and Lb interfaces

lglobal  
Library-internal global log family

llapd  
LAPD in libosmogsm

linp  
A-bis Input Subsystem

lmux  
A-bis B-Subchannel TRAU Frame Multiplex

lmi  
A-bis Input Driver for Signalling

lmib  
A-bis Input Driver for B-Channels (voice)

lsms  
Layer3 Short Message Service (SMS)

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

lsccp  
libosmo-sigtran SCCP Implementation

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

---

imgcp	libosmo-mgcp Media Gateway Control Protocol
ljibuf	libosmo-netif Jitter Buffer
lrspro	Remote SIM protocol
lms	GPRS NS layer
lbssgp	GPRS BSSGP layer
debug	Log debug messages and higher levels
info	Log informational messages and higher levels
notice	Log noticeable messages and higher levels
error	Log error messages and higher levels
fatal	Log only fatal messages
.LOGMESSAGE	Arbitrary message to log on given category and log level

### 1.2.19 no logging level force-all

#### Command

```
no logging level force-all
```

#### Parameters

##### no

Negate a command or set its defaults

##### logging

Configure logging

##### level

Set the log level for a specified category

##### force-all

Release any globally forced log level set with 'logging level force-all <level>'

### 1.2.20 show alarms

#### Command

```
show alarms
```

#### Parameters

show

Show running system information

alarms

Show current logging configuration

### 1.2.21 show asciidoc counters

#### Command

```
show asciidoc counters
```

#### Parameters

show

Show running system information

asciidoc

Asciidoc generation

counters

Generate table of all registered counters

### 1.2.22 show bts <0-255> fail-rep [reset]

#### Command

```
show bts <0-255> fail-rep [reset]
```

#### Parameters

show

Show running system information

bts

Display information about a BTS

<0-255>

BTS number

fail-rep

OML failure reports

[reset]

Clear the list of failure reports after showing them

---

### 1.2.23 show bts <0-255> neighbor arfcn <0-1023> bsic (<0-63>|any)

#### Command

```
show bts <0-255> neighbor arfcn <0-1023> bsic (<0-63>|any)
```

#### Parameters

show

Show running system information

bts

Display information about a BTS

<0-255>

BTS number

neighbor

Query which cell would be the target for this neighbor ARFCN+BSIC

arfcn

ARFCN of neighbor cell

<0-1023>

ARFCN value

bsic

BSIC of neighbor cell

<0-63>

BSIC value

any

for all BSICs / use any BSIC in this ARFCN

### 1.2.24 show bts <0-255> om2k-mo

#### Command

```
show bts <0-255> om2k-mo
```

#### Parameters

show

Show running system information

bts

Display information about a BTS

<0-255>

BTS number

om2k-mo

OM2000 Managed Object information



### 1.2.25 show bts <0-255> smscb [(basic|extended)]

#### Command

```
show bts <0-255> smscb [(basic|extended) ]
```

#### Parameters

show

Show running system information

bts

Display information about a BTS

<0-255>

BTS number

smscb

SMS Cell Broadcast State

[basic]

Show only information related to CBCH BASIC

[extended]

Show only information related to CBCH EXTENDED

### 1.2.26 show bts [<0-255>]

#### Command

```
show bts [<0-255>]
```

#### Parameters

show

Show running system information

bts

Display information about a BTS

[<0-255>]

BTS number

### 1.2.27 show cbc

#### Command

```
show cbc
```

#### Parameters

show

Show running system information

cbc

Display state of CBC / CBSP

### 1.2.28 show conns

#### Command

```
show conns
```

#### Parameters

show

Show running system information

conns

Display currently active subscriber connections

### 1.2.29 show cpu-sched threads

#### Command

```
show cpu-sched threads
```

#### Parameters

show

Show running system information

cpu-sched

Show Sched section information

threads

Show information about running threads)

### 1.2.30 show cs7 (sua|m3ua|ipa) [<0-65534>]

#### Command

```
show cs7 (sua|m3ua|ipa) [<0-65534>]
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

sua

SCCP User Adaptation

m3ua

MTP3 User Adaptation

ipa

IPA Multiplex (SCCP Lite)

[<0-65534>]

Port Number

---

### 1.2.31 show cs7 config

#### Command

```
show cs7 config
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

config

Currently running cs7 configuration

### 1.2.32 show cs7 instance <0-15> as (active|all|m3ua|sua)

#### Command

```
show cs7 instance <0-15> as (active|all|m3ua|sua)
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

as

Application Server (AS)

active

Display all active ASs

all

Display all ASs (default)

m3ua

Display all m3ua ASs

sua

Display all SUA ASs

### 1.2.33 show cs7 instance <0-15> asp

#### Command

```
show cs7 instance <0-15> asp
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### asp

Application Server Process (ASP)

### 1.2.34 show cs7 instance <0-15> sccp addressbook

#### Command

```
show cs7 instance <0-15> sccp addressbook
```

#### Parameters

##### show

Show running system information

##### cs7

ITU-T Signaling System 7

##### instance

An instance of the SS7 stack

##### <0-15>

An instance of the SS7 stack

##### sccp

Signalling Connection Control Part

##### addressbook

List all SCCP addressbook entries

---

### 1.2.35 show cs7 instance <0-15> sccp connections

#### Command

```
show cs7 instance <0-15> sccp connections
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

connections

Show List of active SCCP connections

### 1.2.36 show cs7 instance <0-15> sccp ssn <0-65535>

#### Command

```
show cs7 instance <0-15> sccp ssn <0-65535>
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

ssn

Find an SCCP User registered for the given SSN

<0-65535>

Subsystem Number (SSN)

---

### 1.2.37 show cs7 instance <0-15> sccp timers

#### Command

```
show cs7 instance <0-15> sccp timers
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signaling Connection Control Part

timers

Show List of SCCP timers

### 1.2.38 show cs7 instance <0-15> sccp users

#### Command

```
show cs7 instance <0-15> sccp users
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

users

Show List of SCCP Users registered

### 1.2.39 show cs7 instance <0-15> users

#### Command

```
show cs7 instance <0-15> users
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

users

User Table

### 1.2.40 show e1\_driver

#### Command

```
show e1_driver
```

#### Parameters

show

Show running system information

e1\_driver

Display information about available E1 drivers

### 1.2.41 show e1\_line [line\_nr] [stats]

#### Command

```
show e1_line [line_nr] [stats]
```

#### Parameters

show

Show running system information

e1\_line

Display information about a E1 line

[line\_nr]

E1 Line Number

[stats]

Include statistics

### 1.2.42 show e1\_timeslot [line\_nr] [ts\_nr]

#### Command

```
show e1_timeslot [line_nr] [ts_nr]
```

#### Parameters

show

Show running system information

e1\_timeslot

Display information about a E1 timeslot

[line\_nr]

E1 Line Number

[ts\_nr]

E1 Timeslot Number

### 1.2.43 show fsm NAME

#### Command

```
show fsm NAME
```

#### Parameters

show

Show running system information

fsm

Show information about finite state machines

NAME

Display information about a single named finite state machine

### 1.2.44 show fsm all

#### Command

```
show fsm all
```

#### Parameters

show

Show running system information

fsm

Show information about finite state machines

all

Display a list of all registered finite state machines



### 1.2.45 show fsm-instances NAME

#### Command

```
show fsm-instances NAME
```

#### Parameters

##### show

Show running system information

##### fsm-instances

Show information about finite state machine instances

##### NAME

Display a list of all FSM instances of the named finite state machine

### 1.2.46 show fsm-instances all

#### Command

```
show fsm-instances all
```

#### Parameters

##### show

Show running system information

##### fsm-instances

Show information about finite state machine instances

##### all

Display a list of all FSM instances of all finite state machine

### 1.2.47 show history

#### Command

```
show history
```

#### Parameters

##### show

Show running system information

##### history

Display the session command history

---

### 1.2.48 show lchan [<0-255>] [<0-255>] [<0-7>] [<0-7>]

#### Command

```
show lchan [<0-255>] [<0-255>] [<0-7>] [<0-7>]
```

#### Parameters

show

Show running system information

lchan

Display information about a logical channel

[<0-255>]

BTS Number

[<0-255>]

TRX Number

[<0-7>]

Timeslot Number

[<0-7>]

Logical Channel Number

### 1.2.49 show lchan summary [<0-255>] [<0-255>] [<0-7>] [<0-7>]

#### Command

```
show lchan summary [<0-255>] [<0-255>] [<0-7>] [<0-7>]
```

#### Parameters

show

Show running system information

lchan

Display information about a logical channel

summary

Short summary (used lchans)

[<0-255>]

BTS Number

[<0-255>]

TRX Number

[<0-7>]

Timeslot Number

[<0-7>]

Logical Channel Number

### 1.2.50 show lchan summary-all [<0-255>] [<0-255>] [<0-7>] [<0-7>]

#### Command

```
show lchan summary-all [<0-255>] [<0-255>] [<0-7>] [<0-7>]
```

#### Parameters

##### show

Show running system information

##### lchan

Display information about a logical channel

##### summary-all

Short summary (all lchans)

##### [<0-255>]

BTS Number

##### [<0-255>]

TRX Number

##### [<0-7>]

Timeslot Number

##### [<0-7>]

Logical Channel Number

### 1.2.51 show logging vty

#### Command

```
show logging vty
```

#### Parameters

##### show

Show running system information

##### logging

Show current logging configuration

##### vtty

Show current logging configuration for this vty

### 1.2.52 show mscs

#### Command

```
show mscs
```

#### Parameters

##### show

Show running system information

##### mscs

MSC Connections and State

### 1.2.53 show network

#### Command

```
show network
```

#### Parameters

##### show

Show running system information

##### network

Display information about a GSM NETWORK

### 1.2.54 show nri [<0-1000>]

#### Command

```
show nri [<0-1000>]
```

#### Parameters

##### show

Show running system information

##### nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

##### [<0-1000>]

Optional MSC number to limit to

---

### 1.2.55 show online-help

#### Command

```
show online-help
```

#### Parameters

##### show

Show running system information

##### online-help

Online help

### 1.2.56 show paging [<0-255>]

#### Command

```
show paging [<0-255>]
```

#### Parameters

##### show

Show running system information

##### paging

Display information about paging requests of a BTS

##### [<0-255>]

BTS Number

### 1.2.57 show paging-group <0-255> IMSI

#### Command

```
show paging-group <0-255> IMSI
```

#### Parameters

##### show

Show running system information

##### paging-group

Display the paging group

##### <0-255>

BTS Number

##### IMSI

IMSI

---

### 1.2.58 show position

#### Command

```
show position
```

#### Parameters

show

Show running system information

position

Position information of the BTS

### 1.2.59 show rate-counters

#### Command

```
show rate-counters
```

#### Parameters

show

Show running system information

rate-counters

Show all rate counters

### 1.2.60 show rejected-bts

#### Command

```
show rejected-bts
```

#### Parameters

show

Show running system information

rejected-bts

Display recently rejected BTS devices

### 1.2.61 show statistics

#### Command

```
show statistics
```

#### Parameters

show

Show running system information

statistics

Statistics about the BSC

---

### 1.2.62 show stats

#### Command

```
show stats
```

#### Parameters

show

Show running system information

stats

Show statistical values

### 1.2.63 show stats level (global|peer|subscriber)

#### Command

```
show stats level (global|peer|subscriber)
```

#### Parameters

show

Show running system information

stats

Show statistical values

level

Set the maximum group level

global

Show global groups only

peer

Show global and network peer related groups

subscriber

Show global, peer, and subscriber groups

### 1.2.64 show subscriber all

#### Command

```
show subscriber all
```

#### Parameters

show

Show running system information

subscriber

Display information about subscribers

all

All Subscribers

### 1.2.65 show talloc-context (application|all) (full|brief|DEPTH)

#### Command

```
show talloc-context (application|all) (full|brief|DEPTH)
```

#### Parameters

show

Show running system information

talloc-context

Show talloc memory hierarchy

application

Application's context

all

All contexts, if NULL-context tracking is enabled

full

Display a full talloc memory hierarchy

brief

Display a brief talloc memory hierarchy

DEPTH

Specify required maximal depth value

### 1.2.66 show talloc-context (application|all) (full|brief|DEPTH) filter REGEXP

#### Command

```
show talloc-context (application|all) (full|brief|DEPTH) filter REGEXP
```

#### Parameters

show

Show running system information

talloc-context

Show talloc memory hierarchy

application

Application's context

all

All contexts, if NULL-context tracking is enabled

full

Display a full talloc memory hierarchy

brief

Display a brief talloc memory hierarchy



**DEPTH**

Specify required maximal depth value

**filter**

Filter chunks using regular expression

**REGEXP**

Regular expression

**1.2.67 show talloc-context (application|all) (full|brief|DEPTH) tree ADDRESS****Command**

```
show talloc-context (application|all) (full|brief|DEPTH) tree ADDRESS
```

**Parameters****show**

Show running system information

**talloc-context**

Show talloc memory hierarchy

**application**

Application's context

**all**

All contexts, if NULL-context tracking is enabled

**full**

Display a full talloc memory hierarchy

**brief**

Display a brief talloc memory hierarchy

**DEPTH**

Specify required maximal depth value

**tree**

Display only a specific memory chunk

**ADDRESS**

Chunk address (e.g. 0xdeadbeef)

**1.2.68 show timer [(net|mgw)] [TNNNN]****Command**

```
show timer [(net|mgw)] [TNNNN]
```

**Parameters**

show

Show running system information

timer

Show timers

[net]

GSM network

[mgw]

MGW (Media Gateway) interface

[TNNNN]

T- or X-timer-number -- 3GPP compliant timer number of the format '1234' or 'T1234' or 't1234'; Osmocom-specific timer number of the format: 'X1234' or 'x1234'.

### 1.2.69 show timeslot [<0-255>] [<0-255>] [<0-7>]

Command

```
show timeslot [<0-255>] [<0-255>] [<0-7>]
```

Parameters

show

Show running system information

timeslot

Display information about a TS

[<0-255>]

BTS Number

[<0-255>]

TRX Number

[<0-7>]

Timeslot Number

### 1.2.70 show trx (connected|disconnected)

Command

```
show trx (connected|disconnected)
```

Parameters

show

Show running system information

trx

Display information about a TRX

connected

Show TRX with RSL connected

disconnected

Show TRX with RSL disconnected

### 1.2.71 show trx [<0-255>] [<0-255>]

#### Command

```
show trx [<0-255>] [<0-255>]
```

#### Parameters

##### show

Show running system information

##### trx

Display information about a TRX

[<0-255>]

BTS Number

[<0-255>]

TRX Number

### 1.2.72 show version

#### Command

```
show version
```

#### Parameters

##### show

Show running system information

##### version

Displays program version

### 1.2.73 terminal length <0-512>

#### Command

```
terminal length <0-512>
```

#### Parameters

##### terminal

Set terminal line parameters

##### length

Set number of lines on a screen

<0-512>

Number of lines on screen (0 for no pausing)

---

### 1.2.74 terminal no length

#### Command

```
terminal no length
```

#### Parameters

##### terminal

Set terminal line parameters

##### no

Negate a command or set its defaults

##### length

Set number of lines on a screen

### 1.2.75 who

#### Command

```
who
```

#### Parameters

##### who

Display who is on vty

## 1.3 enable

The enable node is a privileged node, allowing to make changes to the configuration and to access further commands like 'configure'. All commands seen on the view node are also available here.

### 1.3.1 assignment any

#### Command

```
assignment any
```

#### Parameters

##### assignment

Manually trigger assignment (for debugging)

##### any

Pick any actively used TCH/F or TCH/H lchan and re-assign within the same BTS. This will fail if no lchans of the same type are available besides the used one.

### 1.3.2 **bts** <0-255> **om2000 class** (trxc|tg|ts|tf|is|con|dp|mctr|cf|tx|rx) <0-255> <0-255>...

#### Command

```
bts <0-255> om2000 class (trxc|tg|ts|tf|is|con|dp|mctr|cf|tx|rx) <0-255> <0-255> ↵  
    <0-255>
```

#### Parameters

**bts**

BTS related commands

<0-255>

BTS Number

**om2000**

Manipulate the OM2000 managed objects

**class**

Object Class

**trxc**

TRX Controller

**tg**

Trunk Group

**ts**

Timeslot

**tf**

Timing Function

**is**

Interface Switch

**con**

Abis Concentrator

**dp**

Digital Path

**mctr**

Multi Carrier Transceiver

**cf**

Central Function

**tx**

Transmitter

**rx**

Receiver

<0-255>

BTS Number

&lt;0-255&gt;

Associated SO Instance

&lt;0-255&gt;

Instance Number

### 1.3.3 **bts <0-255> om2000 class <0-255> <0-255> <0-255> <0-255>**

Command

```
bts <0-255> om2000 class <0-255> <0-255> <0-255> <0-255>
```

Parameters

bts

BTS related commands

&lt;0-255&gt;

BTS Number

om2000

Manipulate the OML managed objects

class

Object Class

&lt;0-255&gt;

Object Class

&lt;0-255&gt;

BTS Number

&lt;0-255&gt;

Associated SO Instance

&lt;0-255&gt;

Instance Number

### 1.3.4 **bts <0-255> oml class (site-manager|bts|radio-carrier|baseband-transceiver|chann...**

Command

```
bts <0-255> oml class (site-manager|bts|radio-carrier|baseband-transceiver|channel|adjc ↔  
|handover|power-contorl|btse|rack|test|envabtse|bport|gprs-nse|gprs-cell|gprs-nsvc| ↔  
siemenshw) instance <0-255> <0-255> <0-255>
```

Parameters

bts

BTS related commands

&lt;0-255&gt;

BTS Number

oml

Manipulate the OML managed objects

class

Object Class

site-manager

Site Manager Object

bts

BTS Object

radio-carrier

Radio Carrier Object

baseband-transceiver

Baseband Transceiver Object

channel

Channel (Timeslot) Object

adjc

Adjacent Object (Siemens)

handover

Handover Object (Siemens)

power-contorl

Power Control Object (Siemens)

btse

BTSE Object (Siemens)

rack

Rack Object (Siemens)

test

Test Object (Siemens)

envabtse

ENVABTSE Object (Siemens)

bport

BPORT Object (Siemens)

gprs-nse

GPRS NSE Object (ip.access/osmo-bts)

gprs-cell

GPRS Cell Object (ip.acecss/osmo-bts)

gprs-nsvc

GPRS NSVC Object (ip.acecss/osmo-bts)

siemenshw

SIEMENSHW Object (Siemens)

---

instance

Object Instance

<0-255>

BTS Number

<0-255>

TRX Number

<0-255>

TS Number

### 1.3.5 **bts <0-255> oml class <0-255> instance <0-255> <0-255> <0-255>**

Command

```
bts <0-255> oml class <0-255> instance <0-255> <0-255> <0-255>
```

Parameters

bts

BTS related commands

<0-255>

BTS Number

oml

Manipulate the OML managed objects

class

Object Class

<0-255>

Object Class

instance

Object Instance

<0-255>

BTS Number

<0-255>

TRX Number

<0-255>

TS Number



### 1.3.6 **bts <0-255> resend-power-control-defaults**

#### Command

```
bts <0-255> resend-power-control-defaults
```

#### Parameters

bts

BTS Specific Commands

<0-255>

BTS Number

resend-power-control-defaults

Re-generate + re-send default MS/BS Power control parameters

### 1.3.7 **bts <0-255> resend-system-information**

#### Command

```
bts <0-255> resend-system-information
```

#### Parameters

bts

BTS Specific Commands

<0-255>

BTS Number

resend-system-information

Re-generate + re-send BCCH SYSTEM INFORMATION

### 1.3.8 **bts <0-255> trx <0-255> timeslot <0-7> pdch (activate|deactivate)**

#### Command

```
bts <0-255> trx <0-255> timeslot <0-7> pdch (activate|deactivate)
```

#### Parameters

bts

BTS for manual command

<0-255>

BTS Number

trx

TRX for manual command

<0-255>

TRX Number

timeslot

Timeslot for manual command

<0-7>

Timeslot Number

pdch

Packet Data Channel

activate

Activate Dynamic PDCH/TCH (-> PDCH mode)

deactivate

Deactivate Dynamic PDCH/TCH (-> TCH mode)

### 1.3.9 **bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> (activate|deactivate) (hr|...**

Command

```
bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> (activate|deactivate) (hr|fr|efr| ↔  
amr|sig) [<0-7>]
```

Parameters

bts

BTS for manual command

<0-255>

BTS Number

trx

TRX for manual command

<0-255>

TRX Number

timeslot

Timeslot for manual command

<0-7>

Timeslot Number

sub-slot

Sub-slot for manual command

<0-7>

Sub-slot Number

activate

Manual Channel Activation (e.g. for BER test)

deactivate

Manual Channel Deactivation (e.g. for BER test)

hr

Half-Rate v1

fr

Full-Rate

efr

Enhanced Full Rate

amr

Adaptive Multi-Rate

sig

Signalling

[<0-7>]

AMR Mode

### 1.3.10 **bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> assignment**

Command

```
bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> assignment
```

Parameters

bts

BTS for manual command

<0-255>

BTS Number

trx

TRX for manual command

<0-255>

TRX Number

timeslot

Timeslot for manual command

<0-7>

Timeslot Number

sub-slot

Sub-slot for manual command

<0-7>

Sub-slot Number

assignment

Manually trigger assignment (for debugging)

### 1.3.11 **bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> handover <0-255>**

#### Command

```
bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> handover <0-255>
```

#### Parameters

bts

BTS for manual command

<0-255>

BTS Number

trx

TRX for manual command

<0-255>

TRX Number

timeslot

Timeslot for manual command

<0-7>

Timeslot Number

sub-slot

Sub-slot for manual command

<0-7>

Sub-slot Number

handover

Manually trigger handover (for debugging)

<0-255>

New BTS Number

### 1.3.12 **bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> mdcx A.B.C.D <0-65535>**

#### Command

```
bts <0-255> trx <0-255> timeslot <0-7> sub-slot <0-7> mdcx A.B.C.D <0-65535>
```

#### Parameters

bts

BTS for manual command

<0-255>

BTS Number

trx

TRX for manual command

<0-255>

TRX Number

timeslot

Timeslot for manual command

<0-7>

Timeslot Number

sub-slot

Sub-slot for manual command

<0-7>

Sub-slot Number

mdcx

Modify RTP Connection

A.B.C.D

MGW IP Address

<0-65535>

MGW UDP Port

### 1.3.13 configure terminal

Command

```
configure terminal
```

Parameters

configure

Configuration from vty interface

terminal

Configuration terminal

### 1.3.14 copy running-config startup-config

Command

```
copy running-config startup-config
```

Parameters

copy

Copy configuration

running-config

Copy running config to...

startup-config

Copy running config to startup config (same as write file)

### 1.3.15 ctrl-interface generate-trap TRAP VALUE

#### Command

```
ctrl-interface generate-trap TRAP VALUE
```

#### Parameters

##### ctrl-interface

Commands related to the CTRL Interface

##### generate-trap

Generate a TRAP for test purpose

##### TRAP

Identity/Name of the TRAP variable

##### VALUE

Value of the TRAP variable

### 1.3.16 disable

#### Command

```
disable
```

#### Parameters

##### disable

Turn off privileged mode command

### 1.3.17 drop bts connection <0-65535> (oml|rs1)

#### Command

```
drop bts connection <0-65535> (oml|rs1)
```

#### Parameters

##### drop

Debug/Simulation command to drop Abis/IP BTS

##### bts

Debug/Simulation command to drop Abis/IP BTS

##### connection

Debug/Simulation command to drop Abis/IP BTS

##### <0-65535>

BTS NR

##### oml

Drop OML Connection

##### rs1

Drop RSL Connection

### 1.3.18 generate-location-state-trap <0-255>

#### Command

```
generate-location-state-trap <0-255>
```

#### Parameters

generate-location-state-trap

Generate location state report

<0-255>

BTS to report

### 1.3.19 handover any

#### Command

```
handover any
```

#### Parameters

handover

Manually trigger handover (for debugging)

any

Pick any actively used TCH/F or TCH/H lchan and handover to any other BTS. This is likely to fail if not all BTS are guaranteed to be reachable by the MS.

### 1.3.20 handover any to arfcn <0-1023> bsic (<0-63>|any)

#### Command

```
handover any to arfcn <0-1023> bsic (<0-63>|any)
```

#### Parameters

handover

Manually trigger handover (for debugging)

any

Pick any actively used TCH/F or TCH/H lchan to handover to another cell. This is likely to fail outside of a lab setup where you are certain that all MS are able to see the target cell.

to

'to'

arfcn

ARFCN of neighbor cell

---

<0-1023>

ARFCN value

bsic

BSIC of neighbor cell

<0-63>

BSIC value

any

for all BSICs / use any BSIC in this ARFCN

### 1.3.21 logging color (0|1)

Command

```
logging color (0|1)
```

Parameters

logging

Configure logging

color

Configure color-printing for log messages

0

Don't use color for printing messages

1

Use color for printing messages

### 1.3.22 logging disable

Command

```
logging disable
```

Parameters

logging

Configure logging

disable

Disables logging to this vty



### 1.3.23 logging enable

This command is required to make logging commands available on the telnet VTY.

#### Command

```
logging enable
```

#### Parameters

logging

Configure logging

enable

Enables logging to this vty

### 1.3.24 logging filter all (0|1)

Disable/enable general log output on a given target. Typically, 'logging filter all 1' allows to see the usual log output on a given target. Setting to '0' can be useful when logging to the telnet VTY console: mute all log output to allow typing VTY commands on the telnet prompt without interference from log output; 'logging filter all 1' then re-enables logging in the same log output configuration as before. Some applications provide more specific filters, e.g. to log a given IMSI only. To employ such filters, set 'logging filter all 0' to disable general logging, and then enable a more specific filter instead.

#### Command

```
logging filter all (0|1)
```

#### Parameters

logging

Configure logging

filter

Filter log messages

all

Do you want to log all messages?

0

Only print messages matched by other filters

1

Bypass filter and print all messages

### 1.3.25 logging filter imsi IMSI

#### Command

```
logging filter imsi IMSI
```

#### Parameters

---

**logging**

Configure logging

**filter**

Filter log messages

**imsi**

Filter log messages by IMSI

**IMSI**

IMSI to be used as filter

**1.3.26 logging level (rll|mm|rr|rs|nm|pag|meas|msc|ho|hodec|ref|ctrl|filter|pcu|lcls|c...****Command**

```
logging level (rll|mm|rr|rs|nm|pag|meas|msc|ho|hodec|ref|ctrl|filter|pcu|lcls|chan|ts| ↵
as|cbs|lcs|reset|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgsup|loap ↵
|lss7|lsccp|lsua|lm3ua|lmgcp|ljibuf|lrspro|lms|lbssgp) (debug|info|notice|error| ↵
fatal)
```

**Parameters****logging**

Configure logging

**level**

Set the log level for a specified category

**rll**

A-bis Radio Link Layer (RLL)

**mm**

Layer3 Mobility Management (MM)

**rr**

Layer3 Radio Resource (RR)

**rs**

A-bis Radio Signalling Link (RSL)

**nm**

A-bis Network Management / O&amp;M (NM/OML)

**pag**

Paging Subsystem

**meas**

Radio Measurement Processing

**msc**

Mobile Switching Center

**ho**

Hand-Over Process

---

hodec  
    Hand-Over Decision

ref  
    Reference Counting

ctrl  
    Control interface

filter  
    BSC/NAT IMSI based filtering

pcu  
    PCU Interface

lcls  
    Local Call, Local Switch

chan  
    lchan FSM

ts  
    timeslot FSM

as  
    assignment FSM

cbs  
    Cell Broadcast System

lcs  
    Location Services

reset  
    RESET/ACK on A and Lb interfaces

lglobal  
    Library-internal global log family

llapd  
    LAPD in libosmogsm

linp  
    A-bis Input Subsystem

lmux  
    A-bis B-Subchannel TRAU Frame Multiplex

lmi  
    A-bis Input Driver for Signalling

lmib  
    A-bis Input Driver for B-Channels (voice)

lsms  
    Layer3 Short Message Service (SMS)

---

---

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

lsccp  
libosmo-sigtran SCCP Implementation

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

lmgcp  
libosmo-mgcp Media Gateway Control Protocol

ljibuf  
libosmo-netif Jitter Buffer

lrspro  
Remote SIM protocol

lns  
GPRS NS layer

lbssgp  
GPRS BSSGP layer

debug  
Log debug messages and higher levels

info  
Log informational messages and higher levels

notice  
Log noticeable messages and higher levels

error  
Log error messages and higher levels

fatal  
Log only fatal messages

---

### 1.3.27 logging level force-all (debug|info|notice|error|fatal)

#### Command

```
logging level force-all (debug|info|notice|error|fatal)
```

#### Parameters

##### logging

Configure logging

##### level

Set the log level for a specified category

##### force-all

Globally force all logging categories to a specific level. This is released by the 'no logging level force-all' command. Note: any 'logging level <category> <level>' commands will have no visible effect after this, until the forced level is released.

##### debug

Log debug messages and higher levels

##### info

Log informational messages and higher levels

##### notice

Log noticeable messages and higher levels

##### error

Log error messages and higher levels

##### fatal

Log only fatal messages

### 1.3.28 logging level set-all (debug|info|notice|error|fatal)

#### Command

```
logging level set-all (debug|info|notice|error|fatal)
```

#### Parameters

##### logging

Configure logging

##### level

Set the log level for a specified category

##### set-all

Once-off set all categories to the given log level. There is no single command to take back these changes -- each category is set to the given level, period.

##### debug

Log debug messages and higher levels

---

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.3.29 logging print category (0|1)

Command

```
logging print category (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem name

### 1.3.30 logging print category-hex (0|1)

Command

```
logging print category-hex (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category-hex

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem nr in hex ('<000b>')

### 1.3.31 logging print extended-timestamp (0|1)

#### Command

```
logging print extended-timestamp (0|1)
```

#### Parameters

##### logging

Configure logging

##### print

Log output settings

##### extended-timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp with YYYYMMDDhhmmssnnn

### 1.3.32 logging print file (0|1|basename) [last]

#### Command

```
logging print file (0|1|basename) [last]
```

#### Parameters

##### logging

Configure logging

##### print

Log output settings

##### file

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the source file and line

##### basename

Prefix each log message with the source file's basename (strip leading paths) and line

##### [last]

Log source file info at the end of a log line. If omitted, log source file info just before the log text.

### 1.3.33 logging print level (0|1)

#### Command

```
logging print level (0|1)
```

#### Parameters

##### logging

Configure logging

##### print

Log output settings

##### level

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the log level name

### 1.3.34 logging print thread-id (0|1)

#### Command

```
logging print thread-id (0|1)
```

#### Parameters

##### logging

Configure logging

##### print

Log output settings

##### thread-id

Configure log message logging Thread ID

0

Don't prefix each log message

1

Prefix each log message with current Thread ID



### 1.3.35 logging set-log-mask MASK

#### Command

```
logging set-log-mask MASK
```

#### Parameters

##### logging

Configure logging

##### set-log-mask

Set the logmask of this logging target

##### MASK

List of logging categories to log, e.g. 'abc:mno:xyz'. Available log categories depend on the specific application, refer to the 'logging level' command. Optionally add individual log levels like 'abc,1:mno,3:xyz,5', where the level numbers are LOGL\_DEBUG=1 LOGL\_INFO=3 LOGL\_NOTICE=5 LOGL\_ERROR=7 LOGL\_FATAL=8

### 1.3.36 logging timestamp (0|1)

#### Command

```
logging timestamp (0|1)
```

#### Parameters

##### logging

Configure logging

##### timestamp

Configure log message timestamping

##### 0

Don't prefix each log message

##### 1

Prefix each log message with current timestamp

### 1.3.37 logp (rll|mm|rr|rs|nm|pag|meas|msc|ho|hodec|ref|ctrl|filter|pcu|lcls|chan|ts|as...

#### Command

```
logp (rll|mm|rr|rs|nm|pag|meas|msc|ho|hodec|ref|ctrl|filter|pcu|lcls|chan|ts|as|cbs| ↵
    lcs|reset|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtpl|lstats|lgsup|loap|lss7| ↵
    lscdp|lsua|lm3ua|lmgcp|ljibuf|lrspro|lms|lbssgp) (debug|info|notice|error|fatal) . ↵
    LOGMESSAGE
```

#### Parameters

logp

Print a message on all log outputs; useful for placing markers in test logs

rl

A-bis Radio Link Layer (RLL)

mm

Layer3 Mobility Management (MM)

rr

Layer3 Radio Resource (RR)

rsl

A-bis Radio Signalling Link (RSL)

nm

A-bis Network Management / O&M (NM/OML)

pag

Paging Subsystem

meas

Radio Measurement Processing

msc

Mobile Switching Center

ho

Hand-Over Process

hodec

Hand-Over Decision

ref

Reference Counting

ctrl

Control interface

filter

BSC/NAT IMSI based filtering

pcu

PCU Interface

lcls

Local Call, Local Switch

chan

lchan FSM

ts

timeslot FSM

as

assignment FSM

---

---

cbs  
Cell Broadcast System

lcs  
Location Services

reset  
RESET/ACK on A and Lb interfaces

lglobal  
Library-internal global log family

llapd  
LAPD in libosmogsm

linp  
A-bis Input Subsystem

lmux  
A-bis B-Subchannel TRAU Frame Multiplex

lmi  
A-bis Input Driver for Signalling

lmib  
A-bis Input Driver for B-Channels (voice)

lsms  
Layer3 Short Message Service (SMS)

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

lsccp  
libosmo-sigtran SCCP Implementation

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

---

lmgcp  
libosmo-mgcp Media Gateway Control Protocol

ljibuf  
libosmo-netif Jitter Buffer

lrspro  
Remote SIM protocol

lms  
GPRS NS layer

lbssgp  
GPRS BSSGP layer

debug  
Log debug messages and higher levels

info  
Log informational messages and higher levels

notice  
Log noticeable messages and higher levels

error  
Log error messages and higher levels

fatal  
Log only fatal messages

.LOGMESSAGE  
Arbitrary message to log on given category and log level

### 1.3.38 no logging level force-all

Command

```
no logging level force-all
```

Parameters

no

Negate a command or set its defaults

logging

Configure logging

level

Set the log level for a specified category

force-all

Release any globally forced log level set with 'logging level force-all <level>'

### 1.3.39 restart-bts <0-65535>

#### Command

```
restart-bts <0-65535>
```

#### Parameters

##### restart-bts

Restart ip.access nanoBTS through OML

##### <0-65535>

BTS Number

### 1.3.40 show alarms

#### Command

```
show alarms
```

#### Parameters

##### show

Show running system information

##### alarms

Show current logging configuration

### 1.3.41 show asciidoc counters

#### Command

```
show asciidoc counters
```

#### Parameters

##### show

Show running system information

##### asciidoc

Asciidoc generation

##### counters

Generate table of all registered counters

---

### 1.3.42 show bts <0-255> fail-rep [reset]

#### Command

```
show bts <0-255> fail-rep [reset]
```

#### Parameters

##### show

Show running system information

##### bts

Display information about a BTS

##### <0-255>

BTS number

##### fail-rep

OML failure reports

##### [reset]

Clear the list of failure reports after showing them

### 1.3.43 show bts <0-255> neighbor arfcn <0-1023> bsic (<0-63>|any)

#### Command

```
show bts <0-255> neighbor arfcn <0-1023> bsic (<0-63>|any)
```

#### Parameters

##### show

Show running system information

##### bts

Display information about a BTS

##### <0-255>

BTS number

##### neighbor

Query which cell would be the target for this neighbor ARFCN+BSIC

##### arfcn

ARFCN of neighbor cell

##### <0-1023>

ARFCN value

##### bsic

BSIC of neighbor cell

##### <0-63>

BSIC value

##### any

for all BSICs / use any BSIC in this ARFCN

### 1.3.44 show bts <0-255> om2k-mo

#### Command

```
show bts <0-255> om2k-mo
```

#### Parameters

show

Show running system information

bts

Display information about a BTS

<0-255>

BTS number

om2k-mo

OM2000 Managed Object information

### 1.3.45 show bts <0-255> smscb [(basic|extended)]

#### Command

```
show bts <0-255> smscb [(basic|extended)]
```

#### Parameters

show

Show running system information

bts

Display information about a BTS

<0-255>

BTS number

smscb

SMS Cell Broadcast State

[basic]

Show only information related to CBCH BASIC

[extended]

Show only information related to CBCH EXTENDED

### 1.3.46 show bts [<0-255>]

#### Command

```
show bts [<0-255>]
```

#### Parameters

##### show

Show running system information

##### bts

Display information about a BTS

##### [<0-255>]

BTS number

### 1.3.47 show cbc

#### Command

```
show cbc
```

#### Parameters

##### show

Show running system information

##### cbc

Display state of CBC / CBSP

### 1.3.48 show conns

#### Command

```
show conns
```

#### Parameters

##### show

Show running system information

##### conns

Display currently active subscriber connections



### 1.3.49 show cpu-sched threads

#### Command

```
show cpu-sched threads
```

#### Parameters

show

Show running system information

cpu-sched

Show Sched section information

threads

Show information about running threads)

### 1.3.50 show cs7 (sua|m3ua|ipa) [<0-65534>]

#### Command

```
show cs7 (sua|m3ua|ipa) [<0-65534>]
```

#### Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

sua

SCCP User Adaptation

m3ua

MTP3 User Adaptation

ipa

IPA Multiplex (SCCP Lite)

[<0-65534>]

Port Number

### 1.3.51 show cs7 config

#### Command

```
show cs7 config
```

#### Parameters

---

show

Show running system information

cs7

ITU-T Signaling System 7

config

Currently running cs7 configuration

### 1.3.52 show cs7 instance <0-15> as (active|all|m3ua|sua)

Command

```
show cs7 instance <0-15> as (active|all|m3ua|sua)
```

Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

as

Application Server (AS)

active

Display all active ASs

all

Display all ASs (default)

m3ua

Display all m3ua ASs

sua

Display all SUA ASs

### 1.3.53 show cs7 instance <0-15> asp

Command

```
show cs7 instance <0-15> asp
```

Parameters

---

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

asp

Application Server Process (ASP)

### 1.3.54 show cs7 instance <0-15> sccp addressbook

Command

```
show cs7 instance <0-15> sccp addressbook
```

Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

addressbook

List all SCCP addressbook entries

### 1.3.55 show cs7 instance <0-15> sccp connections

Command

```
show cs7 instance <0-15> sccp connections
```

Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

connections

Show List of active SCCP connections

### 1.3.56 show cs7 instance <0-15> sccp ssn <0-65535>

Command

```
show cs7 instance <0-15> sccp ssn <0-65535>
```

Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

ssn

Find an SCCP User registered for the given SSN

<0-65535>

Subsystem Number (SSN)

### 1.3.57 show cs7 instance <0-15> sccp timers

Command

```
show cs7 instance <0-15> sccp timers
```

Parameters

---

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signaling Connection Control Part

timers

Show List of SCCP timers

### 1.3.58 show cs7 instance <0-15> sccp users

Command

```
show cs7 instance <0-15> sccp users
```

Parameters

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

sccp

Signalling Connection Control Part

users

Show List of SCCP Users registered

### 1.3.59 show cs7 instance <0-15> users

Command

```
show cs7 instance <0-15> users
```

Parameters

---

show

Show running system information

cs7

ITU-T Signaling System 7

instance

An instance of the SS7 stack

<0-15>

An instance of the SS7 stack

users

User Table

### 1.3.60 show e1\_driver

Command

```
show e1_driver
```

Parameters

show

Show running system information

e1\_driver

Display information about available E1 drivers

### 1.3.61 show e1\_line [line\_nr] [stats]

Command

```
show e1_line [line_nr] [stats]
```

Parameters

show

Show running system information

e1\_line

Display information about a E1 line

[line\_nr]

E1 Line Number

[stats]

Include statistics

### 1.3.62 show e1\_timeslot [line\_nr] [ts\_nr]

#### Command

```
show e1_timeslot [line_nr] [ts_nr]
```

#### Parameters

show

Show running system information

e1\_timeslot

Display information about a E1 timeslot

[line\_nr]

E1 Line Number

[ts\_nr]

E1 Timeslot Number

### 1.3.63 show fsm NAME

#### Command

```
show fsm NAME
```

#### Parameters

show

Show running system information

fsm

Show information about finite state machines

NAME

Display information about a single named finite state machine

### 1.3.64 show fsm all

#### Command

```
show fsm all
```

#### Parameters

show

Show running system information

fsm

Show information about finite state machines

all

Display a list of all registered finite state machines

---

### 1.3.65 show fsm-instances NAME

#### Command

```
show fsm-instances NAME
```

#### Parameters

##### show

Show running system information

##### fsm-instances

Show information about finite state machine instances

##### NAME

Display a list of all FSM instances of the named finite state machine

### 1.3.66 show fsm-instances all

#### Command

```
show fsm-instances all
```

#### Parameters

##### show

Show running system information

##### fsm-instances

Show information about finite state machine instances

##### all

Display a list of all FSM instances of all finite state machine

### 1.3.67 show history

#### Command

```
show history
```

#### Parameters

##### show

Show running system information

##### history

Display the session command history



### 1.3.68 show lchan [<0-255>] [<0-255>] [<0-7>] [<0-7>]

#### Command

```
show lchan [<0-255>] [<0-255>] [<0-7>] [<0-7>]
```

#### Parameters

show

Show running system information

lchan

Display information about a logical channel

[<0-255>]

BTS Number

[<0-255>]

TRX Number

[<0-7>]

Timeslot Number

[<0-7>]

Logical Channel Number

### 1.3.69 show lchan summary [<0-255>] [<0-255>] [<0-7>] [<0-7>]

#### Command

```
show lchan summary [<0-255>] [<0-255>] [<0-7>] [<0-7>]
```

#### Parameters

show

Show running system information

lchan

Display information about a logical channel

summary

Short summary (used lchans)

[<0-255>]

BTS Number

[<0-255>]

TRX Number

[<0-7>]

Timeslot Number

[<0-7>]

Logical Channel Number

### 1.3.70 show lchan summary-all [<0-255>] [<0-255>] [<0-7>] [<0-7>]

#### Command

```
show lchan summary-all [<0-255>] [<0-255>] [<0-7>] [<0-7>]
```

#### Parameters

##### show

Show running system information

##### lchan

Display information about a logical channel

##### summary-all

Short summary (all lchans)

##### [<0-255>]

BTS Number

##### [<0-255>]

TRX Number

##### [<0-7>]

Timeslot Number

##### [<0-7>]

Logical Channel Number

### 1.3.71 show logging vty

#### Command

```
show logging vty
```

#### Parameters

##### show

Show running system information

##### logging

Show current logging configuration

##### vtty

Show current logging configuration for this vty

---

### 1.3.72 show mscs

#### Command

```
show mscs
```

#### Parameters

##### show

Show running system information

##### mscs

MSC Connections and State

### 1.3.73 show network

#### Command

```
show network
```

#### Parameters

##### show

Show running system information

##### network

Display information about a GSM NETWORK

### 1.3.74 show nri [<0-1000>]

#### Command

```
show nri [<0-1000>]
```

#### Parameters

##### show

Show running system information

##### nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

##### [<0-1000>]

Optional MSC number to limit to

---

### 1.3.75 show online-help

#### Command

```
show online-help
```

#### Parameters

##### show

Show running system information

##### online-help

Online help

### 1.3.76 show paging [<0-255>]

#### Command

```
show paging [<0-255>]
```

#### Parameters

##### show

Show running system information

##### paging

Display information about paging requests of a BTS

##### [<0-255>]

BTS Number

### 1.3.77 show paging-group <0-255> IMSI

#### Command

```
show paging-group <0-255> IMSI
```

#### Parameters

##### show

Show running system information

##### paging-group

Display the paging group

##### <0-255>

BTS Number

##### IMSI

IMSI

---

### 1.3.78 show position

#### Command

```
show position
```

#### Parameters

show

Show running system information

position

Position information of the BTS

### 1.3.79 show rate-counters

#### Command

```
show rate-counters
```

#### Parameters

show

Show running system information

rate-counters

Show all rate counters

### 1.3.80 show rejected-bts

#### Command

```
show rejected-bts
```

#### Parameters

show

Show running system information

rejected-bts

Display recently rejected BTS devices

### 1.3.81 show startup-config

#### Command

```
show startup-config
```

#### Parameters

show

Show running system information

startup-config

Contentes of startup configuration

---

### 1.3.82 show statistics

#### Command

```
show statistics
```

#### Parameters

##### show

Show running system information

##### statistics

Statistics about the BSC

### 1.3.83 show stats

#### Command

```
show stats
```

#### Parameters

##### show

Show running system information

##### stats

Show statistical values

### 1.3.84 show stats level (global|peer|subscriber)

#### Command

```
show stats level (global|peer|subscriber)
```

#### Parameters

##### show

Show running system information

##### stats

Show statistical values

##### level

Set the maximum group level

##### global

Show global groups only

##### peer

Show global and network peer related groups

##### subscriber

Show global, peer, and subscriber groups

---

### 1.3.85 show subscriber all

#### Command

```
show subscriber all
```

#### Parameters

##### show

Show running system information

##### subscriber

Display information about subscribers

##### all

All Subscribers

### 1.3.86 show talloc-context (application|all) (full|brief|DEPTH)

#### Command

```
show talloc-context (application|all) (full|brief|DEPTH)
```

#### Parameters

##### show

Show running system information

##### talloc-context

Show talloc memory hierarchy

##### application

Application's context

##### all

All contexts, if NULL-context tracking is enabled

##### full

Display a full talloc memory hierarchy

##### brief

Display a brief talloc memory hierarchy

##### DEPTH

Specify required maximal depth value

### 1.3.87 show talloc-context (application|all) (full|brief|DEPTH) filter REGEXP

#### Command

```
show talloc-context (application|all) (full|brief|DEPTH) filter REGEXP
```

#### Parameters

##### show

Show running system information

##### talloc-context

Show talloc memory hierarchy

##### application

Application's context

##### all

All contexts, if NULL-context tracking is enabled

##### full

Display a full talloc memory hierarchy

##### brief

Display a brief talloc memory hierarchy

##### DEPTH

Specify required maximal depth value

##### filter

Filter chunks using regular expression

##### REGEXP

Regular expression

### 1.3.88 show talloc-context (application|all) (full|brief|DEPTH) tree ADDRESS

#### Command

```
show talloc-context (application|all) (full|brief|DEPTH) tree ADDRESS
```

#### Parameters

##### show

Show running system information

##### talloc-context

Show talloc memory hierarchy

##### application

Application's context

##### all

All contexts, if NULL-context tracking is enabled

---



full

Display a full talloc memory hierarchy

brief

Display a brief talloc memory hierarchy

DEPTH

Specify required maximal depth value

tree

Display only a specific memory chunk

ADDRESS

Chunk address (e.g. 0xdeadbeef)

### 1.3.89 show timer [(net|mgw)] [TNNNN]

Command

```
show timer [(net|mgw)] [TNNNN]
```

Parameters

show

Show running system information

timer

Show timers

[net]

GSM network

[mgw]

MGW (Media Gateway) interface

[TNNNN]

T- or X-timer-number -- 3GPP compliant timer number of the format '1234' or 'T1234' or 't1234'; Osmocom-specific timer number of the format: 'X1234' or 'x1234'.

### 1.3.90 show timeslot [<0-255>] [<0-255>] [<0-7>]

Command

```
show timeslot [<0-255>] [<0-255>] [<0-7>]
```

Parameters

show

Show running system information

timeslot

Display information about a TS

[<0-255>]

BTS Number

[<0-255>]

TRX Number

[<0-7>]

Timeslot Number

### 1.3.91 **show trx (connected|disconnected)**

Command

```
show trx (connected|disconnected)
```

Parameters

show

Show running system information

trx

Display information about a TRX

connected

Show TRX with RSL connected

disconnected

Show TRX with RSL disconnected

### 1.3.92 **show trx [<0-255>] [<0-255>]**

Command

```
show trx [<0-255>] [<0-255>]
```

Parameters

show

Show running system information

trx

Display information about a TRX

[<0-255>]

BTS Number

[<0-255>]

TRX Number

### 1.3.93 show version

#### Command

```
show version
```

#### Parameters

##### show

Show running system information

##### version

Displays program version

### 1.3.94 stats report

#### Command

```
stats report
```

#### Parameters

##### stats

Stats related commands

##### report

Manurally trigger reporting of stats

### 1.3.95 stats reset

#### Command

```
stats reset
```

#### Parameters

##### stats

Stats related commands

##### reset

Reset all stats

### 1.3.96 terminal length <0-512>

#### Command

```
terminal length <0-512>
```

#### Parameters

##### terminal

Set terminal line parameters

##### length

Set number of lines on a screen

##### <0-512>

Number of lines on screen (0 for no pausing)

### 1.3.97 terminal monitor

#### Command

```
terminal monitor
```

#### Parameters

##### terminal

Set terminal line parameters

##### monitor

Copy debug output to the current terminal line

### 1.3.98 terminal no length

#### Command

```
terminal no length
```

#### Parameters

##### terminal

Set terminal line parameters

##### no

Negate a command or set its defaults

##### length

Set number of lines on a screen

### 1.3.99 terminal no monitor

#### Command

```
terminal no monitor
```

#### Parameters

##### terminal

Set terminal line parameters

##### no

Negate a command or set its defaults

##### monitor

Copy debug output to the current terminal line

### 1.3.100 who

#### Command

```
who
```

#### Parameters

##### who

Display who is on vty

## 1.4 config

The config node is the root for all configuration commands, which are identical to the config file format. Changes made on the telnet VTY can be made persistent with the 'write file' command.

### 1.4.1 banner motd default

#### Command

```
banner motd default
```

#### Parameters

##### banner

Set banner string

##### motd

Strings for motd

##### default

Default string

---

### 1.4.2 banner motd file [FILE]

#### Command

```
banner motd file [FILE]
```

#### Parameters

##### banner

Set banner

##### motd

Banner for motd

##### file

Banner from a file

##### [FILE]

Filename

### 1.4.3 bsc

#### Command

```
bsc
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### bsc

Configure BSC

### 1.4.4 cbc

#### Command

```
cbc
```

#### Parameters

##### cbc

Configure CBSP Link to Cell Broadcast Centre

---

### 1.4.5 cpu-sched

#### Command

```
cpu-sched
```

#### Parameters

cpu-sched

Configure CPU Scheduler related settings

### 1.4.6 cs7 instance <0-15>

#### Command

```
cs7 instance <0-15>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

cs7

ITU-T Signaling System 7

instance

Configure a SS7 Instance

<0-15>

An instance of the SS7 stack

### 1.4.7 ctrl

#### Command

```
ctrl
```

#### Parameters

ctrl

Configure the Control Interface

### 1.4.8 e1\_input

#### Command

```
e1_input
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

e1\_input

Configure E1/T1/J1 TDM input

### 1.4.9 enable password (8|) WORD

#### Command

```
enable password (8|) WORD
```

#### Parameters

enable

Modify enable password parameters

password

Assign the privileged level password

8

Specifies a HIDDEN password will follow

dummy string

WORD

The HIDDEN 'enable' password string

### 1.4.10 enable password LINE

#### Command

```
enable password LINE
```

#### Parameters

enable

Modify enable password parameters

password

Assign the privileged level password

LINE

The UNENCRYPTED (cleartext) 'enable' password

---



### 1.4.11 hostname WORD

#### Command

```
hostname WORD
```

#### Parameters

##### hostname

Set system's network name

##### WORD

This system's network name

### 1.4.12 line vty

#### Command

```
line vty
```

#### Parameters

##### line

Configure a terminal line

##### vtty

Virtual terminal

### 1.4.13 log alarms <2-32700>

#### Command

```
log alarms <2-32700>
```

#### Parameters

##### log

Configure logging sub-system

##### alarms

Logging alarms to osmo\_strrb

##### <2-32700>

Maximum number of messages to log

---

### 1.4.14 log file .FILENAME

#### Command

```
log file .FILENAME
```

#### Parameters

log

Configure logging sub-system

file

Logging to text file

.FILENAME

Filename

### 1.4.15 log gsmtap [HOSTNAME]

#### Command

```
log gsmtap [HOSTNAME]
```

#### Parameters

log

Configure logging sub-system

gsmtap

Logging via GSMTAP

[HOSTNAME]

Host name to send the GSMTAP logging to (UDP port 4729)

### 1.4.16 log stderr

#### Command

```
log stderr
```

#### Parameters

log

Configure logging sub-system

stderr

Logging via STDERR of the process

### 1.4.17 log syslog (authpriv|cron|daemon|ftp|lpr|mail|news|user|uucp)

#### Command

```
log syslog (authpriv|cron|daemon|ftp|lpr|mail|news|user|uucp)
```

#### Parameters

##### log

Configure logging sub-system

##### syslog

Logging via syslog

##### authpriv

Security/authorization messages facility

##### cron

Clock daemon (cron/at) facility

##### daemon

General system daemon facility

##### ftp

Ftp daemon facility

##### lpr

Line printer facility

##### mail

Mail facility

##### news

News facility

##### user

Generic facility

##### uucp

UUCP facility

### 1.4.18 log syslog local <0-7>

#### Command

```
log syslog local <0-7>
```

#### Parameters

##### log

Configure logging sub-system

##### syslog

Logging via syslog

---

local

Syslog LOCAL facility

<0-7>

Local facility number

### 1.4.19 log systemd-journal [raw]

Command

```
log systemd-journal [raw]
```

Parameters

log

Configure logging sub-system

systemd-journal

Logging to systemd-journal

[raw]

Offload rendering of the meta information (location, category) to systemd

### 1.4.20 msc [<0-1000>]

Command

```
msc [<0-1000>]
```

Global attributes

Flag: !

This command applies immediately

Parameters

msc

Configure MSC details

[<0-1000>]

MSC connection to configure

### 1.4.21 network

#### Command

```
network
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

network

Configure the GSM network

### 1.4.22 no banner motd

#### Command

```
no banner motd
```

#### Parameters

no

Negate a command or set its defaults

banner

Set banner string

motd

Strings for motd

### 1.4.23 no enable password

#### Command

```
no enable password
```

#### Parameters

no

Negate a command or set its defaults

enable

Modify enable password parameters

password

Assign the privileged level password

---

### 1.4.24 no hostname [HOSTNAME]

#### Command

```
no hostname [HOSTNAME]
```

#### Parameters

no

Negate a command or set its defaults

hostname

Reset system's network name

[HOSTNAME]

Host name of this router

### 1.4.25 no log alarms

#### Command

```
no log alarms
```

#### Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

alarms

Logging alarms to osmo\_strrb

### 1.4.26 no log file .FILENAME

#### Command

```
no log file .FILENAME
```

#### Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

file

Logging to text file

.FILENAME

Filename

### 1.4.27 no log stderr

#### Command

```
no log stderr
```

#### Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

stderr

Logging via STDERR of the process

### 1.4.28 no log syslog

#### Command

```
no log syslog
```

#### Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

syslog

Logging via syslog

### 1.4.29 no log systemd-journal

#### Command

```
no log systemd-journal
```

#### Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

systemd-journal

Logging to systemd-journal

---

### 1.4.30 no service advanced-vty

#### Command

```
no service advanced-vty
```

#### Parameters

no

Negate a command or set its defaults

service

Set up miscellaneous service

advanced-vty

Enable advanced mode vty interface

### 1.4.31 no service terminal-length [<0-512>]

#### Command

```
no service terminal-length [<0-512>]
```

#### Parameters

no

Negate a command or set its defaults

service

Set up miscellaneous service

terminal-length

System wide terminal length configuration

[<0-512>]

Number of lines of VTY (0 means no line control)

### 1.4.32 no stats reporter log

#### Command

```
no stats reporter log
```

#### Parameters

no

Negate a command or set its defaults

stats

Configure stats sub-system

reporter

Configure a stats reporter

log

Report to the logger



### 1.4.33 no stats reporter statsd

#### Command

```
no stats reporter statsd
```

#### Parameters

no

Negate a command or set its defaults

stats

Configure stats sub-system

reporter

Configure a stats reporter

statsd

Report to a STATSD server

### 1.4.34 password (8|) WORD

#### Command

```
password (8|) WORD
```

#### Parameters

password

Assign the terminal connection password

8

Specifies a HIDDEN password will follow

dummy string

WORD

The HIDDEN line password string

### 1.4.35 password LINE

#### Command

```
password LINE
```

#### Parameters

password

Assign the terminal connection password

LINE

The UNENCRYPTED (cleartext) line password

---

### 1.4.36 service advanced-vty

#### Command

```
service advanced-vty
```

#### Parameters

##### service

Set up miscellaneous service

##### advanced-vty

Enable advanced mode vty interface

### 1.4.37 service terminal-length <0-512>

#### Command

```
service terminal-length <0-512>
```

#### Parameters

##### service

Set up miscellaneous service

##### terminal-length

System wide terminal length configuration

##### <0-512>

Number of lines of VTY (0 means no line control)

### 1.4.38 show history

#### Command

```
show history
```

#### Parameters

##### show

Show running system information

##### history

Display the session command history

---

### 1.4.39 stats interval <0-65535>

#### Command

```
stats interval <0-65535>
```

#### Parameters

stats

Configure stats sub-system

interval

Set the reporting interval

<0-65535>

Interval in seconds (0 disables the reporting interval)

### 1.4.40 stats reporter log

#### Command

```
stats reporter log
```

#### Parameters

stats

Configure stats sub-system

reporter

Configure a stats reporter

log

Report to the logger

### 1.4.41 stats reporter statsd

#### Command

```
stats reporter statsd
```

#### Parameters

stats

Configure stats sub-system

reporter

Configure a stats reporter

statsd

Report to a STATSD server

---

## 1.5 config-log

The log node is commonly available in all Osmocom programs and allows configuring logging to stderr and/or log files, including logging category and level filtering as well as output formatting options. Note that the 'logging enable' command is required to make logging commands available on the telnet VTY.

### 1.5.1 logging color (0|1)

Command

```
logging color (0|1)
```

Parameters

logging

Configure logging

color

Configure color-printing for log messages

0

Don't use color for printing messages

1

Use color for printing messages

### 1.5.2 logging filter all (0|1)

Disable/enable general log output on a given target. Typically, 'logging filter all 1' allows to see the usual log output on a given target. Setting to '0' can be useful when logging to the telnet VTY console: mute all log output to allow typing VTY commands on the telnet prompt without interference from log output; 'logging filter all 1' then re-enables logging in the same log output configuration as before. Some applications provide more specific filters, e.g. to log a given IMSI only. To employ such filters, set 'logging filter all 0' to disable general logging, and then enable a more specific filter instead.

Command

```
logging filter all (0|1)
```

Parameters

logging

Configure logging

filter

Filter log messages

all

Do you want to log all messages?

0

Only print messages matched by other filters

1

Bypass filter and print all messages

---

### 1.5.3 logging filter imsi IMSI

#### Command

```
logging filter imsi IMSI
```

#### Parameters

##### logging

Configure logging

##### filter

Filter log messages

##### imsi

Filter log messages by IMSI

##### IMSI

IMSI to be used as filter

### 1.5.4 logging level (rll|mm|rr|rs|nm|pag|meas|msc|ho|hodec|ref|ctrl|filter|pcu|lcls|c...

#### Command

```
logging level (rll|mm|rr|rs|nm|pag|meas|msc|ho|hodec|ref|ctrl|filter|pcu|lcls|chan|ts| ↵
as|cbs|lcs|reset|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgsup|loap ↵
|lss7|lsccp|lsua|lm3ua|lmgcp|ljibuf|lrspro|lns|lbssgp) (debug|info|notice|error| ↵
fatal)
```

#### Parameters

##### logging

Configure logging

##### level

Set the log level for a specified category

##### rll

A-bis Radio Link Layer (RLL)

##### mm

Layer3 Mobility Management (MM)

##### rr

Layer3 Radio Resource (RR)

##### rs

A-bis Radio Signalling Link (RSL)

##### nm

A-bis Network Management / O&M (NM/OML)

##### pag

Paging Subsystem

---

meas  
    Radio Measurement Processing

msc  
    Mobile Switching Center

ho  
    Hand-Over Process

hodec  
    Hand-Over Decision

ref  
    Reference Counting

ctrl  
    Control interface

filter  
    BSC/NAT IMSI based filtering

pcu  
    PCU Interface

lcls  
    Local Call, Local Switch

chan  
    lchan FSM

ts  
    timeslot FSM

as  
    assignment FSM

cbs  
    Cell Broadcast System

lcs  
    Location Services

reset  
    RESET/ACK on A and Lb interfaces

lglobal  
    Library-internal global log family

llapd  
    LAPD in libosmogsm

linp  
    A-bis Input Subsystem

lmux  
    A-bis B-Subchannel TRAU Frame Multiplex

---

---

lmi  
A-bis Input Driver for Signalling

lmib  
A-bis Input Driver for B-Channels (voice)

lsms  
Layer3 Short Message Service (SMS)

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

lsccp  
libosmo-sigtran SCCP Implementation

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

lmgcp  
libosmo-mgcp Media Gateway Control Protocol

ljibuf  
libosmo-netif Jitter Buffer

lrspro  
Remote SIM protocol

lns  
GPRS NS layer

lbssgp  
GPRS BSSGP layer

debug  
Log debug messages and higher levels

info  
Log informational messages and higher levels

---

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.5.5 logging level force-all (debug|info|notice|error|fatal)

Command

```
logging level force-all (debug|info|notice|error|fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

force-all

Globally force all logging categories to a specific level. This is released by the 'no logging level force-all' command. Note: any 'logging level <category> <level>' commands will have no visible effect after this, until the forced level is released.

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.5.6 logging level set-all (debug|info|notice|error|fatal)

Command

```
logging level set-all (debug|info|notice|error|fatal)
```

Parameters

logging

Configure logging



**level**

Set the log level for a specified category

**set-all**

Once-off set all categories to the given log level. There is no single command to take back these changes -- each category is set to the given level, period.

**debug**

Log debug messages and higher levels

**info**

Log informational messages and higher levels

**notice**

Log noticeable messages and higher levels

**error**

Log error messages and higher levels

**fatal**

Log only fatal messages

### 1.5.7 logging print category (0|1)

**Command**

```
logging print category (0|1)
```

**Parameters****logging**

Configure logging

**print**

Log output settings

**category**

Configure log message

**0**

Don't prefix each log message

**1**

Prefix each log message with category/subsystem name

### 1.5.8 logging print category-hex (0|1)

**Command**

```
logging print category-hex (0|1)
```

**Parameters**

logging

Configure logging

print

Log output settings

category-hex

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem nr in hex ('<000b>')

### 1.5.9 logging print extended-timestamp (0|1)

Command

```
logging print extended-timestamp (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

extended-timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp with YYYYMMDDhhmmssnnn

### 1.5.10 logging print file (0|1|basename) [last]

Command

```
logging print file (0|1|basename) [last]
```

Parameters

logging

Configure logging

print

Log output settings

file

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the source file and line

basename

Prefix each log message with the source file's basename (strip leading paths) and line

[last]

Log source file info at the end of a log line. If omitted, log source file info just before the log text.

### 1.5.11 logging print level (0|1)

Command

```
logging print level (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

level

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the log level name

### 1.5.12 logging print thread-id (0|1)

Command

```
logging print thread-id (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

thread-id

Configure log message logging Thread ID

0

Don't prefix each log message

1

Prefix each log message with current Thread ID

### 1.5.13 logging timestamp (0|1)

Command

```
logging timestamp (0|1)
```

Parameters

logging

Configure logging

timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp

### 1.5.14 no logging level force-all

Command

```
no logging level force-all
```

Parameters

no

Negate a command or set its defaults

logging

Configure logging

level

Set the log level for a specified category

force-all

Release any globally forced log level set with 'logging level force-all <level>'

## 1.6 config-stats

### 1.6.1 disable

Command

```
disable
```

Parameters

disable

Disable the reporter

### 1.6.2 enable

Command

```
enable
```

Parameters

enable

Enable the reporter

### 1.6.3 flush-period <0-65535>

Command

```
flush-period <0-65535>
```

Parameters

flush-period

Configure stats sub-system

<0-65535>

Send all stats even if they have not changed (i.e. force the flush) every N-th reporting interval. Set to 0 to disable regular flush (default).

### 1.6.4 level (global|peer|subscriber)

Command

```
level (global|peer|subscriber)
```

Parameters

---

level

Set the maximum group level

global

Report global groups only

peer

Report global and network peer related groups

subscriber

Report global, peer, and subscriber groups

### 1.6.5 local-ip ADDR

Command

```
local-ip ADDR
```

Parameters

local-ip

Set the IP address to which we bind locally

ADDR

IP Address

### 1.6.6 mtu <100-65535>

Command

```
mtu <100-65535>
```

Parameters

mtu

Set the maximum packet size

<100-65535>

Size in byte

### 1.6.7 no local-ip

Command

```
no local-ip
```

Parameters

no

Negate a command or set its defaults

local-ip

Set the IP address to which we bind locally

---

### 1.6.8 no mtu

#### Command

```
no mtu
```

#### Parameters

no

Negate a command or set its defaults

mtu

Set the maximum packet size

### 1.6.9 no prefix

#### Command

```
no prefix
```

#### Parameters

no

Negate a command or set its defaults

prefix

Set the item name prefix

### 1.6.10 prefix PREFIX

#### Command

```
prefix PREFIX
```

#### Parameters

prefix

Set the item name prefix

PREFIX

The prefix string

### 1.6.11 remote-ip ADDR

#### Command

```
remote-ip ADDR
```

#### Parameters

remote-ip

Set the remote IP address to which we connect

ADDR

IP Address

---

## 1.6.12 remote-port <1-65535>

### Command

```
remote-port <1-65535>
```

### Parameters

#### remote-port

Set the remote port to which we connect

#### <1-65535>

Remote port number

## 1.7 config-line

### 1.7.1 bind A.B.C.D [<0-65535>]

### Command

```
bind A.B.C.D [<0-65535>]
```

### Parameters

#### bind

Accept VTY telnet connections on local interface

#### A.B.C.D

Local interface IP address (default: 127.0.0.1)

#### [<0-65535>]

Local TCP port number

### 1.7.2 login

### Command

```
login
```

### Parameters

#### login

Enable password checking



### 1.7.3 no login

#### Command

```
no login
```

#### Parameters

no

Negate a command or set its defaults

login

Enable password checking

## 1.8 config-e1\_input

### 1.8.1 e1\_line <0-255> driver (misdn|misdn\_lapd|dahdi|e1d|ipa|unixsocket)

#### Command

```
e1_line <0-255> driver (misdn|misdn_lapd|dahdi|e1d|ipa|unixsocket)
```

#### Parameters

e1\_line

Configure E1/T1/J1 Line

<0-255>

Line Number

driver

Set driver for this line

misdn

mISDN supported E1 Card (kernel LAPD)

misdn\_lapd

mISDN supported E1 Card (userspace LAPD)

dahdi

DAHDI supported E1/T1/J1 Card

e1d

osmo-e1d supported E1 interface

ipa

IPA TCP/IP input

unixsocket

Unix socket input

---

### 1.8.2 e1\_line <0-255> ipa-keepalive <1-300> <1-300>

#### Command

```
e1_line <0-255> ipa-keepalive <1-300> <1-300>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

e1\_line

Configure E1/T1/J1 Line

<0-255>

Line Number

ipa-keepalive

Enable IPA PING/PONG keep-alive

<1-300>

Idle interval in seconds before probes are sent

<1-300>

Time to wait for PONG response

### 1.8.3 e1\_line <0-255> keepalive

#### Command

```
e1_line <0-255> keepalive
```

#### Library specific attributes

Flag: I

This command applies on IPA link establishment

#### Parameters

e1\_line

Configure E1/T1/J1 Line

<0-255>

Line Number

keepalive

Enable keep-alive probing

### 1.8.4 e1\_line <0-255> keepalive <1-300> <1-20> <1-300>

#### Command

```
e1_line <0-255> keepalive <1-300> <1-20> <1-300>
```

#### Library specific attributes

#### Flag: I

This command applies on IPA link establishment

#### Parameters

##### e1\_line

Configure E1/T1/J1 Line

##### <0-255>

Line Number

##### keepalive

Enable keep-alive probing

##### <1-300>

Idle interval in seconds before probes are sent

##### <1-20>

Number of probes to sent

##### <1-300>

Delay between probe packets in seconds

### 1.8.5 e1\_line <0-255> name .LINE

#### Command

```
e1_line <0-255> name .LINE
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### e1\_line

Configure E1/T1/J1 Line

##### <0-255>

Line Number

##### name

Set name for this line

##### .LINE

Human readable name

---

## 1.8.6 e1\_line <0-255> port <0-255>

### Command

```
e1_line <0-255> port <0-255>
```

### Library specific attributes

#### Flag: L

This command applies on E1 line update

### Parameters

#### e1\_line

Configure E1/T1/J1 Line

#### <0-255>

Line Number

#### port

Set physical port/span/card number

#### <0-255>

E1/T1 Port/Span/Card number

## 1.8.7 e1\_line <0-255> socket .SOCKET

### Command

```
e1_line <0-255> socket .SOCKET
```

### Library specific attributes

#### Flag: L

This command applies on E1 line update

### Parameters

#### e1\_line

Configure E1/T1/J1 Line

#### <0-255>

Line Number

#### socket

Set socket path for unixsocket

#### .SOCKET

socket path

### 1.8.8 ipa bind A.B.C.D

#### Command

```
ipa bind A.B.C.D
```

#### Library specific attributes

#### Flag: L

This command applies on E1 line update

#### Parameters

##### ipa

ipa driver config

##### bind

Set ipa local bind address

##### A.B.C.D

Listen on this IP address (default 0.0.0.0)

### 1.8.9 no e1\_line <0-255> ipa-keepalive

#### Command

```
no e1_line <0-255> ipa-keepalive
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### no

Negate a command or set its defaults

##### e1\_line

Configure E1/T1/J1 Line

##### <0-255>

Line Number

##### ipa-keepalive

Enable IPA PING/PONG keep-alive

---

### 1.8.10 no e1\_line <0-255> keepalive

#### Command

```
no e1_line <0-255> keepalive
```

#### Library specific attributes

#### Flag: I

This command applies on IPA link establishment

#### Parameters

##### no

Negate a command or set its defaults

##### e1\_line

Configure E1/T1/J1 Line

##### <0-255>

Line Number

##### keepalive

Enable keep-alive probing

### 1.8.11 no pcap

#### Command

```
no pcap
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### no

Negate a command or set its defaults

##### pcap

Disable pcap recording of all E1 traffic

## 1.8.12 pcap .FILE

Command

```
pcap .FILE
```

Global attributes

Flag: !

This command applies immediately

Parameters

pcap

Setup a pcap recording of all E1 traffic

.FILE

Filename to save the packets to

## 1.9 config-ctrl

### 1.9.1 bind A.B.C.D

Command

```
bind A.B.C.D
```

Parameters

bind

Set bind address to listen for Control connections

A.B.C.D

Local IP address (default 127.0.0.1)

## 1.10 config-cs7

### 1.10.1 as NAME (sua|m3ua|ipa)

Command

```
as NAME (sua|m3ua|ipa)
```

Global attributes

Flag: !

This command applies immediately

#### Parameters

as

Configure an Application Server

NAME

Name of the Application Server

sua

SCCP User Adaptation

m3ua

MTP3 User Adaptation

ipa

IPA Multiplex (SCCP Lite)

### 1.10.2 asp NAME <0-65535> <0-65535> (sua|m3ua|ipa)

#### Command

```
asp NAME <0-65535> <0-65535> (sua|m3ua|ipa)
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

asp

Configure Application Server Process

NAME

Name of ASP

<0-65535>

Remote SCTP port number

<0-65535>

Local SCTP port number

sua

SCCP User Adaptation

m3ua

MTP3 User Adaptation

ipa

IPA Multiplex (SCCP Lite)



### 1.10.3 description .TEXT

#### Command

```
description .TEXT
```

#### Parameters

##### description

Save human-readable description of the object

##### .TEXT

Text until the end of the line

### 1.10.4 network-indicator (international | national | reserved | spare)

#### Command

```
network-indicator (international | national | reserved | spare)
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### network-indicator

Configure the Network Indicator

##### international

International Network

##### national

National Network

##### reserved

Reserved Network

##### spare

Spare Network

### 1.10.5 no as NAME

#### Command

```
no as NAME
```

#### Global attributes

---

Flag: !

This command applies immediately

Parameters

no

Negate a command or set its defaults

as

Disable Application Server

NAME

Name of AS

### 1.10.6 no asp NAME

Command

```
no asp NAME
```

Global attributes

Flag: !

This command applies immediately

Parameters

no

Negate a command or set its defaults

asp

Disable Application Server Process

NAME

Name of ASP

### 1.10.7 no sccp-address NAME

Command

```
no sccp-address NAME
```

Global attributes

Flag: !

This command applies immediately

Parameters

no

Negate a command or set its defaults

sccp-address

Delete an SCCP addressbook entry

NAME

Name of the SCCP Address

### 1.10.8 point-code POINT\_CODE

#### Command

```
point-code POINT_CODE
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Configure the local Point Code

POINT\_CODE

Point Code

### 1.10.9 point-code delimiter (default|dash)

#### Command

```
point-code delimiter (default|dash)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Point Code

delimiter

Configure Point Code Delimiter

default

Use dot as delimiter

dash

User dash as delimiter

### 1.10.10 point-code format <1-24> [<1-23>] [<1-22>]

#### Command

```
point-code format <1-24> [<1-23>] [<1-22>]
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Point Code

format

Configure Point Code Format

<1-24>

Length of first PC component

[<1-23>]

Length of second PC component

[<1-22>]

Length of third PC component

### 1.10.11 point-code format default

#### Command

```
point-code format default
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Point Code

format

Configure Point Code Format

default

Default Point Code Format (3.8.3)

### 1.10.12 sccp-address NAME

Command

```
sccp-address NAME
```

Global attributes

Flag: !

This command applies immediately

Parameters

sccp-address

Create/Modify an SCCP addressbook entry

NAME

Name of the SCCP Address

### 1.10.13 sccp-timer (conn\_est|ias|iar|rel|repeat\_rel|int|guard|reset|reassembly) <1-99999...

Command

```
sccp-timer (conn_est|ias|iar|rel|repeat_rel|int|guard|reset|reassembly) <1-999999>
```

Global attributes

Flag: !

This command applies immediately

Parameters

sccp-timer

Configure SCCP timer values, see ITU-T Q.714

conn\_est

Waiting for connection confirm message, 1 to 2 minutes (default: 60)

ias

Send keep-alive: on an idle connection, delay before sending an Idle Timer message, 5 to 10 minutes (default: 420)

iar

Receive keep-alive: on an idle connection, delay until considering a connection as stale, 11 to 21 minutes (default: 900)

rel

Waiting for release complete message, 10 to 20 seconds (default: 10)

repeat\_rel

Waiting for release complete message; or to repeat sending released message after the initial expiry, 10 to 20 seconds (default: 10)

**int**

Waiting for release complete message; or to release connection resources, freeze the LRN and alert a maintenance function after the initial expiry, extending to 1 minute (default: 60)

**guard**

Waiting to resume normal procedure for temporary connection sections during the restart procedure, 23 to 25 minutes (default: 1380)

**reset**

Waiting to release temporary connection section or alert maintenance function after reset request message is sent, 10 to 20 seconds (default: 10)

**reassembly**

Waiting to receive all the segments of the remaining segments, single segmented message after receiving the first segment, 10 to 20 seconds (default: 10)

**<1-999999>**

Timer value, in seconds

### 1.10.14 xua rkm routing-key-allocation (static-only|dynamic-permitted)

**Command**

```
xua rkm routing-key-allocation (static-only|dynamic-permitted)
```

**Global attributes****Flag: !**

This command applies immediately

**Parameters****xua**

SIGTRAN xxxUA related

**rkm**

Routing Key Management

**routing-key-allocation**

Routing Key Management Allocation Policy

**static-only**

Only static (pre-configured) Routing Keys permitted

**dynamic-permitted**

Dynamically allocate Routing Keys for what ASPs request

---

## 1.11 config-cs7-as

### 1.11.1 asp NAME

Command

```
asp NAME
```

Global attributes

Flag: !

This command applies immediately

Parameters

asp

Specify that a given ASP is part of this AS

NAME

Name of ASP to be added to AS

### 1.11.2 description .TEXT

Command

```
description .TEXT
```

Parameters

description

Save human-readable description of the object

.TEXT

Text until the end of the line

### 1.11.3 no asp NAME

Command

```
no asp NAME
```

Global attributes

Flag: !

This command applies immediately

Parameters

no

Negate a command or set its defaults

asp

Specify ASP to be removed from this AS

NAME

Name of ASP to be removed

---

### 1.11.4 no traffic-mode

#### Command

```
no traffic-mode
```

#### Parameters

no

Negate a command or set its defaults

traffic-mode

Remove explicit traffic mode of operation of this AS

### 1.11.5 point-code override dpc PC

#### Command

```
point-code override dpc PC
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Point Code Specific Features

override

Override (force) a point-code to hard-coded value

dpc

Override Source Point Code

PC

Override Destination Point Code

### 1.11.6 point-code override patch-sccp (disabled|both)

#### Command

```
point-code override patch-sccp (disabled|both)
```

#### Global attributes

Flag: !

This command applies immediately

---



#### Parameters

##### point-code

Point Code Specific Features

##### override

Override (force) a point-code to hard-coded value

##### patch-sccp

Patch point code values into SCCP called/calling address

##### disabled

Don't patch any point codes into SCCP called/calling address

##### both

Patch both origin and destination point codes into SCCP called/calling address

### 1.11.7 qos-class <0-255>

#### Command

```
qos-class <0-255>
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### qos-class

Specity QoS Class of AS

##### <0-255>

QoS Class of AS

### 1.11.8 recovery-timeout <1-2000>

#### Command

```
recovery-timeout <1-2000>
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### recovery-timeout

Specifies the recovery timeout value in milliseconds

##### <1-2000>

Recovery Timeout in Milliseconds

---

### 1.11.9 routing-key RCONTEXT DPC

#### Command

```
routing-key RCONTEXT DPC
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### routing-key

Define a routing key

##### RCONTEXT

Routing context number

##### DPC

Destination Point Code

### 1.11.10 routing-key RCONTEXT DPC si (aal2|bicc|b-isup|h248|isup|sat-isup|sccp|tup)

#### Command

```
routing-key RCONTEXT DPC si (aal2|bicc|b-isup|h248|isup|sat-isup|sccp|tup)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### routing-key

Define a routing key

##### RCONTEXT

Routing context number

##### DPC

Destination Point Code

##### si

Match on Service Indicator

##### aal2

ATM Adaption Layer 2

##### bicc

Bearer Independent Call Control

---

b-isup

Broadband ISDN User Part

h248

H.248

isup

ISDN User Part

sat-isup

Sattelite ISDN User Part

sccp

Signalling Connection Control Part

tup

Telephony User Part

### 1.11.11 routing-key RCONTEXT DPC si (aal2|bicc|b-isup|h248|isup|sat-isup|sccp|tup) ssn S...

Command

```
routing-key RCONTEXT DPC si (aal2|bicc|b-isup|h248|isup|sat-isup|sccp|tup) ssn SSN
```

Global attributes

Flag: !

This command applies immediately

Parameters

routing-key

Define a routing key

RCONTEXT

Routing context number

DPC

Destination Point Code

si

Match on Service Indicator

aal2

ATM Adaption Layer 2

bicc

Bearer Independent Call Control

b-isup

Broadband ISDN User Part

h248

H.248

isup

ISDN User Part

sat-isup

Sattelite ISDN User Part

sccp

Signalling Connection Control Part

tup

Telephony User Part

ssn

Match on Sub-System Number

SSN

Sub-System Number to match on

### 1.11.12 routing-key RCONTEXT DPC ssn SSN

Command

```
routing-key RCONTEXT DPC ssn SSN
```

Global attributes

Flag: !

This command applies immediately

Parameters

routing-key

Define a routing key

RCONTEXT

Routing context number

DPC

Destination Point Code

ssn

Match on Sub-System Number

SSN

Sub-System Number to match on

### 1.11.13 traffic-mode (broadcast | loadshare | roundrobin | override)

#### Command

```
traffic-mode (broadcast | loadshare | roundrobin | override)
```

#### Parameters

##### traffic-mode

Specifies traffic mode of operation of the ASP within the AS

##### broadcast

Broadcast to all ASP within AS

##### loadshare

Share Load among all ASP within AS

##### roundrobin

Round-Robin between all ASP within AS

##### override

Override

## 1.12 config-cs7-asp

### 1.12.1 block

#### Command

```
block
```

#### Global attributes

##### Flag: @

This command applies on VTY node exit

#### Parameters

##### block

Allows a SCTP Association with ASP, but doesn't let it become active

### 1.12.2 description .TEXT

#### Command

```
description .TEXT
```

#### Parameters

##### description

Save human-readable description of the object

##### .TEXT

Text until the end of the line

---

### 1.12.3 local-ip (A.B.C.D|X:X::X:X)

#### Command

```
local-ip (A.B.C.D|X:X::X:X)
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

local-ip

Specify Local IP Address from which to contact ASP

A.B.C.D

Local IPv4 Address from which to contact of ASP

X:X::X:X

Local IPv6 Address from which to contact of ASP

### 1.12.4 qos-class <0-255>

#### Command

```
qos-class <0-255>
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

qos-class

Specify QoS Class of ASP

<0-255>

QoS Class of ASP

### 1.12.5 remote-ip (A.B.C.D|X:X::X:X)

#### Command

```
remote-ip (A.B.C.D|X:X::X:X)
```

#### Global attributes

---

Flag: @

This command applies on VTY node exit

#### Parameters

remote-ip

Specify Remote IP Address of ASP

A.B.C.D

Remote IPv4 Address of ASP

X:X::X:X

Remote IPv6 Address of ASP

### 1.12.6 role (sg|asp|ipsp)

#### Command

```
role (sg|asp|ipsp)
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

role

Specify the xUA role for this ASP

sg

SG (Signaling Gateway)

asp

ASP (Application Server Process)

ipsp

IPSP (IP Signalling Point)

### 1.12.7 sctp-role (client|server)

#### Command

```
sctp-role (client|server)
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

##### sctp-role

Specify the SCTP role for this ASP

##### client

Operate as SCTP client; connect to a server

##### server

Operate as SCTP server; wait for client connections

## 1.12.8 shutdown

#### Command

```
shutdown
```

#### Global attributes

Flag: @

This command applies on VTY node exit

#### Parameters

##### shutdown

Terminates SCTP association; New associations will be rejected

## 1.13 config-cs7-sccpaddr

### 1.13.1 global-title

#### Command

```
global-title
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### global-title

Add/Modify Global Title



### 1.13.2 no global-title

#### Command

```
no global-title
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### no

Negate a command or set its defaults

#### global-title

Remove Global Title

### 1.13.3 no point-code

#### Command

```
no point-code
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### no

Negate a command or set its defaults

#### point-code

Remove point-code Number

### 1.13.4 no subsystem-number

#### Command

```
no subsystem-number
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### no

Negate a command or set its defaults

#### subsystem-number

Remove Subsystem Number

---

### 1.13.5 point-code POINT\_CODE

#### Command

```
point-code POINT_CODE
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

point-code

Add point-code Number

POINT\_CODE

PC

### 1.13.6 routing-indicator (GT|PC|IP)

#### Command

```
routing-indicator (GT|PC|IP)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

routing-indicator

Add Routing Indicator

GT

by global-title

PC

by point-code

IP

by ip-address

### 1.13.7 subsystem-number <0-4294967295>

#### Command

```
subsystem-number <0-4294967295>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

subsystem-number

Add Subsystem Number

<0-4294967295>

SSN

## 1.14 config-cs7-sccpaddr-gt

### 1.14.1 digits DIGITS

#### Command

```
digits DIGITS
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

digits

Set Global Title Digits

DIGITS

Number digits

### 1.14.2 global-title-indicator <0-15>

#### Command

```
global-title-indicator <0-15>
```

#### Global attributes

---

Flag: !

This command applies immediately

Parameters

global-title-indicator

Set Global Title Indicator

<0-15>

GTI

### 1.14.3 nature-of-address-indicator <0-127>

Command

```
nature-of-address-indicator <0-127>
```

Global attributes

Flag: !

This command applies immediately

Parameters

nature-of-address-indicator

Set Global Title Nature of Address Indicator

<0-127>

NAI

### 1.14.4 numbering-plan-indicator <0-15>

Command

```
numbering-plan-indicator <0-15>
```

Global attributes

Flag: !

This command applies immediately

Parameters

numbering-plan-indicator

Set Global Title Numbering Plan Indicator

<0-15>

NPI

### 1.14.5 translation-type <0-255>

#### Command

```
translation-type <0-255>
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### translation-type

Set Global Title Translation Type

#### <0-255>

TT

## 1.15 config-cpu-sched

### 1.15.1 cpu-affinity (self|all|<0-4294967295>|THREADNAME) CPUHEXMASK [delay]

#### Command

```
cpu-affinity (self|all|<0-4294967295>|THREADNAME) CPUHEXMASK [delay]
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### cpu-affinity

Set CPU affinity mask on a (group of) thread(s)

#### self

Set CPU affinity mask on thread running the VTY

#### all

Set CPU affinity mask on all process' threads

#### <0-4294967295>

Set CPU affinity mask on a thread with specified PID

#### THREADNAME

Set CPU affinity mask on a thread with specified thread name

#### CPUHEXMASK

CPU affinity mask

#### [delay]

If set, delay applying the affinity mask now and let the app handle it at a later point

### 1.15.2 policy rr <1-32>

#### Command

```
policy rr <1-32>
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### policy

Set the scheduling policy to use for the process

##### rr

Use the SCHED\_RR real-time scheduling algorithm

##### <1-32>

Set the SCHED\_RR real-time priority

## 1.16 config-net

### 1.16.1 allow-unusable-timeslots

#### Command

```
allow-unusable-timeslots
```

#### Parameters

##### allow-unusable-timeslots

Don't refuse to start with mutually exclusive codec settings

### 1.16.2 bts <0-255>

#### Command

```
bts <0-255>
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### bts

Select a BTS to configure

##### <0-255>

BTS Number

---

### 1.16.3 encryption a5 <0-3> [<0-3>] [<0-3>] [<0-3>]

#### Command

```
encryption a5 <0-3> [<0-3>] [<0-3>] [<0-3>]
```

#### Application specific attributes

##### Flag: !

This command applies for newly created lchans

#### Parameters

##### encryption

Encryption options

##### a5

GSM A5 Air Interface Encryption

##### <0-3>

A5/n Algorithm Number

##### [<0-3>]

A5/n Algorithm Number

##### [<0-3>]

A5/n Algorithm Number

##### [<0-3>]

A5/n Algorithm Number

### 1.16.4 handover (0|1|default)

#### Command

```
handover (0|1|default)
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### handover

Handover general config

##### 0

Disable in-call handover

##### 1

Enable in-call handover

##### default

Enable/disable handover: Use default (0), remove explicit setting on this node

---

### 1.16.5 handover algorithm (1|2|default)

#### Command

```
handover algorithm (1|2|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover

Handover general config

##### algorithm

Choose algorithm for handover decision

1

Algorithm 1: trigger handover based on comparing current cell and neighbor RxLev and RxQual, only.

2

Algorithm 2: trigger handover on RxLev/RxQual, and also to balance the load across several cells. Consider available codecs. Prevent repeated handover by penalty timers.

##### default

Use default (1), remove explicit setting on this node

### 1.16.6 handover1 maximum distance (<0-9999>|default)

#### Command

```
handover1 maximum distance (<0-9999>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover1

Handover options for handover decision algorithm 1

##### maximum

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

##### distance

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

<0-9999>

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

##### default

Use default (9999), remove explicit setting on this node



### 1.16.7 handover1 power budget hysteresis (<0-999>|default)

#### Command

```
handover1 power budget hysteresis (<0-999>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover1

Handover options for handover decision algorithm 1

##### power

Neighbor cell power triggering

##### budget

Neighbor cell power triggering

##### hysteresis

How many dB stronger must a neighbor be to become a HO candidate

##### <0-999>

Neighbor's strength difference in dB

##### default

Use default (3), remove explicit setting on this node

### 1.16.8 handover1 power budget interval (<1-99>|default)

#### Command

```
handover1 power budget interval (<1-99>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover1

Handover options for handover decision algorithm 1

##### power

Neighbor cell power triggering

##### budget

Neighbor cell power triggering

---

interval

How often to check for a better cell (SACCH frames)

<1-99>

Check for stronger neighbor every N number of SACCH frames

default

Use default (6), remove explicit setting on this node

### 1.16.9 handover1 window rxlev averaging (<1-10>|default)

Command

```
handover1 window rxlev averaging (<1-10>|default)
```

Global attributes

Flag: !

This command applies immediately

Parameters

handover1

Handover options for handover decision algorithm 1

window

Measurement averaging settings

rxlev

Received-Level averaging

averaging

How many RxLev measurements to use for averaging

<1-10>

RxLev averaging: Number of values to average over

default

Use default (10), remove explicit setting on this node

### 1.16.10 handover1 window rxlev neighbor averaging (<1-10>|default)

Command

```
handover1 window rxlev neighbor averaging (<1-10>|default)
```

Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover1

Handover options for handover decision algorithm 1

##### window

Measurement averaging settings

##### rxlev

Received-Level averaging

##### neighbor

How many Neighbor RxLev measurements to use for averaging

##### averaging

How many Neighbor RxLev measurements to use for averaging

##### <1-10>

Neighbor RxLev averaging: Number of values to average over

##### default

Use default (10), remove explicit setting on this node

### 1.16.11 handover1 window rxqual averaging (<1-10>|default)

#### Command

```
handover1 window rxqual averaging (<1-10>|default)
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### handover1

Handover options for handover decision algorithm 1

##### window

Measurement averaging settings

##### rxqual

Received-Quality averaging

##### averaging

How many RxQual measurements to use for averaging

##### <1-10>

RxQual averaging: Number of values to average over

##### default

Use default (1), remove explicit setting on this node

### 1.16.12 handover2 afs-bias rxlev (<0-20>|default)

#### Command

```
handover2 afs-bias rxlev (<0-20>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### afs-bias

Configure bias to prefer AFS (AMR on TCH/F) over other codecs

##### rxlev

RxLev improvement bias for AFS over other codecs

##### <0-20>

Virtual RxLev improvement (dB)

##### default

Use default (0), remove explicit setting on this node

### 1.16.13 handover2 afs-bias rxqual (<0-7>|default)

#### Command

```
handover2 afs-bias rxqual (<0-7>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### afs-bias

Configure bias to prefer AFS (AMR on TCH/F) over other codecs

##### rxqual

RxQual improvement bias for AFS over other codecs

##### <0-7>

Virtual RxQual improvement

##### default

Use default (0), remove explicit setting on this node

### 1.16.14 handover2 assignment (0|1|default)

#### Command

```
handover2 assignment (0|1|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### assignment

Enable or disable in-call channel re-assignment within the same cell

0

Disable in-call assignment

1

Enable in-call assignment

##### default

Use default (0), remove explicit setting on this node

### 1.16.15 handover2 congestion-check (disabled|<1-999>|now)

#### Command

```
handover2 congestion-check (disabled|<1-999>|now)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### congestion-check

Configure congestion check interval

##### disabled

Disable congestion checking, do not handover based on cell load. Note: there is one global congestion check interval, i.e. contrary to other handover2 settings, this is not configurable per individual cell.

##### <1-999>

Congestion check interval in seconds (default 10)

##### now

Manually trigger a congestion check to run right now

### 1.16.16 handover2 max-handovers (<1-9999>|default)

#### Command

```
handover2 max-handovers (<1-9999>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### max-handovers

Maximum number of concurrent handovers allowed per cell

<1-9999>

Number

##### default

Use default (9999), remove explicit setting on this node

### 1.16.17 handover2 maximum distance (<0-9999>|default)

#### Command

```
handover2 maximum distance (<0-9999>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### maximum

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

##### distance

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

<0-9999>

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

##### default

Use default (9999), remove explicit setting on this node

### 1.16.18 handover2 min rxlev (<-110--50>|default)

#### Command

```
handover2 min rxlev (<-110--50>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### min

Minimum Level/Quality thresholds before triggering HO

##### rxlev

How weak may RxLev of an MS become before triggering HO

##### <-110--50>

minimum RxLev (dBm; note: negative values)

##### default

Use default (-100), remove explicit setting on this node

### 1.16.19 handover2 min rxqual (<0-7>|default)

#### Command

```
handover2 min rxqual (<0-7>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### min

Minimum Level/Quality thresholds before triggering HO

##### rxqual

How bad may RxQual of an MS become before triggering HO, where 0 is the best quality (bit error rate < 0.2%) and 7 is the worst quality (bit error rate > 12.8%), see 3GPP TS 45.008 8.2.4.

##### <0-7>

worst acceptable RxQual

##### default

Use default (5), remove explicit setting on this node

### 1.16.20 handover2 min-free-slots tch/f (<0-9999>|default)

#### Command

```
handover2 min-free-slots tch/f (<0-9999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### min-free-slots

Minimum free TCH timeslots before cell is considered congested

##### tch/f

Minimum free TCH/F timeslots before cell is considered congested

##### <0-9999>

Number of TCH/F slots

##### default

Use default (0), remove explicit setting on this node

### 1.16.21 handover2 min-free-slots tch/h (<0-9999>|default)

#### Command

```
handover2 min-free-slots tch/h (<0-9999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### min-free-slots

Minimum free TCH timeslots before cell is considered congested

##### tch/h

Minimum free TCH/H timeslots before cell is considered congested

##### <0-9999>

Number of TCH/H slots

##### default

Use default (0), remove explicit setting on this node



### 1.16.22 handover2 penalty-time failed-assignment (<0-99999>|default)

#### Command

```
handover2 penalty-time failed-assignment (<0-99999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### penalty-time

Set penalty times to wait between repeated handovers

##### failed-assignment

Time to suspend handover for a subscriber after a failed re-assignment within this cell; see also 'handover2 retries'

##### <0-99999>

Seconds

##### default

Use default (60), remove explicit setting on this node

### 1.16.23 handover2 penalty-time failed-ho (<0-99999>|default)

#### Command

```
handover2 penalty-time failed-ho (<0-99999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### penalty-time

Set penalty times to wait between repeated handovers

##### failed-ho

Time to suspend handover for a subscriber after a failed handover into this cell; see also 'handover2 retries'

##### <0-99999>

Seconds

##### default

Use default (60), remove explicit setting on this node

### 1.16.24 handover2 penalty-time max-distance (<0-99999>|default)

#### Command

```
handover2 penalty-time max-distance (<0-99999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### penalty-time

Set penalty times to wait between repeated handovers

##### max-distance

Time to suspend handover for a subscriber after leaving this cell due to exceeding max distance; see also 'handover2 retries'

##### <0-99999>

Seconds

##### default

Use default (300), remove explicit setting on this node

### 1.16.25 handover2 power budget hysteresis (<0-999>|default)

#### Command

```
handover2 power budget hysteresis (<0-999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### power

Neighbor cell power triggering

##### budget

Neighbor cell power triggering

##### hysteresis

How many dB stronger must a neighbor be to become a HO candidate

##### <0-999>

Neighbor's strength difference in dB

##### default

Use default (3), remove explicit setting on this node

---

### 1.16.26 handover2 power budget interval (<1-99>|default)

#### Command

```
handover2 power budget interval (<1-99>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### power

Neighbor cell power triggering

##### budget

Neighbor cell power triggering

##### interval

How often to check for a better cell (SACCH frames)

##### <1-99>

Check for stronger neighbor every N number of SACCH frames

##### default

Use default (6), remove explicit setting on this node

### 1.16.27 handover2 retries (<0-9>|default)

#### Command

```
handover2 retries (<0-9>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### retries

Number of times to immediately retry a failed handover/assignment, before a penalty time is applied

##### <0-9>

Number of retries

##### default

Use default (0), remove explicit setting on this node

---

### 1.16.28 handover2 tdma-measurement (full|subset|default)

#### Command

```
handover2 tdma-measurement (full|subset|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### handover2

Handover options for handover decision algorithm 2

#### tdma-measurement

Define measurement set of TDMA frames

#### full

Full set of 102/104 TDMA frames

#### subset

Sub set of 4 TDMA frames (SACCH)

#### default

Use default (subset), remove explicit setting on this node

### 1.16.29 handover2 window rxlev averaging (<1-10>|default)

#### Command

```
handover2 window rxlev averaging (<1-10>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### handover2

Handover options for handover decision algorithm 2

#### window

Measurement averaging settings

#### rxlev

Received-Level averaging

#### averaging

How many RxLev measurements to use for averaging

#### <1-10>

RxLev averaging: Number of values to average over

#### default

Use default (10), remove explicit setting on this node

### 1.16.30 handover2 window rxlev neighbor averaging (<1-10>|default)

#### Command

```
handover2 window rxlev neighbor averaging (<1-10>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### window

Measurement averaging settings

##### rxlev

Received-Level averaging

##### neighbor

How many Neighbor RxLev measurements to use for averaging

##### averaging

How many Neighbor RxLev measurements to use for averaging

##### <1-10>

Neighbor RxLev averaging: Number of values to average over

##### default

Use default (10), remove explicit setting on this node

### 1.16.31 handover2 window rxqual averaging (<1-10>|default)

#### Command

```
handover2 window rxqual averaging (<1-10>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### window

Measurement averaging settings

---

rxqual

Received-Quality averaging

averaging

How many RxQual measurements to use for averaging

<1-10>

RxQual averaging: Number of values to average over

default

Use default (1), remove explicit setting on this node

### 1.16.32 meas-feed destination ADDR <0-65535>

Command

```
meas-feed destination ADDR <0-65535>
```

Global attributes

Flag: !

This command applies immediately

Parameters

meas-feed

Measurement Report export

destination

Where to forward Measurement Report feeds

ADDR

address or hostname

<0-65535>

port number

### 1.16.33 meas-feed scenario NAME

Command

```
meas-feed scenario NAME
```

Global attributes

Flag: !

This command applies immediately

Parameters

meas-feed

Measurement Report export

scenario

Set a name to include in the Measurement Report feeds

NAME

Name string, up to 31 characters

### 1.16.34 mobile network code <0-999>

#### Command

```
mobile network code <0-999>
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### mobile

Set the GSM mobile network code

#### network

Network Commands

#### code

Code commands

#### <0-999>

Mobile Network Code to use

### 1.16.35 neci (0|1)

#### Command

```
neci (0|1)
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### neci

New Establish Cause Indication

#### 0

Don't set the NECI bit

#### 1

Set the NECI bit

### 1.16.36 neighbor-resolution bind (A.B.C.D|X:X::X:X) [<0-65535>]

#### Command

```
neighbor-resolution bind (A.B.C.D|X:X::X:X) [<0-65535>]
```

#### Parameters

##### neighbor-resolution

Manage local and remote-BSS neighbor cells

##### bind

Bind Neighbor Resolution Service (CTRL interface) to given ip and port

##### A.B.C.D

IP information

##### X:X::X:X

IPv6 information

##### [<0-65535>]

Port to bind the service to [defaults to 4248 if not provided]

### 1.16.37 network country code <1-999>

#### Command

```
network country code <1-999>
```

#### Application specific attributes

##### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### network

Set the GSM network country code

##### country

Country commands

##### code

Code commands

##### <1-999>

Network Country Code to use

---



### 1.16.38 no periodic location update

#### Command

```
no periodic location update
```

#### Parameters

no

Negate a command or set its defaults

periodic

Periodic Location Updating Interval

location

Periodic Location Updating Interval

update

Periodic Location Updating Interval

### 1.16.39 no timezone

#### Command

```
no timezone
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

no

Negate a command or set its defaults

timezone

Disable network timezone override, use system tz

### 1.16.40 nri bitlen <1-15>

#### Command

```
nri bitlen <1-15>
```

#### Global attributes

Flag: !

This command applies immediately

---

#### Parameters

##### nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

##### bitlen

Set number of bits that an NRI has, to extract from TMSI identities (always starting just after the TMSI's most significant octet).

##### <1-15>

bit count (default: NRI\_BITLEN\_DEFAULT)

### 1.16.41 nri null add <0-32767> [<0-32767>]

#### Command

```
nri null add <0-32767> [<0-32767>]
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

##### null

Define NULL-NRI values that cause re-assignment of an MS to a different MSC, for MSC pooling.

##### add

Add NULL-NRI value (or range)

##### <0-32767>

First value of the NRI value range, should not surpass the configured 'nri bitlen'.

##### [<0-32767>]

Last value of the NRI value range, should not surpass the configured 'nri bitlen' and be larger than the first value; if omitted, apply only the first value.

### 1.16.42 nri null del <0-32767> [<0-32767>]

#### Command

```
nri null del <0-32767> [<0-32767>]
```

#### Global attributes

##### Flag: !

This command applies immediately

---

#### Parameters

nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

null

Define NULL-NRI values that cause re-assignment of an MS to a different MSC, for MSC pooling.

del

Remove NRI value or range from the NRI mapping for this MSC

<0-32767>

First value of the NRI value range, should not surpass the configured 'nri bitlen'.

[<0-32767>]

Last value of the NRI value range, should not surpass the configured 'nri bitlen' and be larger than the first value; if omitted, apply only the first value.

### 1.16.43 paging any use tch (0|1)

#### Command

```
paging any use tch (0|1)
```

#### Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

paging

Assign a TCH when receiving a Paging Any request

any

Any Channel

use

Use

tch

TCH

0

Do not use TCH for Paging Request Any

1

Do use TCH for Paging Request Any

### 1.16.44 periodic location update <6-1530>

#### Command

```
periodic location update <6-1530>
```

#### Parameters

##### periodic

Periodic Location Updating Interval

##### location

Periodic Location Updating Interval

##### update

Periodic Location Updating Interval

##### <6-1530>

Periodic Location Updating Interval in Minutes

### 1.16.45 timer [(net|mgw)] [TNNNN] [(<0-2147483647>|default)]

#### Command

```
timer [(net|mgw)] [TNNNN] [(<0-2147483647>|default)]
```

#### Parameters

##### timer

Configure or show timers

##### [net]

GSM network

##### [mgw]

MGW (Media Gateway) interface

##### [TNNNN]

T- or X-timer-number -- 3GPP compliant timer number of the format '1234' or 'T1234' or 't1234'; Osmocom-specific timer number of the format: 'X1234' or 'x1234'.

##### [<0-2147483647>]

New timer value

##### [default]

Set to default timer value

### 1.16.46 **timezone** <-19-19> (0|15|30|45)

#### Command

```
timezone <-19-19> (0|15|30|45)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### timezone

Set the Timezone Offset of the network

##### <-19-19>

Timezone offset (hours)

0

Timezone offset (00 minutes)

15

Timezone offset (15 minutes)

30

Timezone offset (30 minutes)

45

Timezone offset (45 minutes)

### 1.16.47 **timezone** <-19-19> (0|15|30|45) <0-2>

#### Command

```
timezone <-19-19> (0|15|30|45) <0-2>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### timezone

Set the Timezone Offset of the network

##### <-19-19>

Timezone offset (hours)

0

Timezone offset (00 minutes)

- 15  
Timezone offset (15 minutes)
- 30  
Timezone offset (30 minutes)
- 45  
Timezone offset (45 minutes)
- <0-2>  
DST offset (hours)

## 1.17 config-net-bts

### 1.17.1 (bs-power-control|ms-power-control)

Command

```
(bs-power-control|ms-power-control)
```

Parameters

bs-power-control

BS (Downlink) power control parameters

ms-power-control

MS (Uplink) power control parameters

### 1.17.2 abis-lower-transport (single-timeslot|super-channel)

Command

```
abis-lower-transport (single-timeslot|super-channel)
```

Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

Parameters

abis-lower-transport

Configure thee Abis Lower Transport

single-timeslot

Single Timeslot (classic Abis)

super-channel

SuperChannel (Packet Abis)

### 1.17.3 access-control-class-ramping

#### Command

```
access-control-class-ramping
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

access-control-class-ramping

Enable Access Control Class ramping

### 1.17.4 access-control-class-ramping-chan-load <0-100> <0-100>

#### Command

```
access-control-class-ramping-chan-load <0-100> <0-100>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

access-control-class-ramping-chan-load

Configure Access Control Class ramping channel load thresholds

<0-100>

Lower Channel load threshold (%) below which subset size of allowed broadcast ACCs can be increased

<0-100>

Upper channel load threshold (%) above which subset size of allowed broadcast ACCs can be decreased

### 1.17.5 access-control-class-ramping-step-interval (<5-600>|dynamic)

#### Command

```
access-control-class-ramping-step-interval (<5-600>|dynamic)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

access-control-class-ramping-step-interval

Configure Access Control Class ramping step interval

<5-600>

Set a fixed step interval (in seconds)

dynamic

Use dynamic step interval based on BTS channel load (deprecated, don't use, ignored)

### 1.17.6 access-control-class-ramping-step-size (<1-10>)

#### Command

```
access-control-class-ramping-step-size (<1-10>)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

access-control-class-ramping-step-size

Configure Access Control Class ramping step size

<1-10>

Set the number of Access Control Classes to enable per ramping step

### 1.17.7 access-control-class-rotate <0-10>

#### Command

```
access-control-class-rotate <0-10>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

access-control-class-rotate

Enable Access Control Class allowed subset rotation

<0-10>

Size of the rotating allowed ACC 0-9 subset (default=10, no subset)

---



### 1.17.8 access-control-class-rotate-quantum <1-65535>

#### Command

```
access-control-class-rotate-quantum <1-65535>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

access-control-class-rotate-quantum

Time between rotation of ACC 0-9 generated subsets

<1-65535>

Time in seconds (default=20)

### 1.17.9 amr tch-f hysteresis (ms|bts) <0-15>

#### Command

```
amr tch-f hysteresis (ms|bts) <0-15>
```

#### Application specific attributes

Flag: 1

This command applies for newly created lchans

#### Parameters

amr

Adaptive Multi Rate settings

tch-f

Full Rate

hysteresis

AMR hysteresis between codecs

ms

MS side

bts

BTS side

<0-15>

Hysteresis between codec 1 and 2

---

### 1.17.10 amr tch-f hysteresis (ms|bts) <0-15> <0-15>

#### Command

```
amr tch-f hysteresis (ms|bts) <0-15> <0-15>
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-f

Full Rate

##### hysteresis

AMR hysteresis between codecs

##### ms

MS side

##### bts

BTS side

##### <0-15>

Hysteresis between codec 1 and 2

##### <0-15>

Hysteresis between codec 1 and 2

### 1.17.11 amr tch-f hysteresis (ms|bts) <0-15> <0-15> <0-15>

#### Command

```
amr tch-f hysteresis (ms|bts) <0-15> <0-15> <0-15>
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-f

Full Rate

---

hysteresis

AMR hysteresis between codecs

ms

MS side

bts

BTS side

<0-15>

Hysteresis between codec 1 and 2

<0-15>

Hysteresis between codec 1 and 2

<0-15>

Hysteresis between codec 1 and 2

### 1.17.12 amr tch-f modes (0|1|2|3|4|5|6|7)

Command

```
amr tch-f modes (0|1|2|3|4|5|6|7)
```

Application specific attributes

Flag: 1

This command applies for newly created lchans

Parameters

amr

Adaptive Multi Rate settings

tch-f

Full Rate

modes

Codec modes to use with AMR codec

0

4,75k

1

5,15k

2

5,90k

3

6,70k

4

7,40k

5	7,95k
6	10,2k
7	12,2k

### 1.17.13 amr tch-f modes (0|1|2|3|4|5|6|7) (0|1|2|3|4|5|6|7)

#### Command

```
amr tch-f modes (0|1|2|3|4|5|6|7) (0|1|2|3|4|5|6|7)
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-f

Full Rate

##### modes

Codec modes to use with AMR codec

0	4,75k
1	5,15k
2	5,90k
3	6,70k
4	7,40k
5	7,95k
6	10,2k
7	12,2k

0	4,75k
1	5,15k
2	5,90k
3	6,70k
4	7,40k
5	7,95k
6	10,2k
7	12,2k

#### 1.17.14 **amr tch-f modes (0|1|2|3|4|5|6|7) (0|1|2|3|4|5|6|7) (0|1|2|3|4|5|6|7)**

##### Command

```
amr tch-f modes (0|1|2|3|4|5|6|7) (0|1|2|3|4|5|6|7) (0|1|2|3|4|5|6|7)
```

##### Application specific attributes

##### Flag: l

This command applies for newly created lchans

##### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-f

Full Rate

##### modes

Codec modes to use with AMR codec

0	4,75k
1	5,15k
2	5,90k

3  
6,70k  
4  
7,40k  
5  
7,95k  
6  
10,2k  
7  
12,2k  
0  
4,75k  
1  
5,15k  
2  
5,90k  
3  
6,70k  
4  
7,40k  
5  
7,95k  
6  
10,2k  
7  
12,2k  
0  
4,75k  
1  
5,15k  
2  
5,90k  
3  
6,70k  
4  
7,40k  
5  
7,95k

---

6  
10,2k

7  
12,2k

### 1.17.15 **amr tch-f modes (0|1|2|3|4|5|6|7) (0|1|2|3|4|5|6|7) (0|1|2|3|4|5|6|7) (0|1|2|3|4...**

#### Command

```
amr tch-f modes (0|1|2|3|4|5|6|7) (0|1|2|3|4|5|6|7) (0|1|2|3|4|5|6|7) (0|1|2|3|4|5|6|7)
```

#### Application specific attributes

Flag: 1

This command applies for newly created lchans

#### Parameters

amr

Adaptive Multi Rate settings

tch-f

Full Rate

modes

Codec modes to use with AMR codec

0  
4,75k

1  
5,15k

2  
5,90k

3  
6,70k

4  
7,40k

5  
7,95k

6  
10,2k

7  
12,2k

0  
4,75k

- 1
  - 5,15k
- 2
  - 5,90k
- 3
  - 6,70k
- 4
  - 7,40k
- 5
  - 7,95k
- 6
  - 10,2k
- 7
  - 12,2k
- 0
  - 4,75k
- 1
  - 5,15k
- 2
  - 5,90k
- 3
  - 6,70k
- 4
  - 7,40k
- 5
  - 7,95k
- 6
  - 10,2k
- 7
  - 12,2k
- 0
  - 4,75k
- 1
  - 5,15k
- 2
  - 5,90k
- 3
  - 6,70k



- 4  
7,40k
- 5  
7,95k
- 6  
10,2k
- 7  
12,2k

### 1.17.16 amr tch-f start-mode (auto|1|2|3|4)

#### Command

```
amr tch-f start-mode (auto|1|2|3|4)
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-f

Full Rate

##### start-mode

Initial codec to use with AMR

##### auto

Automatically

##### 1

First codec

##### 2

Second codec

##### 3

Third codec

##### 4

Fourth codec

### 1.17.17 amr tch-f threshold (ms|bts) <0-63>

#### Command

```
amr tch-f threshold (ms|bts) <0-63>
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-f

Full Rate

##### threshold

AMR threshold between codecs

##### ms

MS side

##### bts

BTS side

##### <0-63>

Threshold between codec 1 and 2

### 1.17.18 amr tch-f threshold (ms|bts) <0-63> <0-63>

#### Command

```
amr tch-f threshold (ms|bts) <0-63> <0-63>
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-f

Full Rate

##### threshold

AMR threshold between codecs

---

ms

MS side

bts

BTS side

<0-63>

Threshold between codec 1 and 2

<0-63>

Threshold between codec 1 and 2

### 1.17.19 amr tch-f threshold (ms|bts) <0-63> <0-63> <0-63>

Command

```
amr tch-f threshold (ms|bts) <0-63> <0-63> <0-63>
```

Application specific attributes

Flag: 1

This command applies for newly created lchans

Parameters

amr

Adaptive Multi Rate settings

tch-f

Full Rate

threshold

AMR threshold between codecs

ms

MS side

bts

BTS side

<0-63>

Threshold between codec 1 and 2

<0-63>

Threshold between codec 1 and 2

<0-63>

Threshold between codec 1 and 2

### 1.17.20 amr tch-h hysteresis (ms|bts) <0-15>

#### Command

```
amr tch-h hysteresis (ms|bts) <0-15>
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-h

Half Rate

##### hysteresis

AMR hysteresis between codecs

##### ms

MS side

##### bts

BTS side

##### <0-15>

Hysteresis between codec 1 and 2

### 1.17.21 amr tch-h hysteresis (ms|bts) <0-15> <0-15>

#### Command

```
amr tch-h hysteresis (ms|bts) <0-15> <0-15>
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-h

Half Rate

##### hysteresis

AMR hysteresis between codecs

---

ms

MS side

bts

BTS side

<0-15>

Hysteresis between codec 1 and 2

<0-15>

Hysteresis between codec 1 and 2

### 1.17.22 amr tch-h hysteresis (ms|bts) <0-15> <0-15> <0-15>

Command

```
amr tch-h hysteresis (ms|bts) <0-15> <0-15> <0-15>
```

Application specific attributes

Flag: 1

This command applies for newly created lchans

Parameters

amr

Adaptive Multi Rate settings

tch-h

Half Rate

hysteresis

AMR hysteresis between codecs

ms

MS side

bts

BTS side

<0-15>

Hysteresis between codec 1 and 2

<0-15>

Hysteresis between codec 1 and 2

<0-15>

Hysteresis between codec 1 and 2

### 1.17.23 amr tch-h modes (0|1|2|3|4|5)

#### Command

```
amr tch-h modes (0|1|2|3|4|5)
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-h

Half Rate

##### modes

Codec modes to use with AMR codec

##### 0

4,75k

##### 1

5,15k

##### 2

5,90k

##### 3

6,70k

##### 4

7,40k

##### 5

7,95k

### 1.17.24 amr tch-h modes (0|1|2|3|4|5) (0|1|2|3|4|5)

#### Command

```
amr tch-h modes (0|1|2|3|4|5) (0|1|2|3|4|5)
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

---

amr

Adaptive Multi Rate settings

tch-h

Half Rate

modes

Codec modes to use with AMR codec

0

4,75k

1

5,15k

2

5,90k

3

6,70k

4

7,40k

5

7,95k

0

4,75k

1

5,15k

2

5,90k

3

6,70k

4

7,40k

5

7,95k

#### 1.17.25 amr tch-h modes (0|1|2|3|4|5) (0|1|2|3|4|5) (0|1|2|3|4|5)

Command

```
amr tch-h modes (0|1|2|3|4|5) (0|1|2|3|4|5) (0|1|2|3|4|5)
```

Application specific attributes

Flag: 1

This command applies for newly created lchans

Parameters

amr

Adaptive Multi Rate settings

tch-h

Half Rate

modes

Codec modes to use with AMR codec

0

4,75k

1

5,15k

2

5,90k

3

6,70k

4

7,40k

5

7,95k

0

4,75k

1

5,15k

2

5,90k

3

6,70k

4

7,40k

5

7,95k

0

4,75k

1

5,15k

2

5,90k

3

6,70k



4  
7,40k

5  
7,95k

### 1.17.26 amr tch-h modes (0|1|2|3|4|5) (0|1|2|3|4|5) (0|1|2|3|4|5) (0|1|2|3|4|5)

#### Command

```
amr tch-h modes (0|1|2|3|4|5) (0|1|2|3|4|5) (0|1|2|3|4|5) (0|1|2|3|4|5)
```

#### Application specific attributes

Flag: 1

This command applies for newly created lchans

#### Parameters

amr

Adaptive Multi Rate settings

tch-h

Half Rate

modes

Codec modes to use with AMR codec

0  
4,75k

1  
5,15k

2  
5,90k

3  
6,70k

4  
7,40k

5  
7,95k

0  
4,75k

1  
5,15k

2  
5,90k

3	6,70k
4	7,40k
5	7,95k
0	4,75k
1	5,15k
2	5,90k
3	6,70k
4	7,40k
5	7,95k
0	4,75k
1	5,15k
2	5,90k
3	6,70k
4	7,40k
5	7,95k

### 1.17.27 amr tch-h start-mode (auto|1|2|3|4)

Command

```
amr tch-h start-mode (auto|1|2|3|4)
```

Application specific attributes

Flag: 1

This command applies for newly created lchans

### Parameters

amr

Adaptive Multi Rate settings

tch-h

Half Rate

start-mode

Initial codec to use with AMR

auto

Automatically

1

First codec

2

Second codec

3

Third codec

4

Fourth codec

## 1.17.28 amr tch-h threshold (ms|bts) <0-63>

### Command

```
amr tch-h threshold (ms|bts) <0-63>
```

### Application specific attributes

Flag: 1

This command applies for newly created lchans

### Parameters

amr

Adaptive Multi Rate settings

tch-h

Half Rate

threshold

AMR threshold between codecs

ms

MS side

bts

BTS side

<0-63>

Threshold between codec 1 and 2

---

### 1.17.29 amr tch-h threshold (ms|bts) <0-63> <0-63>

#### Command

```
amr tch-h threshold (ms|bts) <0-63> <0-63>
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-h

Half Rate

##### threshold

AMR threshold between codecs

##### ms

MS side

##### bts

BTS side

##### <0-63>

Threshold between codec 1 and 2

##### <0-63>

Threshold between codec 1 and 2

### 1.17.30 amr tch-h threshold (ms|bts) <0-63> <0-63> <0-63>

#### Command

```
amr tch-h threshold (ms|bts) <0-63> <0-63> <0-63>
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### amr

Adaptive Multi Rate settings

##### tch-h

Half Rate

---

threshold

AMR threshold between codecs

ms

MS side

bts

BTS side

<0-63>

Threshold between codec 1 and 2

<0-63>

Threshold between codec 1 and 2

<0-63>

Threshold between codec 1 and 2

### 1.17.31 band BAND

Command

```
band BAND
```

Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

Parameters

band

Set the frequency band of this BTS

BAND

Frequency band

### 1.17.32 base\_station\_id\_code <0-63>

Command

```
base_station_id_code <0-63>
```

Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

Parameters

base\_station\_id\_code

Set the Base Station Identity Code (BSIC) of this BTS

<0-63>

BSIC of this BTS

### 1.17.33 ccch load-indication-threshold <0-100>

#### Command

```
ccch load-indication-threshold <0-100>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

ccch

Common Control Channel

load-indication-threshold

Percentage of CCCH load at which BTS sends RSL CCCH LOAD IND

<0-100>

CCCH Load Threshold in percent (Default: 10)

### 1.17.34 cell bar qualify (0|1)

#### Command

```
cell bar qualify (0|1)
```

#### Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

cell

Cell Parameters

bar

Cell Bar Qualify

qualify

Cell Bar Qualify

0

Set CBQ to 0

1

Set CBQ to 1

### 1.17.35 cell barred (0|1)

#### Command

```
cell barred (0|1)
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### cell

Should this cell be barred from access?

##### barred

Should this cell be barred from access?

##### 0

Cell should NOT be barred

##### 1

Cell should be barred

### 1.17.36 cell reselection hysteresis <0-14>

#### Command

```
cell reselection hysteresis <0-14>
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### cell

Cell Parameters

##### reselection

Cell re-selection parameters

##### hysteresis

Cell Re-Selection Hysteresis in dB

##### <0-14>

Cell Re-Selection Hysteresis in dB

---

### 1.17.37 cell reselection offset <0-126>

#### Command

```
cell reselection offset <0-126>
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### cell

Cell Parameters

#### reselection

Cell Re-Selection Parameters

#### offset

Cell Re-Selection Offset (CRO) in dB

#### <0-126>

Cell Re-Selection Offset (CRO) in dB

### 1.17.38 cell\_identity <0-65535>

#### Command

```
cell_identity <0-65535>
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### cell\_identity

Set the Cell identity of this BTS

#### <0-65535>

Cell Identity



### 1.17.39 channel allocator (ascending|descending)

#### Command

```
channel allocator (ascending|descending)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

channel

Channel Allocator

allocator

Channel Allocator

ascending

Allocate Timeslots and Transceivers in ascending order

descending

Allocate Timeslots and Transceivers in descending order

### 1.17.40 channel-description attach (0|1)

#### Command

```
channel-description attach (0|1)
```

#### Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

channel-description

Channel Description

attach

Set if attachment is required

0

Attachment is NOT required

1

Attachment is required (standard)

---

### 1.17.41 channel-description bs-ag-blks-res <0-7>

#### Command

```
channel-description bs-ag-blks-res <0-7>
```

#### Application specific attributes

##### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### channel-description

Channel Description

##### bs-ag-blks-res

Set number of blocks reserved for access grant

##### <0-7>

Number of blocks reserved for access grant

### 1.17.42 channel-description bs-pa-mfrms <2-9>

#### Command

```
channel-description bs-pa-mfrms <2-9>
```

#### Application specific attributes

##### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### channel-description

Channel Description

##### bs-pa-mfrms

Set number of multiframe periods for paging groups

##### <2-9>

Number of multiframe periods for paging groups

---

### 1.17.43 codec-support fr

#### Command

```
codec-support fr
```

#### Application specific attributes

#### Flag: 1

This command applies for newly created lchans

#### Parameters

#### codec-support

Codec Support settings

#### fr

Fullrate

### 1.17.44 codec-support fr (hr|efr|amr)

#### Command

```
codec-support fr (hr|efr|amr)
```

#### Application specific attributes

#### Flag: 1

This command applies for newly created lchans

#### Parameters

#### codec-support

Codec Support settings

#### fr

Fullrate

#### hr

Half Rate

#### efr

Enhanced Full Rate

#### amr

Adaptive Multirate

### 1.17.45 codec-support fr (hr|efr|amr) (hr|efr|amr)

#### Command

```
codec-support fr (hr|efr|amr) (hr|efr|amr)
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### codec-support

Codec Support settings

##### fr

Fullrate

##### hr

Half Rate

##### efr

Enhanced Full Rate

##### amr

Adaptive Multirate

##### hr

Half Rate

##### efr

Enhanced Full Rate

##### amr

Adaptive Multirate

### 1.17.46 codec-support fr (hr|efr|amr) (hr|efr|amr) (hr|efr|amr)

#### Command

```
codec-support fr (hr|efr|amr) (hr|efr|amr) (hr|efr|amr)
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### codec-support

Codec Support settings

fr  
Fullrate

hr  
Half Rate

efr  
Enhanced Full Rate

amr  
Adaptive Multirate

hr  
Half Rate

efr  
Enhanced Full Rate

amr  
Adaptive Multirate

hr  
Half Rate

efr  
Enhanced Full Rate

amr  
Adaptive Multirate

#### 1.17.47 **codec-support fr (hr|efr|amr) (hr|efr|amr) (hr|efr|amr) (hr|efr|amr)**

Command

```
codec-support fr (hr|efr|amr) (hr|efr|amr) (hr|efr|amr) (hr|efr|amr)
```

Application specific attributes

Flag: 1

This command applies for newly created lchans

Parameters

codec-support  
Codec Support settings

fr  
Fullrate

hr  
Half Rate

efr  
Enhanced Full Rate

amr  
Adaptive Multirate

hr  
Half Rate

efr  
Enhanced Full Rate

amr  
Adaptive Multirate

hr  
Half Rate

efr  
Enhanced Full Rate

amr  
Adaptive Multirate

hr  
Half Rate

efr  
Enhanced Full Rate

amr  
Adaptive Multirate

### 1.17.48 con-connection-group <1-31>

Command

```
con-connection-group <1-31>
```

Global attributes

Flag: !

This command applies immediately

Parameters

con-connection-group

Configure a CON (Concentrator) Connection Group

<1-31>

CON Connection Group Number

### 1.17.49 del-connection-group <1-31>

#### Command

```
del-connection-group <1-31>
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### del-connection-group

Delete a CON (Concentrator) Connection Group

#### <1-31>

CON Connection Group Number

### 1.17.50 depends-on-bts <0-255>

#### Command

```
depends-on-bts <0-255>
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### depends-on-bts

This BTS can only be started if another one is up

#### <0-255>

BTS Number

### 1.17.51 description .TEXT

#### Command

```
description .TEXT
```

#### Parameters

#### description

Save human-readable description of the object

#### .TEXT

Text until the end of the line

---

### 1.17.52 dtx downlink

#### Command

```
dtx downlink
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### dtx

Configure discontinuous transmission

##### downlink

Enable Downlink DTX for this BTS

### 1.17.53 dtx uplink [force]

#### Command

```
dtx uplink [force]
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### dtx

Configure discontinuous transmission

##### uplink

Enable Uplink DTX for this BTS

##### [force]

MS 'shall' use DTXu instead of 'may' use (might not be supported by older phones).

### 1.17.54 early-classmark-sending (allowed|forbidden)

#### Command

```
early-classmark-sending (allowed|forbidden)
```

#### Application specific attributes

---



Flag: r

This command applies on A-bis RSL link (re)establishment

Parameters

early-classmark-sending

Early Classmark Sending

allowed

Early Classmark Sending is allowed

forbidden

Early Classmark Sending is forbidden

### 1.17.55 early-classmark-sending-3g (allowed|forbidden)

Command

```
early-classmark-sending-3g (allowed|forbidden)
```

Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

Parameters

early-classmark-sending-3g

3G Early Classmark Sending

allowed

3G Early Classmark Sending is allowed

forbidden

3G Early Classmark Sending is forbidden

### 1.17.56 force-combined-si

Command

```
force-combined-si
```

Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

Parameters

force-combined-si

Force the generation of a single SI (no ter/bis)

---

### 1.17.57 gprs ccn-active (0|1|default)

#### Command

```
gprs ccn-active (0|1|default)
```

#### Application specific attributes

##### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### gprs

GPRS Packet Network

##### ccn-active

Set CCN\_ACTIVE in the GPRS Cell Options IE on the BCCH (SI13)

##### 0

Disable

##### 1

Enable

##### default

Default based on BTS type support

### 1.17.58 gprs cell bvci <2-65535>

#### Command

```
gprs cell bvci <2-65535>
```

#### Application specific attributes

##### Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

##### gprs

GPRS Packet Network

##### cell

GPRS Cell Settings

##### bvci

GPRS BSSGP VC Identifier

##### <2-65535>

GPRS BSSGP VC Identifier

---

### 1.17.59 gprs cell timer (blocking-timer|blocking-retries|unblocking-retries|reset-timer|...

#### Command

```
gprs cell timer (blocking-timer|blocking-retries|unblocking-retries|reset-timer|reset- ↔  
retries|suspend-timer|suspend-retries|resume-timer|resume-retries|capability-update ↔  
-timer|capability-update-retries) <0-255>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

gprs

GPRS Packet Network

cell

Cell / BSSGP

timer

Cell/BSSGP Timer

blocking-timer

Tbvc-block timeout

blocking-retries

Tbvc-block retries

unblocking-retries

Tbvc-unblock retries

reset-timer

Tbvcc-reset timeout

reset-retries

Tbvc-reset retries

suspend-timer

Tbvc-suspend timeout

suspend-retries

Tbvc-suspend retries

resume-timer

Tbvc-resume timeout

resume-retries

Tbvc-resume retries

capability-update-timer

Tbvc-capacity-update timeout

capability-update-retries

Tbvc-capacity-update retries

<0-255>

Timer Value

### 1.17.60 gprs control-ack-type-rach

#### Command

```
gprs control-ack-type-rach
```

#### Application specific attributes

##### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### gprs

GPRS Packet Network

##### control-ack-type-rach

Set GPRS Control Ack Type for PACKET CONTROL ACKNOWLEDGMENT message to four access bursts format instead of default RLC/MAC control block

### 1.17.61 gprs egprs-packet-channel-request

#### Command

```
gprs egprs-packet-channel-request
```

#### Application specific attributes

##### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### gprs

GPRS Packet Network

##### egprs-packet-channel-request

EGPRS Packet Channel Request support

### 1.17.62 gprs mode (none|gprs|egprs)

#### Command

```
gprs mode (none|gprs|egprs)
```

#### Application specific attributes

##### Flag: o

This command applies on A-bis OML link (re)establishment

---

#### Parameters

gprs

GPRS Packet Network

mode

GPRS Mode for this BTS

none

GPRS Disabled on this BTS

gprs

GPRS Enabled on this BTS

egprs

EGPRS (EDGE) Enabled on this BTS

### 1.17.63 gprs network-control-order (nc0|nc1|nc2)

#### Command

```
gprs network-control-order (nc0|nc1|nc2)
```

#### Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

gprs

GPRS Packet Network

network-control-order

GPRS Network Control Order

nc0

MS controlled cell re-selection, no measurement reporting

nc1

MS controlled cell re-selection, MS sends measurement reports

nc2

Network controlled cell re-selection, MS sends measurement reports

### 1.17.64 gprs ns timer (tns-block|tns-block-retries|tns-reset|tns-reset-retries|tns-test|...

#### Command

```
gprs ns timer (tns-block|tns-block-retries|tns-reset|tns-reset-retries|tns-test|tns- ↵  
alive|tns-alive-retries|tsns-prov) <0-255>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

gprs

GPRS Packet Network

ns

Network Service

timer

Network Service Timer

tns-block

(un)blocking Timer (Tns-block) timeout

tns-block-retries

(un)blocking Timer (Tns-block) number of retries

tns-reset

Reset Timer (Tns-reset) timeout

tns-reset-retries

Reset Timer (Tns-reset) number of retries

tns-test

Test Timer (Tns-test) timeout

tns-alive

Alive Timer (Tns-alive) timeout

tns-alive-retries

Alive Timer (Tns-alive) number of retries

tsns-prov

SNS Provision Timer (Tsns-prov) timeout

<0-255>

Timer Value

---

### 1.17.65 gprs nsei <0-65535>

#### Command

```
gprs nsei <0-65535>
```

#### Application specific attributes

#### Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

#### gprs

GPRS Packet Network

#### nsei

GPRS NS Entity Identifier

<0-65535>

GPRS NS Entity Identifier

### 1.17.66 gprs nsvc <0-1> local udp port <0-65535>

#### Command

```
gprs nsvc <0-1> local udp port <0-65535>
```

#### Application specific attributes

#### Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

#### gprs

GPRS Packet Network

#### nsvc

Network Service Virtual Connection (NS-VC)

<0-1>

NSVC Logical Number

#### local

GPRS NS Local UDP Port

#### udp

GPRS NS Local UDP Port

#### port

GPRS NS Local UDP Port

<0-65535>

GPRS NS Local UDP Port Number

### 1.17.67 gprs nsvc <0-1> nsvci <0-65535>

#### Command

```
gprs nsvc <0-1> nsvci <0-65535>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

gprs

GPRS Packet Network

nsvc

Network Service Virtual Connection (NS-VC)

<0-1>

NSVC Logical Number

nsvci

NS Virtual Connection Identifier

<0-65535>

GPRS NS VC Identifier

### 1.17.68 gprs nsvc <0-1> remote ip (A.B.C.D|X:X::X:X)

#### Command

```
gprs nsvc <0-1> remote ip (A.B.C.D|X:X::X:X)
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

gprs

GPRS Packet Network

nsvc

Network Service Virtual Connection (NS-VC)

<0-1>

NSVC Logical Number

remote

GPRS NS Remote IP Address



ip

GPRS NS Remote IP Address

A.B.C.D

GPRS NS Remote IPv4 Address

X:X::X:X

GPRS NS Remote IPv6 Address

### 1.17.69 gprs nsvc <0-1> remote udp port <0-65535>

Command

```
gprs nsvc <0-1> remote udp port <0-65535>
```

Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

Parameters

gprs

GPRS Packet Network

nsvc

Network Service Virtual Connection (NS-VC)

<0-1>

NSVC Logical Number

remote

GPRS NS Remote UDP Port

udp

GPRS NS Remote UDP Port

port

GPRS NS Remote UDP Port

<0-65535>

GPRS NS Remote UDP Port Number

### 1.17.70 gprs power-control alpha <0-10>

Command

```
gprs power-control alpha <0-10>
```

Application specific attributes

---

Flag: r

This command applies on A-bis RSL link (re)establishment

Parameters

gprs

GPRS Packet Network

power-control

GPRS Global Power Control Parameters IE (SI13)

alpha

Set alpha

<0-10>

alpha for MS output power control in units of 0.1 (defaults to 0)

### 1.17.71 gprs routing area <0-255>

Command

```
gprs routing area <0-255>
```

Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

Parameters

gprs

GPRS Packet Network

routing

GPRS Routing Area Code

area

GPRS Routing Area Code

<0-255>

GPRS Routing Area Code

### 1.17.72 handover (0|1|default)

Command

```
handover (0|1|default)
```

Global attributes

---

Flag: !

This command applies immediately

Parameters

handover

Handover general config

0

Disable in-call handover

1

Enable in-call handover

default

Enable/disable handover: Use default (0), remove explicit setting on this node

### 1.17.73 handover algorithm (1|2|default)

Command

```
handover algorithm (1|2|default)
```

Global attributes

Flag: !

This command applies immediately

Parameters

handover

Handover general config

algorithm

Choose algorithm for handover decision

1

Algorithm 1: trigger handover based on comparing current cell and neighbor RxLev and RxQual, only.

2

Algorithm 2: trigger handover on RxLev/RxQual, and also to balance the load across several cells. Consider available codecs. Prevent repeated handover by penalty timers.

default

Use default (1), remove explicit setting on this node

---

### 1.17.74 handover1 maximum distance (<0-9999>|default)

#### Command

```
handover1 maximum distance (<0-9999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover1

Handover options for handover decision algorithm 1

##### maximum

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

##### distance

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

##### <0-9999>

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

##### default

Use default (9999), remove explicit setting on this node

### 1.17.75 handover1 power budget hysteresis (<0-999>|default)

#### Command

```
handover1 power budget hysteresis (<0-999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover1

Handover options for handover decision algorithm 1

##### power

Neighbor cell power triggering

##### budget

Neighbor cell power triggering

##### hysteresis

How many dB stronger must a neighbor be to become a HO candidate

##### <0-999>

Neighbor's strength difference in dB

##### default

Use default (3), remove explicit setting on this node

### 1.17.76 handover1 power budget interval (<1-99>|default)

#### Command

```
handover1 power budget interval (<1-99>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover1

Handover options for handover decision algorithm 1

##### power

Neighbor cell power triggering

##### budget

Neighbor cell power triggering

##### interval

How often to check for a better cell (SACCH frames)

##### <1-99>

Check for stronger neighbor every N number of SACCH frames

##### default

Use default (6), remove explicit setting on this node

### 1.17.77 handover1 window rxlev averaging (<1-10>|default)

#### Command

```
handover1 window rxlev averaging (<1-10>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover1

Handover options for handover decision algorithm 1

##### window

Measurement averaging settings

##### rxlev

Received-Level averaging

---

averaging

How many RxLev measurements to use for averaging

<1-10>

RxLev averaging: Number of values to average over

default

Use default (10), remove explicit setting on this node

### 1.17.78 handover1 window rxlev neighbor averaging (<1-10>|default)

Command

```
handover1 window rxlev neighbor averaging (<1-10>|default)
```

Global attributes

Flag: !

This command applies immediately

Parameters

handover1

Handover options for handover decision algorithm 1

window

Measurement averaging settings

rxlev

Received-Level averaging

neighbor

How many Neighbor RxLev measurements to use for averaging

averaging

How many Neighbor RxLev measurements to use for averaging

<1-10>

Neighbor RxLev averaging: Number of values to average over

default

Use default (10), remove explicit setting on this node

### 1.17.79 handover1 window rxqual averaging (<1-10>|default)

Command

```
handover1 window rxqual averaging (<1-10>|default)
```

Global attributes

---

Flag: !

This command applies immediately

#### Parameters

handover1

Handover options for handover decision algorithm 1

window

Measurement averaging settings

rxqual

Received-Quality averaging

averaging

How many RxQual measurements to use for averaging

<1-10>

RxQual averaging: Number of values to average over

default

Use default (1), remove explicit setting on this node

### 1.17.80 handover2 afs-bias rxlev (<0-20>|default)

#### Command

```
handover2 afs-bias rxlev (<0-20>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

handover2

Handover options for handover decision algorithm 2

afs-bias

Configure bias to prefer AFS (AMR on TCH/F) over other codecs

rxlev

RxLev improvement bias for AFS over other codecs

<0-20>

Virtual RxLev improvement (dB)

default

Use default (0), remove explicit setting on this node

### 1.17.81 handover2 afs-bias rxqual (<0-7>|default)

#### Command

```
handover2 afs-bias rxqual (<0-7>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### afs-bias

Configure bias to prefer AFS (AMR on TCH/F) over other codecs

##### rxqual

RxQual improvement bias for AFS over other codecs

##### <0-7>

Virtual RxQual improvement

##### default

Use default (0), remove explicit setting on this node

### 1.17.82 handover2 assignment (0|1|default)

#### Command

```
handover2 assignment (0|1|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### assignment

Enable or disable in-call channel re-assignment within the same cell

##### 0

Disable in-call assignment

##### 1

Enable in-call assignment

##### default

Use default (0), remove explicit setting on this node

---



### 1.17.83 handover2 max-handovers (<1-9999>|default)

#### Command

```
handover2 max-handovers (<1-9999>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### max-handovers

Maximum number of concurrent handovers allowed per cell

<1-9999>

Number

##### default

Use default (9999), remove explicit setting on this node

### 1.17.84 handover2 maximum distance (<0-9999>|default)

#### Command

```
handover2 maximum distance (<0-9999>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### maximum

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

##### distance

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

<0-9999>

Maximum Timing-Advance value (i.e. MS distance) before triggering HO

##### default

Use default (9999), remove explicit setting on this node

### 1.17.85 handover2 min rxlev (<-110--50>|default)

#### Command

```
handover2 min rxlev (<-110--50>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### min

Minimum Level/Quality thresholds before triggering HO

##### rxlev

How weak may RxLev of an MS become before triggering HO

<-110--50>

minimum RxLev (dBm; note: negative values)

##### default

Use default (-100), remove explicit setting on this node

### 1.17.86 handover2 min rxqual (<0-7>|default)

#### Command

```
handover2 min rxqual (<0-7>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### min

Minimum Level/Quality thresholds before triggering HO

##### rxqual

How bad may RxQual of an MS become before triggering HO, where 0 is the best quality (bit error rate < 0.2%) and 7 is the worst quality (bit error rate > 12.8%), see 3GPP TS 45.008 8.2.4.

<0-7>

worst acceptable RxQual

##### default

Use default (5), remove explicit setting on this node

### 1.17.87 handover2 min-free-slots tch/f (<0-9999>|default)

#### Command

```
handover2 min-free-slots tch/f (<0-9999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### min-free-slots

Minimum free TCH timeslots before cell is considered congested

##### tch/f

Minimum free TCH/F timeslots before cell is considered congested

##### <0-9999>

Number of TCH/F slots

##### default

Use default (0), remove explicit setting on this node

### 1.17.88 handover2 min-free-slots tch/h (<0-9999>|default)

#### Command

```
handover2 min-free-slots tch/h (<0-9999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### min-free-slots

Minimum free TCH timeslots before cell is considered congested

##### tch/h

Minimum free TCH/H timeslots before cell is considered congested

##### <0-9999>

Number of TCH/H slots

##### default

Use default (0), remove explicit setting on this node

---

### 1.17.89 handover2 penalty-time failed-assignment (<0-99999>|default)

#### Command

```
handover2 penalty-time failed-assignment (<0-99999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### penalty-time

Set penalty times to wait between repeated handovers

##### failed-assignment

Time to suspend handover for a subscriber after a failed re-assignment within this cell; see also 'handover2 retries'

##### <0-99999>

Seconds

##### default

Use default (60), remove explicit setting on this node

### 1.17.90 handover2 penalty-time failed-ho (<0-99999>|default)

#### Command

```
handover2 penalty-time failed-ho (<0-99999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### penalty-time

Set penalty times to wait between repeated handovers

##### failed-ho

Time to suspend handover for a subscriber after a failed handover into this cell; see also 'handover2 retries'

##### <0-99999>

Seconds

##### default

Use default (60), remove explicit setting on this node

---

### 1.17.91 handover2 penalty-time max-distance (<0-99999>|default)

#### Command

```
handover2 penalty-time max-distance (<0-99999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### penalty-time

Set penalty times to wait between repeated handovers

##### max-distance

Time to suspend handover for a subscriber after leaving this cell due to exceeding max distance; see also 'handover2 retries'

##### <0-99999>

Seconds

##### default

Use default (300), remove explicit setting on this node

### 1.17.92 handover2 power budget hysteresis (<0-999>|default)

#### Command

```
handover2 power budget hysteresis (<0-999>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### power

Neighbor cell power triggering

##### budget

Neighbor cell power triggering

##### hysteresis

How many dB stronger must a neighbor be to become a HO candidate

##### <0-999>

Neighbor's strength difference in dB

##### default

Use default (3), remove explicit setting on this node

---

### 1.17.93 handover2 power budget interval (<1-99>|default)

#### Command

```
handover2 power budget interval (<1-99>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### power

Neighbor cell power triggering

##### budget

Neighbor cell power triggering

##### interval

How often to check for a better cell (SACCH frames)

##### <1-99>

Check for stronger neighbor every N number of SACCH frames

##### default

Use default (6), remove explicit setting on this node

### 1.17.94 handover2 retries (<0-9>|default)

#### Command

```
handover2 retries (<0-9>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### retries

Number of times to immediately retry a failed handover/assignment, before a penalty time is applied

##### <0-9>

Number of retries

##### default

Use default (0), remove explicit setting on this node

---

### 1.17.95 handover2 tdma-measurement (full|subset|default)

#### Command

```
handover2 tdma-measurement (full|subset|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### handover2

Handover options for handover decision algorithm 2

#### tdma-measurement

Define measurement set of TDMA frames

#### full

Full set of 102/104 TDMA frames

#### subset

Sub set of 4 TDMA frames (SACCH)

#### default

Use default (subset), remove explicit setting on this node

### 1.17.96 handover2 window rxlev averaging (<1-10>|default)

#### Command

```
handover2 window rxlev averaging (<1-10>|default)
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### handover2

Handover options for handover decision algorithm 2

#### window

Measurement averaging settings

#### rxlev

Received-Level averaging

#### averaging

How many RxLev measurements to use for averaging

#### <1-10>

RxLev averaging: Number of values to average over

#### default

Use default (10), remove explicit setting on this node

### 1.17.97 handover2 window rxlev neighbor averaging (<1-10>|default)

#### Command

```
handover2 window rxlev neighbor averaging (<1-10>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### window

Measurement averaging settings

##### rxlev

Received-Level averaging

##### neighbor

How many Neighbor RxLev measurements to use for averaging

##### averaging

How many Neighbor RxLev measurements to use for averaging

##### <1-10>

Neighbor RxLev averaging: Number of values to average over

##### default

Use default (10), remove explicit setting on this node

### 1.17.98 handover2 window rxqual averaging (<1-10>|default)

#### Command

```
handover2 window rxqual averaging (<1-10>|default)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### handover2

Handover options for handover decision algorithm 2

##### window

Measurement averaging settings

---



rxqual

Received-Quality averaging

averaging

How many RxQual measurements to use for averaging

<1-10>

RxQual averaging: Number of values to average over

default

Use default (1), remove explicit setting on this node

### 1.17.99 ipa rsl-ip A.B.C.D

Command

```
ipa rsl-ip A.B.C.D
```

Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

Parameters

ipa

Abis/IP specific options

rsl-ip

Set the IPA RSL IP Address of the BSC

A.B.C.D

Destination IP address for RSL connection

### 1.17.100 ipa unit-id <0-65534> <0-255>

Command

```
ipa unit-id <0-65534> <0-255>
```

Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

Parameters

ipa

Abis/IP specific options

unit-id

Set the IPA BTS Unit ID

<0-65534>

Unit ID (Site)

<0-255>

Unit ID (BTS)

### 1.17.101 is-connection-list (add|del) <0-2047> <0-2047> <0-255>

#### Command

```
is-connection-list (add|del) <0-2047> <0-2047> <0-255>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

is-connection-list

Interface Switch Connection List

add

Add to IS list

del

Delete from IS list

<0-2047>

ICP1

<0-2047>

ICP2

<0-255>

Contiguity Index

### 1.17.102 location\_area\_code <0-65535>

#### Command

```
location_area_code <0-65535>
```

#### Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

location\_area\_code

Set the Location Area Code (LAC) of this BTS

<0-65535>

LAC

### 1.17.103 ms max power <0-40>

#### Command

```
ms max power <0-40>
```

#### Application specific attributes

#### Flag: 1

This command applies for newly created lchans

#### Parameters

ms

MS Options

max

Maximum transmit power of the MS

power

Maximum transmit power of the MS

<0-40>

Maximum transmit power of the MS in dBm

### 1.17.104 neighbor bts <0-255>

#### Command

```
neighbor bts <0-255>
```

#### Parameters

neighbor

Manage local and remote-BSS neighbor cells

bts

Add Neighbor cell by local BTS number

<0-255>

BTS number

### 1.17.105 neighbor cgi <0-999> <0-999> <0-65535> <0-65535>

#### Command

```
neighbor cgi <0-999> <0-999> <0-65535> <0-65535>
```

#### Parameters

---

neighbor

Manage local and remote-BSS neighbor cells

cgi

Add Neighbor cell by cgi

<0-999>

MCC

<0-999>

MNC

<0-65535>

LAC

<0-65535>

CI

### 1.17.106 neighbor cgi <0-999> <0-999> <0-65535> <0-65535> arfcn <0-1023> bsic (<0-63>|any...

Command

```
neighbor cgi <0-999> <0-999> <0-65535> <0-65535> arfcn <0-1023> bsic (<0-63>|any)
```

Parameters

neighbor

Manage local and remote-BSS neighbor cells

cgi

Add Neighbor cell by cgi

<0-999>

MCC

<0-999>

MNC

<0-65535>

LAC

<0-65535>

CI

arfcn

ARFCN of neighbor cell

<0-1023>

ARFCN value

bsic

BSIC of neighbor cell

<0-63>

BSIC value

any

for all BSICs / use any BSIC in this ARFCN

**1.17.107 neighbor cgi-ps <0-999> <0-999> <0-65535> <0-255> <0-65535>**

## Command

```
neighbor cgi-ps <0-999> <0-999> <0-65535> <0-255> <0-65535>
```

## Parameters

## neighbor

Manage local and remote-BSS neighbor cells

## cgi-ps

Add Neighbor cell by cgi (Packet Switched, with RAC)

<0-999>

MCC

<0-999>

MNC

<0-65535>

LAC

<0-255>

RAC

<0-65535>

CI

**1.17.108 neighbor cgi-ps <0-999> <0-999> <0-65535> <0-255> <0-65535> arfcn <0-1023> bsic ...**

## Command

```
neighbor cgi-ps <0-999> <0-999> <0-65535> <0-255> <0-65535> arfcn <0-1023> bsic ↔  
(<0-63>|any)
```

## Parameters

## neighbor

Manage local and remote-BSS neighbor cells

## cgi-ps

Add Neighbor cell by cgi (Packet Switched, with RAC)

<0-999>

MCC

<0-999>

MNC

<0-65535>

LAC

<0-255>

RAC

<0-65535>

CI

arfcn

ARFCN of neighbor cell

<0-1023>

ARFCN value

bsic

BSIC of neighbor cell

<0-63>

BSIC value

any

for all BSICs / use any BSIC in this ARFCN

### 1.17.109 neighbor lac <0-65535>

Command

```
neighbor lac <0-65535>
```

Parameters

neighbor

Manage local and remote-BSS neighbor cells

lac

Add Neighbor cell by LAC

<0-65535>

LAC

### 1.17.110 neighbor lac <0-65535> arfcn <0-1023> bsic (<0-63>|any)

Command

```
neighbor lac <0-65535> arfcn <0-1023> bsic (<0-63>|any)
```

Parameters

neighbor

Manage local and remote-BSS neighbor cells

lac

Add Neighbor cell by LAC

<0-65535>

LAC

arfcn

ARFCN of neighbor cell

<0-1023>

ARFCN value

bsic

BSIC of neighbor cell

<0-63>

BSIC value

any

for all BSICs / use any BSIC in this ARFCN

### 1.17.111 neighbor lac-ci <0-65535> <0-65535>

Command

```
neighbor lac-ci <0-65535> <0-65535>
```

Parameters

neighbor

Manage local and remote-BSS neighbor cells

lac-ci

Add Neighbor cell by LAC and CI

<0-65535>

LAC

<0-65535>

CI

### 1.17.112 neighbor lac-ci <0-65535> <0-65535> arfcn <0-1023> bsic (<0-63>|any)

Command

```
neighbor lac-ci <0-65535> <0-65535> arfcn <0-1023> bsic (<0-63>|any)
```

Parameters

neighbor

Manage local and remote-BSS neighbor cells

lac-ci

Add Neighbor cell by LAC and CI

<0-65535>

LAC

<0-65535>

CI

arfcn

ARFCN of neighbor cell

<0-1023>

ARFCN value

bsic

BSIC of neighbor cell

<0-63>

BSIC value

any

for all BSICs / use any BSIC in this ARFCN

### 1.17.113 neighbor-list (add|del) arfcn <0-1023>

Command

```
neighbor-list (add|del) arfcn <0-1023>
```

Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

Parameters

neighbor-list

Neighbor List

add

Add to manual neighbor list

del

Delete from manual neighbor list

arfcn

ARFCN of neighbor

<0-1023>

ARFCN of neighbor



### 1.17.114 neighbor-list mode (automatic|manual|manual-si5)

#### Command

```
neighbor-list mode (automatic|manual|manual-si5)
```

#### Application specific attributes

##### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### neighbor-list

Neighbor List

##### mode

Mode of Neighbor List generation

##### automatic

Automatically from all BTS in this BSC

##### manual

Manual

##### manual-si5

Manual with different lists for SI2 and SI5

### 1.17.115 no (bs-power-control|ms-power-control)

#### Command

```
no (bs-power-control|ms-power-control)
```

#### Application specific attributes

##### Flag: l

This command applies for newly created lchans

#### Parameters

##### no

Negate a command or set its defaults

##### bs-power-control

BS (Downlink) power control parameters

##### ms-power-control

MS (Uplink) power control parameters

---

### 1.17.116 no access-control-class-ramping

#### Command

```
no access-control-class-ramping
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### no

Negate a command or set its defaults

#### access-control-class-ramping

Disable Access Control Class ramping

### 1.17.117 no depends-on-bts <0-255>

#### Command

```
no depends-on-bts <0-255>
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### no

Negate a command or set its defaults

#### depends-on-bts

This BTS can only be started if another one is up

#### <0-255>

BTS Number

### 1.17.118 no description

#### Command

```
no description
```

#### Parameters

#### no

Negate a command or set its defaults

#### description

Remove description of the object

---

### 1.17.119 no dtx downlink

#### Command

```
no dtx downlink
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### no

Negate a command or set its defaults

##### dtx

Configure discontinuous transmission

##### downlink

Disable Downlink DTX for this BTS

### 1.17.120 no dtx uplink

#### Command

```
no dtx uplink
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### no

Negate a command or set its defaults

##### dtx

Configure discontinuous transmission

##### uplink

Disable Uplink DTX for this BTS

### 1.17.121 no force-combined-si

#### Command

```
no force-combined-si
```

#### Application specific attributes

#### Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

#### no

Negate a command or set its defaults

#### force-combined-si

Force the generation of a single SI (no ter/bis)

### 1.17.122 no gprs control-ack-type-rach

#### Command

```
no gprs control-ack-type-rach
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### no

Negate a command or set its defaults

#### gprs

GPRS Packet Network

#### control-ack-type-rach

Set GPRS Control Ack Type for PACKET CONTROL ACKNOWLEDGMENT message to default RLC/MAC control block

---

### 1.17.123 no gprs egprs-packet-channel-request

#### Command

```
no gprs egprs-packet-channel-request
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### no

Negate a command or set its defaults

#### gprs

GPRS Packet Network

#### egprs-packet-channel-request

EGPRS Packet Channel Request support

### 1.17.124 no neighbor arfcn <0-1023> bsic (<0-63>|any)

#### Command

```
no neighbor arfcn <0-1023> bsic (<0-63>|any)
```

#### Parameters

#### no

Negate a command or set its defaults

#### neighbor

Remove local or remote-BSS neighbor cell

#### arfcn

ARFCN of neighbor cell

#### <0-1023>

ARFCN value

#### bsic

BSIC of neighbor cell

#### <0-63>

BSIC value

#### any

for all BSICs / use any BSIC in this ARFCN

### 1.17.125 no neighbor bts <0-255>

#### Command

```
no neighbor bts <0-255>
```

#### Parameters

no

Negate a command or set its defaults

neighbor

Remove local or remote-BSS neighbor cell

bts

Neighbor cell by local BTS number

<0-255>

BTS number

### 1.17.126 no neighbors

#### Command

```
no neighbors
```

#### Parameters

no

Negate a command or set its defaults

neighbors

Remove all local and remote-BSS neighbor config for this cell. Note that this falls back to the legacy behavior of regarding all local cells as neighbors.

### 1.17.127 no repeat (ul-sacch|dl-sacch)

#### Command

```
no repeat (ul-sacch|dl-sacch)
```

#### Application specific attributes

Flag: 1

This command applies for newly created lchans

#### Parameters

no

Negate a command or set its defaults

---

repeat

FACCH/SACCH repetition

ul-sacch

Disable UL-SACCH repetition for this BTS

dl-sacch

Disable DL-SACCH repetition for this BTS

### 1.17.128 no repeat dl-facch

Command

```
no repeat dl-facch
```

Application specific attributes

Flag: !

This command applies for newly created lchans

Parameters

no

Negate a command or set its defaults

repeat

FACCH/SACCH repetition

dl-facch

Disable DL-FACCH repetition for this BTS

### 1.17.129 no rf-lock-exclude

Command

```
no rf-lock-exclude
```

Global attributes

Flag: !

This command applies immediately

Parameters

no

Negate a command or set its defaults

rf-lock-exclude

Exclude this BTS from the global RF Lock

### 1.17.130 no system-information unused-send-empty

#### Command

```
no system-information unused-send-empty
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### no

Negate a command or set its defaults

#### system-information

System Information Messages

#### unused-send-empty

Avoid sending BCCH Info with empty 'Full BCCH Info' TLV to notify disabled SI. Some nanoBTS fw versions are known to fail upon receipt of these messages.

### 1.17.131 no timer-dynamic TNNNN

#### Command

```
no timer-dynamic TNNNN
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### no

Negate a command or set its defaults

#### timer-dynamic

Set given timer to non-dynamic and use the default or user provided fixed value

#### TNNNN

T-number, optionally preceded by 't' or 'T'



### 1.17.132 nokia\_site bts-reset-timer <15-100>

#### Command

```
nokia_site bts-reset-timer <15-100>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

nokia\_site

Nokia \*Site related commands

bts-reset-timer

The amount of time (in sec.) between BTS\_RESET is sent,

<15-100>

and the BTS is being bootstrapped.

### 1.17.133 nokia\_site no-local-rel-conf (0|1)

#### Command

```
nokia_site no-local-rel-conf (0|1)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

nokia\_site

Nokia \*Site related commands

no-local-rel-conf

Do not wait for RELease CONFirm message when releasing channel locally

0

Wait for RELease CONFirm

1

Do not wait for RELease CONFirm

---

### 1.17.134 nokia\_site skip-reset (0|1)

#### Command

```
nokia_site skip-reset (0|1)
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

nokia\_site

Nokia \*Site related commands

skip-reset

Skip the reset step during bootstrap process of this BTS

0

Do NOT skip the reset

1

Skip the reset

### 1.17.135 om2000 version-limit (oml|rsl) gen <0-99> rev <0-99>

#### Command

```
om2000 version-limit (oml|rsl) gen <0-99> rev <0-99>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

om2000

Configure OM2K specific parameters

version-limit

Configure optional maximum protocol version to negotiate

oml

Limit OML IWD version

rsl

Limit RSL IWD version

gen

Generation limit

<0-99>

Generation number to limit to (inclusive)

rev

Revision limit

<0-99>

Revision number to limit to (inclusive)

### 1.17.136 oml e1 line E1\_LINE timeslot <1-31> sub-slot (0|1|2|3|full)

Command

```
oml e1 line E1_LINE timeslot <1-31> sub-slot (0|1|2|3|full)
```

Parameters

oml

Organization & Maintenance Link

e1

OML E1/T1 Configuration

line

E1/T1 line number to be used for OML

E1\_LINE

E1/T1 line number to be used for OML

timeslot

E1/T1 timeslot to be used for OML

<1-31>

E1/T1 timeslot to be used for OML

sub-slot

E1/T1 sub-slot to be used for OML

0

Use E1/T1 sub-slot 0

1

Use E1/T1 sub-slot 1

2

Use E1/T1 sub-slot 2

3

Use E1/T1 sub-slot 3

full

Use full E1 slot 3

### 1.17.137 oml e1 tei <0-63>

#### Command

```
oml e1 tei <0-63>
```

#### Application specific attributes

##### Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

##### oml

Organization & Maintenance Link

##### e1

OML E1/T1 Configuration

##### tei

Set the TEI to be used for OML

##### <0-63>

TEI Number

### 1.17.138 oml ipa stream-id <0-255> line E1\_LINE

#### Command

```
oml ipa stream-id <0-255> line E1_LINE
```

#### Application specific attributes

##### Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

##### oml

Organization & Maintenance Link

##### ipa

A-bis/IP Specific Options

##### stream-id

Set the ipa Stream ID of the OML link of this BTS

##### <0-255>

Stream Identifier

##### line

Virtual E1 Line Number

##### E1\_LINE

Virtual E1 Line Number

### 1.17.139 paging free <-1-1024>

#### Command

```
paging free <-1-1024>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

paging

Paging options

free

Only page when having a certain amount of free slots

<-1-1024>

amount of required free paging slots. -1 to disable

### 1.17.140 pcu-socket PATH

#### Command

```
pcu-socket PATH
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

pcu-socket

PCU Socket Path for using OsmoPCU co-located with BSC (legacy BTS)

PATH

Path in the file system for the unix-domain PCU socket

### 1.17.141 penalty time <20-620>

#### Command

```
penalty time <20-620>
```

#### Application specific attributes

---

Flag: r

This command applies on A-bis RSL link (re)establishment

Parameters

penalty

Cell selection penalty time

time

Cell selection penalty time

<20-620>

Cell selection penalty time in seconds (by 20s increments)

### 1.17.142 penalty time reserved

Command

```
penalty time reserved
```

Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

Parameters

penalty

Cell selection penalty time

time

Cell selection penalty time

reserved

Set cell selection penalty time to reserved value 31, (indicate that CELL\_RESELECT\_OFFSET is subtracted from C2 and TEMPORARY\_OFFSET is ignored)

### 1.17.143 rach access-control-class (0|1|2|3|4|5|6|7|8|9|11|12|13|14|15) (barred|allowed)

Command

```
rach access-control-class (0|1|2|3|4|5|6|7|8|9|11|12|13|14|15) (barred|allowed)
```

Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

Parameters

---

rach

Random Access Control Channel

access-control-class

Set access control class

0

Access control class 0

1

Access control class 1

2

Access control class 2

3

Access control class 3

4

Access control class 4

5

Access control class 5

6

Access control class 6

7

Access control class 7

8

Access control class 8

9

Access control class 9

11

Access control class 11 for PLMN use

12

Access control class 12 for security services

13

Access control class 13 for public utilities (e.g. water/gas suppliers)

14

Access control class 14 for emergency services

15

Access control class 15 for PLMN staff

barred

barred to use access control class

allowed

allowed to use access control class

---

### 1.17.144 rach emergency call allowed (0|1)

#### Command

```
rach emergency call allowed (0|1)
```

#### Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

rach

Random Access Control Channel

emergency

Should this cell allow emergency calls?

call

Should this cell allow emergency calls?

allowed

Should this cell allow emergency calls?

0

Do NOT allow emergency calls

1

Allow emergency calls

### 1.17.145 rach max transmission (1|2|4|7)

#### Command

```
rach max transmission (1|2|4|7)
```

#### Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

rach

Random Access Control Channel

max

Set the maximum number of RACH burst transmissions

transmission

Set the maximum number of RACH burst transmissions



- 1  
Maximum number of 1 RACH burst transmissions
- 2  
Maximum number of 2 RACH burst transmissions
- 4  
Maximum number of 4 RACH burst transmissions
- 7  
Maximum number of 7 RACH burst transmissions

### 1.17.146 rach nm busy threshold <0-255>

#### Command

```
rach nm busy threshold <0-255>
```

#### Application specific attributes

##### Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

##### rach

Random Access Control Channel

##### nm

Network Management

##### busy

Set the NM Busy Threshold

##### threshold

Set the NM Busy Threshold

##### <0-255>

NM Busy Threshold in dB

### 1.17.147 rach nm load average <0-65535>

#### Command

```
rach nm load average <0-65535>
```

#### Application specific attributes

##### Flag: o

This command applies on A-bis OML link (re)establishment

## Parameters

rach

Random Access Control Channel

nm

Network Management

load

Set the NM Loadaverage Slots value

average

Set the NM Loadaverage Slots value

&lt;0-65535&gt;

NM Loadaverage Slots value

**1.17.148 rach tx integer <0-15>**

## Command

```
rach tx integer <0-15>
```

## Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

## Parameters

rach

Random Access Control Channel

tx

Set the raw tx integer value in RACH Control parameters IE

integer

Set the raw tx integer value in RACH Control parameters IE

&lt;0-15&gt;

Raw tx integer value in RACH Control parameters IE

**1.17.149 radio-link-timeout <4-64>**

## Command

```
radio-link-timeout <4-64>
```

## Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

##### radio-link-timeout

Radio link timeout criterion (BTS side)

<4-64>

Radio link timeout value (lost SACCH block)

### 1.17.150 radio-link-timeout infinite

#### Command

```
radio-link-timeout infinite
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

##### radio-link-timeout

Radio link timeout criterion (BTS side)

infinite

Infinite Radio link timeout value (use only for BTS RF testing)

### 1.17.151 repeat (ul-sacch|dl-sacch)

#### Command

```
repeat (ul-sacch|dl-sacch)
```

#### Application specific attributes

Flag: l

This command applies for newly created lchans

#### Parameters

##### repeat

FACCH/SACCH repetition

##### ul-sacch

Enable UL-SACCH repetition for this BTS

##### dl-sacch

Enable DL-SACCH repetition for this BTS

### 1.17.152 repeat dl-facch (command|all)

#### Command

```
repeat dl-facch (command|all)
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### repeat

FACCH/SACCH repetition

##### dl-facch

Enable DL-FACCH repetition for this BTS

##### command

command LAPDm frames only

##### all

all LAPDm frames

### 1.17.153 repeat rxqual (0|1|2|3|4|5|6|7)

#### Command

```
repeat rxqual (0|1|2|3|4|5|6|7)
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

##### repeat

FACCH/SACCH repetition

##### rxqual

Set UL-SACCH/DL-FACCH rxqual threshold-ber

##### 0

0 disabled (always on)

##### 1

1 BER >= 0.2%

##### 2

2 BER >= 0.4%

- 3
  - 3 BER >= 0.8%
- 4
  - 4 BER >= 1.6% (default)
- 5
  - 5 BER >= 3.2%
- 6
  - 6 BER >= 6.4%
- 7
  - 7 BER >= 12.8%

### 1.17.154 rf-lock-exclude

Command

```
rf-lock-exclude
```

Global attributes

Flag: !

This command applies immediately

Parameters

rf-lock-exclude

Exclude this BTS from the global RF Lock

### 1.17.155 rxlev access min <0-63>

Command

```
rxlev access min <0-63>
```

Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

Parameters

rxlev

Minimum RxLev needed for cell access

access

Minimum RxLev needed for cell access

min

Minimum RxLev needed for cell access

<0-63>

Minimum RxLev needed for cell access (better than -110dBm)

### 1.17.156 si2quater neighbor-list add earfcn <0-65535> thresh-hi <0-31> thresh-lo <0-32> p...

#### Command

```
si2quater neighbor-list add earfcn <0-65535> thresh-hi <0-31> thresh-lo <0-32> prio <0-8> qrxlv <0-32> meas <0-8>
```

#### Application specific attributes

##### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### si2quater

SI2quater Neighbor List

##### neighbor-list

SI2quater Neighbor List

##### add

Add to manual SI2quater neighbor list

##### earfcn

EARFCN of neighbor

##### <0-65535>

EARFCN of neighbor

##### thresh-hi

threshold high bits

##### <0-31>

threshold high bits

##### thresh-lo

threshold low bits

##### <0-32>

threshold low bits (32 means NA)

##### prio

priority

##### <0-8>

priority (8 means NA)

##### qrxlv

QRXLEVMIN

##### <0-32>

QRXLEVMIN (32 means NA)

##### meas

measurement bandwidth

##### <0-8>

measurement bandwidth (8 means NA)

### 1.17.157 si2quater neighbor-list add uarfcn <0-16383> <0-511> <0-1>

#### Command

```
si2quater neighbor-list add uarfcn <0-16383> <0-511> <0-1>
```

#### Application specific attributes

##### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### si2quater

SI2quater Neighbor List

##### neighbor-list

SI2quater Neighbor List

##### add

Add to manual SI2quater neighbor list

##### uarfcn

UARFCN of neighbor

##### <0-16383>

UARFCN of neighbor

##### <0-511>

scrambling code

##### <0-1>

diversity bit

### 1.17.158 si2quater neighbor-list del earfcn <0-65535>

#### Command

```
si2quater neighbor-list del earfcn <0-65535>
```

#### Application specific attributes

##### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

##### si2quater

SI2quater Neighbor List

##### neighbor-list

SI2quater Neighbor List

---

del

Delete from SI2quater manual neighbor list

earfcn

EARFCN of neighbor

<0-65535>

EARFCN

### 1.17.159 si2quater neighbor-list del uarfcn <0-16383> <0-511>

Command

```
si2quater neighbor-list del uarfcn <0-16383> <0-511>
```

Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

Parameters

si2quater

SI2quater Neighbor List

neighbor-list

SI2quater Neighbor List

del

Delete from SI2quater manual neighbor list

uarfcn

UARFCN of neighbor

<0-16383>

UARFCN

<0-511>

scrambling code

### 1.17.160 si5 neighbor-list (add|del) arfcn <0-1023>

Command

```
si5 neighbor-list (add|del) arfcn <0-1023>
```

Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment



## Parameters

si5

SI5 Neighbor List

neighbor-list

SI5 Neighbor List

add

Add to manual SI5 neighbor list

del

Delete from SI5 manual neighbor list

arfcn

ARFCN of neighbor

&lt;0-1023&gt;

ARFCN of neighbor

**1.17.161 system-information (1|2|3|4|5|6|7|8|9|10|13|16|17|18|19|20|2bis|2ter|2quater|5bi...**

## Command

```
system-information (1|2|3|4|5|6|7|8|9|10|13|16|17|18|19|20|2bis|2ter|2quater|5bis|5ter) ←
mode (static|computed)
```

## Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

## Parameters

system-information

System Information Messages

1

System Information Type 1

2

System Information Type 2

3

System Information Type 3

4

System Information Type 4

5

System Information Type 5

6

System Information Type 6

---

7	System Information Type 7
8	System Information Type 8
9	System Information Type 9
10	System Information Type 10
13	System Information Type 13
16	System Information Type 16
17	System Information Type 17
18	System Information Type 18
19	System Information Type 19
20	System Information Type 20
2bis	System Information Type 2bis
2ter	System Information Type 2ter
2quater	System Information Type 2quater
5bis	System Information Type 5bis
5ter	System Information Type 5ter
mode	System Information Mode
static	Static user-specified
computed	Dynamic, BSC-computed

---

## 1.17.162 system-information (1|2|3|4|5|6|7|8|9|10|13|16|17|18|19|20|2bis|2ter|2quater|5bi...

### Command

```
system-information (1|2|3|4|5|6|7|8|9|10|13|16|17|18|19|20|2bis|2ter|2quater|5bis|5ter) ↔  
static HEXSTRING
```

### Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

### Parameters

system-information

System Information Messages

1

System Information Type 1

2

System Information Type 2

3

System Information Type 3

4

System Information Type 4

5

System Information Type 5

6

System Information Type 6

7

System Information Type 7

8

System Information Type 8

9

System Information Type 9

10

System Information Type 10

13

System Information Type 13

16

System Information Type 16

17

System Information Type 17

18  
    System Information Type 18

19  
    System Information Type 19

20  
    System Information Type 20

2bis  
    System Information Type 2bis

2ter  
    System Information Type 2ter

2quater  
    System Information Type 2quater

5bis  
    System Information Type 5bis

5ter  
    System Information Type 5ter

static  
    Static System Information filling

HEXSTRING  
    Static user-specified SI content in HEX notation

### 1.17.163 system-information unused-send-empty

Command

```
system-information unused-send-empty
```

Application specific attributes

Flag: r

This command applies on A-bis RSL link (re)establishment

Parameters

system-information

System Information Messages

unused-send-empty

Send BCCH Info with empty 'Full BCCH Info' TLV to notify disabled SI. Some nanoBTS fw versions are known to fail upon receival of these messages.

### 1.17.164 temporary offset <0-60>

#### Command

```
temporary offset <0-60>
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### temporary

Cell selection temporary negative offset

#### offset

Cell selection temporary negative offset

#### <0-60>

Cell selection temporary negative offset in dB

### 1.17.165 temporary offset infinite

#### Command

```
temporary offset infinite
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### temporary

Cell selection temporary negative offset

#### offset

Cell selection temporary negative offset

#### infinite

Sets cell selection temporary negative offset to infinity

### 1.17.166 timer-dynamic TNNNN

#### Command

```
timer-dynamic TNNNN
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

timer-dynamic

Calculate T3113 dynamically based on channel config and load

TNNNN

T-number, optionally preceded by 't' or 'T'

### 1.17.167 trx <0-255>

#### Command

```
trx <0-255>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

trx

Radio Transceiver

<0-255>

Select a TRX to configure

### 1.17.168 type (unknown|bs11|nanobts|rbs2000|nokia\_site|sysmobts)

#### Command

```
type (unknown|bs11|nanobts|rbs2000|nokia_site|sysmobts)
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

## Parameters

### type

BTS Vendor/Type

### unknown

Unknown BTS Type

### bs11

Siemens BTS (BS-11 or compatible)

### nanobts

ip.access nanoBTS or compatible

### rbs2000

Ericsson RBS2000 Series

### nokia\_site

Nokia {Metro,Ultra,In}Site

### sysmobts

sysmocom sysmoBTS

## 1.18 config-net-bts-trx

### 1.18.1 arfcn <0-1023>

#### Command

```
arfcn <0-1023>
```

#### Application specific attributes

#### Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

##### arfcn

Set the ARFCN for this TRX

##### <0-1023>

Absolute Radio Frequency Channel Number

### 1.18.2 description .TEXT

#### Command

```
description .TEXT
```

#### Parameters

##### description

Save human-readable description of the object

##### .TEXT

Text until the end of the line

---

### 1.18.3 max\_power\_red <0-100>

#### Command

```
max_power_red <0-100>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

max\_power\_red

Reduction of maximum BS RF Power (relative to nominal power)

<0-100>

Reduction of maximum BS RF Power in dB

### 1.18.4 no description

#### Command

```
no description
```

#### Parameters

no

Negate a command or set its defaults

description

Remove description of the object

### 1.18.5 nominal power <-20-100>

#### Command

```
nominal power <-20-100>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

nominal

Nominal TRX RF Power in dBm

power

Nominal TRX RF Power in dBm

<-20-100>

Nominal TRX RF Power in dBm

---



### 1.18.6 rf\_locked (0|1)

#### Command

```
rf_locked (0|1)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

##### rf\_locked

Set or unset the RF Locking (Turn off RF of the TRX)

0

TRX is NOT RF locked (active)

1

TRX is RF locked (turned off)

### 1.18.7 rsl e1 line E1\_LINE timeslot <1-31> sub-slot (0|1|2|3|full)

#### Command

```
rsl e1 line E1_LINE timeslot <1-31> sub-slot (0|1|2|3|full)
```

#### Parameters

##### rsl

RSL Parameters

##### e1

E1/T1 interface to be used for RSL

##### line

E1/T1 interface to be used for RSL

##### E1\_LINE

E1/T1 Line Number to be used for RSL

##### timeslot

E1/T1 Timeslot to be used for RSL

##### <1-31>

E1/T1 Timeslot to be used for RSL

##### sub-slot

E1/T1 Sub-slot to be used for RSL

0

E1/T1 Sub-slot 0 is to be used for RSL

- 1  
E1/T1 Sub-slot 1 is to be used for RSL
- 2  
E1/T1 Sub-slot 2 is to be used for RSL
- 3  
E1/T1 Sub-slot 3 is to be used for RSL
- full  
E1/T1 full timeslot is to be used for RSL

### 1.18.8 rsl e1 tei <0-63>

#### Command

```
rsl e1 tei <0-63>
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### rsl

RSL Parameters

#### e1

Set the TEI to be used for RSL

#### tei

Set the TEI to be used for RSL

#### <0-63>

TEI to be used for RSL

### 1.18.9 timeslot <0-7>

#### Command

```
timeslot <0-7>
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### timeslot

Select a Timeslot to configure

#### <0-7>

Timeslot number

## 1.19 config-net-bts-trx-ts

### 1.19.1 e1 line E1\_LINE timeslot <1-31> sub-slot (0|1|2|3|full)

#### Command

```
e1 line E1_LINE timeslot <1-31> sub-slot (0|1|2|3|full)
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

e1

E1/T1 channel connected to this on-air timeslot

line

E1/T1 channel connected to this on-air timeslot

E1\_LINE

E1/T1 line connected to this on-air timeslot

timeslot

E1/T1 timeslot connected to this on-air timeslot

<1-31>

E1/T1 timeslot connected to this on-air timeslot

sub-slot

E1/T1 sub-slot connected to this on-air timeslot

0

E1/T1 sub-slot 0 connected to this on-air timeslot

1

E1/T1 sub-slot 1 connected to this on-air timeslot

2

E1/T1 sub-slot 2 connected to this on-air timeslot

3

E1/T1 sub-slot 3 connected to this on-air timeslot

full

Full E1/T1 timeslot connected to this on-air timeslot

### 1.19.2 hopping arfcn add <0-1023>

#### Command

```
hopping arfcn add <0-1023>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

hopping

Configure frequency hopping

arfcn

Configure hopping ARFCN list

add

Add an entry to the hopping ARFCN list

<0-1023>

ARFCN

### 1.19.3 hopping arfcn del <0-1023>

#### Command

```
hopping arfcn del <0-1023>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

hopping

Configure frequency hopping

arfcn

Configure hopping ARFCN list

del

Delete an entry to the hopping ARFCN list

<0-1023>

ARFCN

### 1.19.4 hopping arfcn del-all

#### Command

```
hopping arfcn del-all
```

#### Application specific attributes

##### Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

##### hopping

Configure frequency hopping

##### arfcn

Configure hopping ARFCN list

##### del-all

Delete all previously configured entries

### 1.19.5 hopping enabled (0|1)

#### Command

```
hopping enabled (0|1)
```

#### Application specific attributes

##### Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

##### hopping

Configure frequency hopping

##### enabled

Enable or disable frequency hopping

##### 0

Disable frequency hopping

##### 1

Enable frequency hopping

---

### 1.19.6 hopping maio <0-63>

#### Command

```
hopping maio <0-63>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

hopping

Configure frequency hopping

maio

Which hopping MAIO to use for this channel

<0-63>

Mobile Allocation Index Offset (MAIO)

### 1.19.7 hopping sequence-number <0-63>

#### Command

```
hopping sequence-number <0-63>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

hopping

Configure frequency hopping

sequence-number

Which hopping sequence to use for this channel

<0-63>

Hopping Sequence Number (HSN)

### 1.19.8 phys\_chan\_config (none|ccch|ccch+sdccch4|tch/f|tch/h|sdccch8|pdch|tch/f\_pdch|unkno...

#### Command

```
phys_chan_config (none|ccch|ccch+sdccch4|tch/f|tch/h|sdccch8|pdch|tch/f_pdch|unknown|ccch ↔
+sdccch4+cbch|sdccch8+cbch|tch/f_tch/h_pdch)
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

##### phys\_chan\_config

Physical Channel Combination

none

Physical Channel not configured

ccch

FCCH + SCH + BCCH + CCCH (Comb. IV)

ccch+sdccch4

FCCH + SCH + BCCH + CCCH + 4 SDCCH + 2 SACCH (Comb. V)

tch/f

TCH/F + FACCH/F + SACCH (Comb. I)

tch/h

2 TCH/H + 2 FACCH/H + 2 SACCH (Comb. II)

sdccch8

8 SDCCH + 4 SACCH (Comb. VII)

pdch

Packet Data Channel for GPRS/EDGE

tch/f\_pdch

Dynamic TCH/F or GPRS PDCH

unknown

Unknown / Unsupported channel combination

ccch+sdccch4+cbch

FCCH + SCH + BCCH + CCCH + CBCH + 3 SDCCH + 2 SACCH (Comb. V)

sdccch8+cbch

7 SDCCH + 4 SACCH + CBCH (Comb. VII)

tch/f\_tch/h\_pdch

Dynamic TCH/F or TCH/H or GPRS PDCH

### 1.19.9 training\_sequence\_code <0-7>

#### Command

```
training_sequence_code <0-7>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

training\_sequence\_code

Training Sequence Code of the Timeslot

<0-7>

TSC

## 1.20 oml

### 1.20.1 change-adm-state (locked|unlocked|shutdown|null)

#### Command

```
change-adm-state (locked|unlocked|shutdown|null)
```

#### Parameters

change-adm-state

Change the Administrative State

locked

Locked

unlocked

Unlocked

shutdown

Shutdown

null

NULL

### 1.20.2 opstart

#### Command

```
opstart
```

#### Parameters

opstart

Send an OPSTART message to the object

---



## 1.21 config-msc

This node allows to configure the MSC connection related settings.

### 1.21.1 allow-attach

Command

```
allow-attach
```

Global attributes

Flag: !

This command applies immediately

Parameters

allow-attach

Allow this MSC to attach new subscribers (default).

### 1.21.2 allow-emergency (allow|deny)

Command

```
allow-emergency (allow|deny)
```

Global attributes

Flag: !

This command applies immediately

Parameters

allow-emergency

Allow CM ServiceRequests with type emergency

allow

Allow

deny

Deny

### 1.21.3 amr-config 10\_2k (allowed|forbidden)

#### Command

```
amr-config 10_2k (allowed|forbidden)
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### amr-config

AMR Multirate Configuration

#### 10\_2k

Bitrate

#### allowed

Allowed

#### forbidden

Forbidden

### 1.21.4 amr-config 12\_2k (allowed|forbidden)

#### Command

```
amr-config 12_2k (allowed|forbidden)
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### amr-config

AMR Multirate Configuration

#### 12\_2k

Bitrate

#### allowed

Allowed

#### forbidden

Forbidden

### 1.21.5 amr-config 4\_75k (allowed|forbidden)

#### Command

```
amr-config 4_75k (allowed|forbidden)
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### amr-config

AMR Multirate Configuration

#### 4\_75k

Bitrate

#### allowed

Allowed

#### forbidden

Forbidden

### 1.21.6 amr-config 5\_15k (allowed|forbidden)

#### Command

```
amr-config 5_15k (allowed|forbidden)
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### amr-config

AMR Multirate Configuration

#### 5\_15k

Bitrate

#### allowed

Allowed

#### forbidden

Forbidden

### 1.21.7 amr-config 5\_90k (allowed|forbidden)

#### Command

```
amr-config 5_90k (allowed|forbidden)
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### amr-config

AMR Multirate Configuration

#### 5\_90k

Bitrate

#### allowed

Allowed

#### forbidden

Forbidden

### 1.21.8 amr-config 6\_70k (allowed|forbidden)

#### Command

```
amr-config 6_70k (allowed|forbidden)
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### amr-config

AMR Multirate Configuration

#### 6\_70k

Bitrate

#### allowed

Allowed

#### forbidden

Forbidden

### 1.21.9 amr-config 7\_40k (allowed|forbidden)

#### Command

```
amr-config 7_40k (allowed|forbidden)
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### amr-config

AMR Multirate Configuration

#### 7\_40k

Bitrate

#### allowed

Allowed

#### forbidden

Forbidden

### 1.21.10 amr-config 7\_95k (allowed|forbidden)

#### Command

```
amr-config 7_95k (allowed|forbidden)
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### amr-config

AMR Multirate Configuration

#### 7\_95k

Bitrate

#### allowed

Allowed

#### forbidden

Forbidden

### 1.21.11 amr-payload (octet-aligned|bandwith-efficient

#### Command

```
amr-payload (octet-aligned|bandwith-efficient
```

#### Application specific attributes

#### Flag: 1

This command applies for newly created lchans

#### Parameters

#### amr-payload

Set AMR payload framing mode

#### octet-aligned

payload fields aligned on octet boundaries

#### bandwith-efficient

payload fields packed (AoIP)

### 1.21.12 asp-protocol (m3ua|sua|ipa)

#### Command

```
asp-protocol (m3ua|sua|ipa)
```

#### Parameters

#### asp-protocol

A interface protocol to use for this MSC)

#### m3ua

MTP3 User Adaptation

#### sua

SCCP User Adaptation

#### ipa

IPA Multiplex (SCCP Lite)

### 1.21.13 bsc-addr NAME

#### Command

```
bsc-addr NAME
```

#### Parameters

#### bsc-addr

Calling Address (local address of this BSC)

#### NAME

SCCP address name

---

### 1.21.14 codec-list .LIST

#### Command

```
codec-list .LIST
```

#### Application specific attributes

#### Flag: r

This command applies on A-bis RSL link (re)establishment

#### Parameters

#### codec-list

Set the allowed audio codecs

#### .LIST

List of audio codecs, e.g. fr3 fr1 hr3

### 1.21.15 core-mobile-country-code <1-999>

#### Command

```
core-mobile-country-code <1-999>
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### core-mobile-country-code

Use this country code for the core network

#### <1-999>

MCC value

### 1.21.16 core-mobile-network-code <1-999>

#### Command

```
core-mobile-network-code <1-999>
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

#### core-mobile-network-code

Use this network code for the core network

#### <1-999>

MNC value

---

### 1.21.17 lcls-codec-mismatch (allowed|forbidden)

#### Command

```
lcls-codec-mismatch (allowed|forbidden)
```

#### Application specific attributes

#### Flag: 1

This command applies for newly created lchans

#### Parameters

##### lcls-codec-mismatch

Allow 3GPP LCLS (Local Call, Local Switch) when call legs use different codec/rate

##### allowed

Allow LCLS only for calls that use the same codec/rate on both legs

##### forbidden

Do not Allow LCLS for calls that use a different codec/rate on both legs

### 1.21.18 lcls-mode (disabled|mgw-loop|bts-loop)

#### Command

```
lcls-mode (disabled|mgw-loop|bts-loop)
```

#### Application specific attributes

#### Flag: 1

This command applies for newly created lchans

#### Parameters

##### lcls-mode

Configure 3GPP LCLS (Local Call, Local Switch)

##### disabled

Disable LCLS for all calls of this MSC

##### mgw-loop

Enable LCLS with looping traffic in MGW

##### bts-loop

Enable LCLS with looping traffic between BTS



### 1.21.19 mgw endpoint-domain NAME

#### Command

```
mgw endpoint-domain NAME
```

#### Parameters

mgw

Configure MGCP connection to Media Gateway

endpoint-domain

Set the domain name to send in MGCP messages, e.g. the part 'foo' in 'rtpbridge/\*@foo'.

NAME

Domain name, should be alphanumeric.

### 1.21.20 mgw local-ip (A.B.C.D|X:X::X:X)

#### Command

```
mgw local-ip (A.B.C.D|X:X::X:X)
```

#### Parameters

mgw

Configure MGCP connection to Media Gateway

local-ip

local bind to connect to MGW from

A.B.C.D

local bind IPv4 address

X:X::X:X

local bind IPv6 address

### 1.21.21 mgw local-port <0-65535>

#### Command

```
mgw local-port <0-65535>
```

#### Parameters

mgw

Configure MGCP connection to Media Gateway

local-port

local port to connect to MGW from

<0-65535>

local bind port

---

### 1.21.22 mgw remote-ip (A.B.C.D|X:X::X:X)

#### Command

```
mgw remote-ip (A.B.C.D|X:X::X:X)
```

#### Parameters

##### mgw

Configure MGCP connection to Media Gateway

##### remote-ip

remote IP address to reach the MGW at

##### A.B.C.D

remote IPv4 address

##### X:X::X:X

remote IPv6 address

### 1.21.23 mgw remote-port <0-65535>

#### Command

```
mgw remote-port <0-65535>
```

#### Parameters

##### mgw

Configure MGCP connection to Media Gateway

##### remote-port

remote port to reach the MGW at

##### <0-65535>

remote port

### 1.21.24 mgw x-osmo-ign call-id

#### Command

```
mgw x-osmo-ign call-id
```

#### Application specific attributes

##### Flag: 1

This command applies for newly created lchans

#### Parameters

---

mgw

Configure MGCP connection to Media Gateway

x-osmo-ign

Set a (non-standard) X-Osmo-IGN header in all CRCX messages for RTP streams associated with this MSC, useful for A/SCCP lite MSCs, since osmo-bsc cannot know the MSC's chosen CallID. This is enabled by default for A/SCCP lite connections, disabled by default for all others.

call-id

Send 'X-Osmo-IGN: C' to ignore CallID mismatches. See OsmoMGW.

### 1.21.25 msc-addr NAME

Command

```
msc-addr NAME
```

Parameters

msc-addr

Called Address (remote address of the MSC)

NAME

SCCP address name

### 1.21.26 no allow-attach

Command

```
no allow-attach
```

Global attributes

Flag: !

This command applies immediately

Parameters

no

Negate a command or set its defaults

allow-attach

Do not assign new subscribers to this MSC. Useful if an MSC in an MSC pool is configured to off-load subscribers. The MSC will still be operational for already IMSI-Attached subscribers, but the NAS node selection function will skip this MSC for new subscribers

### 1.21.27 no mgw x-osmo-ign

#### Command

```
no mgw x-osmo-ign
```

#### Application specific attributes

#### Flag: !

This command applies for newly created lchans

#### Parameters

##### no

Negate a command or set its defaults

##### mgw

Configure MGCP connection to Media Gateway

##### x-osmo-ign

Do not send X-Osmo-IGN MGCP header to this MSC

### 1.21.28 nri add <0-32767> [<0-32767>]

#### Command

```
nri add <0-32767> [<0-32767>]
```

#### Global attributes

#### Flag: !

This command applies immediately

#### Parameters

##### nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

##### add

Add NRI value or range to the NRI mapping for this MSC

##### <0-32767>

First value of the NRI value range, should not surpass the configured 'nri bitlen'.

##### [<0-32767>]

Last value of the NRI value range, should not surpass the configured 'nri bitlen' and be larger than the first value; if omitted, apply only the first value.

### 1.21.29 nri del <0-32767> [<0-32767>]

#### Command

```
nri del <0-32767> [<0-32767>]
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

del

Remove NRI value or range from the NRI mapping for this MSC

<0-32767>

First value of the NRI value range, should not surpass the configured 'nri bitlen'.

[<0-32767>]

Last value of the NRI value range, should not surpass the configured 'nri bitlen' and be larger than the first value; if omitted, apply only the first value.

### 1.21.30 osmux (on|off|only)

#### Command

```
osmux (on|off|only)
```

#### Application specific attributes

Flag: l

This command applies for newly created lchans

#### Parameters

osmux

RTP multiplexing

on

Enable OSMUX

off

Disable OSMUX

only

Only use OSMUX

---

### 1.21.31 show nri

#### Command

```
show nri
```

#### Parameters

##### show

Show running system information

##### nri

Mapping of Network Resource Indicators to this MSC, for MSC pooling

## 1.22 om2k

### 1.22.1 arbitrary <0-65535> [HEXSTRING]

#### Command

```
arbitrary <0-65535> [HEXSTRING]
```

#### Parameters

##### arbitrary

Send arbitrary OM2k message

##### <0-65535>

Command identifier

##### [HEXSTRING]

Hex Encoded payload

### 1.22.2 capabilities-request

#### Command

```
capabilities-request
```

#### Parameters

##### capabilities-request

Request MO capabilities

### 1.22.3 configuration-request

#### Command

```
configuration-request
```

#### Parameters

configuration-request

Send the configuration request for current MO

### 1.22.4 connect-command

#### Command

```
connect-command
```

#### Parameters

connect-command

Connect the MO

### 1.22.5 disable-request

#### Command

```
disable-request
```

#### Parameters

disable-request

Disable the MO

### 1.22.6 disconnect-command

#### Command

```
disconnect-command
```

#### Parameters

disconnect-command

Disconnect the MO

---

### 1.22.7 enable-request

#### Command

```
enable-request
```

#### Parameters

enable-request

Enable the MO

### 1.22.8 operational-info <0-1>

#### Command

```
operational-info <0-1>
```

#### Parameters

operational-info

Set operational information

<0-1>

Set operational info to 0 or 1

### 1.22.9 reset-command

#### Command

```
reset-command
```

#### Parameters

reset-command

Reset the MO

### 1.22.10 start-request

#### Command

```
start-request
```

#### Parameters

start-request

Start the MO

---



### 1.22.11 status-request

#### Command

```
status-request
```

#### Parameters

status-request

Get the MO Status

### 1.22.12 test-request

#### Command

```
test-request
```

#### Parameters

test-request

Test the MO

## 1.23 om2k-con-group

### 1.23.1 con-path (add|del) <0-2047> <0-255> concentrated <1-16>

#### Command

```
con-path (add|del) <0-2047> <0-255> concentrated <1-16>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

con-path

CON Path (In/Out)

add

Add CON Path to Concentration Group

del

Delete CON Path from Concentration Group

<0-2047>

CON Connection Point

<0-255>

Contiguity Index

concentrated

Concentrated in/outlet

<1-16>

Tag Number

---

### 1.23.2 con-path (add|del) <0-2047> <0-255> deconcentrated <0-63>

#### Command

```
con-path (add|del) <0-2047> <0-255> deconcentrated <0-63>
```

#### Application specific attributes

Flag: o

This command applies on A-bis OML link (re)establishment

#### Parameters

con-path

CON Path (In/Out)

add

Add CON Path to Concentration Group

del

Delete CON Path from Concentration Group

<0-2047>

CON Connection Point

<0-255>

Contiguity Index

deconcentrated

De-concentrated in/outlet

<0-63>

TEI Value

## 1.24 config-bsc

This node allows to configure the BSC connection related settings.

### 1.24.1 bsc-auto-rf-off <1-65000>

#### Command

```
bsc-auto-rf-off <1-65000>
```

#### Global attributes

Flag: !

This command applies immediately

#### Parameters

bsc-auto-rf-off

Disable RF on MSC Connection

<1-65000>

Timeout

### 1.24.2 bsc-rf-socket PATH

#### Command

```
bsc-rf-socket PATH
```

#### Parameters

##### bsc-rf-socket

Set the filename for the RF control interface.

##### PATH

RF Control path

### 1.24.3 mid-call-timeout NR

#### Command

```
mid-call-timeout NR
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### mid-call-timeout

Switch from Grace to Off in NR seconds.

##### NR

Timeout in seconds

### 1.24.4 no bsc-auto-rf-off

#### Command

```
no bsc-auto-rf-off
```

#### Global attributes

##### Flag: !

This command applies immediately

#### Parameters

##### no

Negate a command or set its defaults

##### bsc-auto-rf-off

Disable RF on MSC Connection

---

## 1.25 config-cbc

### 1.25.1 client

Command

```
client
```

Parameters

client

Configure OsmoBSC's CBSP client role

### 1.25.2 mode (server|client|disabled)

Command

```
mode (server|client|disabled)
```

Parameters

mode

Set OsmoBSC as CBSP server or client

server

CBSP Server: listen for inbound TCP connections from a remote Cell Broadcast Centre

client

CBSP Client: establish outbound TCP connection to a remote Cell Broadcast Centre

disabled

Disable CBSP link

### 1.25.3 server

Command

```
server
```

Parameters

server

Configure OsmoBSC's CBSP server role

## 1.26 config-cbc-server

### 1.26.1 local-ip (A.B.C.D|X:X::X:X)

#### Command

```
local-ip (A.B.C.D|X:X::X:X)
```

#### Parameters

##### local-ip

Set IP Address to listen on for inbound CBSP from a Cell Broadcast Centre

##### A.B.C.D

IPv4 address

##### X:X::X:X

IPv6 address

### 1.26.2 local-port <1-65535>

#### Command

```
local-port <1-65535>
```

#### Parameters

##### local-port

Set TCP port to listen on for inbound CBSP from a Cell Broadcast Centre

##### <1-65535>

CBSP port number (Default: 48049)

## 1.27 config-cbc-client

### 1.27.1 local-ip (A.B.C.D|X:X::X:X)

#### Command

```
local-ip (A.B.C.D|X:X::X:X)
```

#### Parameters

##### local-ip

Set local bind address for the outbound CBSP link to the Cell Broadcast Centre

##### A.B.C.D

IPv4 address

##### X:X::X:X

IPv6 address

### 1.27.2 local-port <1-65535>

#### Command

```
local-port <1-65535>
```

#### Parameters

##### local-port

Set local bind port for the outbound CBSP link to the Cell Broadcast Centre

##### <1-65535>

port number

### 1.27.3 no local-ip

#### Command

```
no local-ip
```

#### Parameters

##### no

Negate a command or set its defaults

##### local-ip

Remove local IP address bind config for the CBSP client mode

### 1.27.4 no local-port

#### Command

```
no local-port
```

#### Parameters

##### no

Negate a command or set its defaults

##### local-port

Remove local TCP port bind config for the CBSP client mode

---

### 1.27.5 remote-ip (A.B.C.D|X:X::X:X)

#### Command

```
remote-ip (A.B.C.D|X:X::X:X)
```

#### Parameters

##### remote-ip

Set IP Address of the Cell Broadcast Centre, to establish CBSP link to

##### A.B.C.D

IPv4 address

##### X:X::X:X

IPv6 address

### 1.27.6 remote-port <1-65535>

#### Command

```
remote-port <1-65535>
```

#### Parameters

##### remote-port

Set TCP port of the Cell Broadcast Centre, to establish CBSP link to

##### <1-65535>

CBSP port number (Default: 48049)

## 1.28 config-power-ctrl

### 1.28.1 (rxlev-avg|rxqual-avg) algo (unweighted|weighted|mod-median)

#### Command

```
(rxlev-avg|rxqual-avg) algo (unweighted|weighted|mod-median)
```

#### Application specific attributes

##### Flag: l

This command applies for newly created lchans

##### Flag: v

This command/parameter is BTS vendor specific

#### Parameters

---

rxlev-avg

RxLev (signal strength) measurement averaging (for dynamic mode)

rxqual-avg

RxQual (signal quality) measurement averaging (for dynamic mode)

algo

Select the averaging algorithm

unweighted

Un-weighted average

weighted

Weighted average

mod-median

Modified median calculation

### 1.28.2 (rxlev-avg|rxqual-avg) algo osmo-ewma beta <1-99>

Command

```
(rxlev-avg|rxqual-avg) algo osmo-ewma beta <1-99>
```

Application specific attributes

Flag: l

This command applies for newly created lchans

Flag: v

This command/parameter is BTS vendor specific

Parameters

rxlev-avg

RxLev (signal strength) measurement averaging (for dynamic mode)

rxqual-avg

RxQual (signal quality) measurement averaging (for dynamic mode)

algo

Select the averaging algorithm

osmo-ewma

Exponentially Weighted Moving Average (EWMA)

beta

Smoothing factor (in %):  $\beta = (100 - \alpha)$

<1-99>

1% - lowest smoothing, 99% - highest smoothing



### 1.28.3 (rxlev-avg|rxqual-avg) params hreqave <1-31> hreqt <1-31>

#### Command

```
(rxlev-avg|rxqual-avg) params hreqave <1-31> hreqt <1-31>
```

#### Application specific attributes

##### Flag: l

This command applies for newly created lchans

##### Flag: v

This command/parameter is BTS vendor specific

#### Parameters

##### rxlev-avg

RxLev (signal strength) measurement averaging (for dynamic mode)

##### rxqual-avg

RxQual (signal quality) measurement averaging (for dynamic mode)

##### params

Configure general averaging parameters

##### hreqave

Hreqave: the period over which an average is produced

##### <1-31>

Hreqave value (so that Hreqave \* Hreqt < 32)

##### hreqt

Hreqt: the number of averaged results that are maintained

##### <1-31>

Hreqt value (so that Hreqave \* Hreqt < 32)

### 1.28.4 bs-power (static|dyn-max) <0-30>

#### Command

```
bs-power (static|dyn-max) <0-30>
```

#### Application specific attributes

##### Flag: l

This command applies for newly created lchans

#### Parameters

##### bs-power

BS Power IE value to be send to the BTS

---

static

Fixed BS Power reduction value (for static mode)

dyn-max

Maximum BS Power reduction value (for dynamic mode)

<0-30>

BS Power reduction value (in dB, even numbers only)

### 1.28.5 ctrl-interval <0-31>

Command

```
ctrl-interval <0-31>
```

Application specific attributes

Flag: l

This command applies for newly created lchans

Flag: v

This command/parameter is BTS vendor specific

Parameters

ctrl-interval

Set power control interval (for dynamic mode)

<0-31>

P\_CON\_INTERVAL, in units of 2 SACCH periods (0.96 seconds)

### 1.28.6 mode (static|dyn-bts) [reset]

Command

```
mode (static|dyn-bts) [reset]
```

Application specific attributes

Flag: l

This command applies for newly created lchans

Parameters

mode

Power control mode

static

Instruct the MS/BTS to use a static power level

dyn-bts

Power control to be performed dynamically by the BTS itself

[reset]

Reset to default parameters for the given mode

---

### 1.28.7 no (rxlev-avg|rxqual-avg)

#### Command

```
no (rxlev-avg|rxqual-avg)
```

#### Application specific attributes

##### Flag: l

This command applies for newly created lchans

##### Flag: v

This command/parameter is BTS vendor specific

#### Parameters

##### no

Negate a command or set its defaults

##### rxlev-avg

RxLev (signal strength) measurement averaging (for dynamic mode)

##### rxqual-avg

RxQual (signal quality) measurement averaging (for dynamic mode)

### 1.28.8 rxlev-thresh lower <0-63> upper <0-63>

#### Command

```
rxlev-thresh lower <0-63> upper <0-63>
```

#### Application specific attributes

##### Flag: l

This command applies for newly created lchans

##### Flag: v

This command/parameter is BTS vendor specific

#### Parameters

##### rxlev-thresh

Set target RxLev thresholds (for dynamic mode)

##### lower

Lower RxLev value (default is 32, i.e. -78 dBm)

##### <0-63>

Lower RxLev value (signal strength, 0 is worst, 63 is best)

##### upper

Upper RxLev value (default is 38, i.e. -72 dBm)

##### <0-63>

Upper RxLev value (signal strength, 0 is worst, 63 is best)

### 1.28.9 rxlev-thresh-comp lower <0-31> <0-31> upper <0-31> <0-31>

#### Command

```
rxlev-thresh-comp lower <0-31> <0-31> upper <0-31> <0-31>
```

#### Application specific attributes

##### Flag: l

This command applies for newly created lchans

##### Flag: v

This command/parameter is BTS vendor specific

#### Parameters

##### rxlev-thresh-comp

Set RxLev threshold comparators (for dynamic mode)

##### lower

Lower RxLev threshold comparators (see 3GPP TS 45.008, A.3.2.1)

##### <0-31>

P1 (default 10)

##### <0-31>

N1 (default 12)

##### upper

Upper RxLev threshold comparators (see 3GPP TS 45.008, A.3.2.1)

##### <0-31>

P2 (default 10)

##### <0-31>

N2 (default 12)

### 1.28.10 rxqual-thresh lower <0-7> upper <0-7>

#### Command

```
rxqual-thresh lower <0-7> upper <0-7>
```

#### Application specific attributes

##### Flag: l

This command applies for newly created lchans

##### Flag: v

This command/parameter is BTS vendor specific

#### Parameters

---

**rxqual-thresh**

Set target RxQual thresholds (for dynamic mode)

**lower**

Lower RxQual value (default is 3, i.e.  $0.8\% \leq \text{BER} < 1.6\%$ )

<0-7>

Lower RxQual value (signal quality, 0 is best, 7 is worst)

**upper**

Upper RxQual value (default is 0, i.e.  $\text{BER} < 0.2\%$ )

<0-7>

Upper RxQual value (signal quality, 0 is best, 7 is worst)

**1.28.11 rxqual-thresh-comp lower <0-31> <0-31> upper <0-31> <0-31>****Command**

```
rxqual-thresh-comp lower <0-31> <0-31> upper <0-31> <0-31>
```

**Application specific attributes****Flag: l**

This command applies for newly created lchans

**Flag: v**

This command/parameter is BTS vendor specific

**Parameters****rxqual-thresh-comp**

Set RxQual threshold comparators (for dynamic mode)

**lower**

Lower RxQual threshold comparators (see 3GPP TS 45.008, A.3.2.1)

<0-31>

P3 (default 5)

<0-31>

N3 (default 7)

**upper**

Upper RxQual threshold comparators (see 3GPP TS 45.008, A.3.2.1)

<0-31>

P4 (default 15)

<0-31>

N4 (default 18)

## 1.28.12 step-size inc <2-6> red <2-4>

### Command

```
step-size inc <2-6> red <2-4>
```

### Application specific attributes

#### Flag: l

This command applies for newly created lchans

#### Flag: v

This command/parameter is BTS vendor specific

### Parameters

#### step-size

Set power change step size (for dynamic mode)

#### inc

Increase step size (default is 4 dB)

#### <2-6>

Step size (2, 4, or 6 dB)

#### red

Reduce step size (default is 2 dB)

#### <2-4>

Step size (2 or 4 dB)